AUD-DTE-8X8LINE Tesira Command Sheet

For Tesira Command String blocks · Version 1.0.3

Every command the AUD-DTE-8X8LINE takes over the network, as fixed strings for Tesira Command String blocks. The unit is controlled on its own control port (TCP 8000); no other KanexPro software is needed. The same strings, with their bytes, are in `KanexPro-AUD-DTE-8X8LINE-Tesira-Command-Sheet-1.0.3.csv` for copying.

> **Before you start —** the Tesira server must reach the AUD-DTE-8X8LINE on TCP port 8000. Give the unit a fixed IP address (or a DHCP reservation).

TABLE OF CONTENTS

1. Connection
2. Using the strings
3. Commands
4. Reading the unit back
5. Troubleshooting

1. CONNECTION

HOW THE UNIT IS CONTROLLED	
Transport	TCP, port 8000 (the unit's control port)
Line ending	CR LF (hex `0D 0A`), after every string
Pacing	One string at a time. The unit answers within about 1.5 s; wait for the answer before the next string.
A refused string	The unit answers with an error line.

2. USING THE STRINGS

1. Point the Command String block at the unit's IP address, TCP port 8000.
2. Add one command per row of section 3: its string, then the line ending (hex `0D 0A`).
3. Wire each command to the control that should send it. The Bytes column is the whole string as it goes on the wire, to compare with a network capture.

Settings that only the unit's own web page has (its network, logins and firmware) stay on that page.

3. COMMANDS

991 strings, and a template for each level with more values than fit a list.

#	Command	String	Bytes (hex, with the line ending)
1	**Outputs: Line out 1: Gain (dB) = {level} (-60 to 12)**	`set output 1 gain {level}`	`the level in place of {level}`
2	**Outputs: Line out 1: Gain (dB) = -60**	`set output 1 gain -60`	`73 65 74 20 6F 75 74 70 75 74 20 31 20 67 61 69 6E 20 2D 36 30 0D 0A`
3	**Outputs: Line out 1: Gain (dB) = -24**	`set output 1 gain -24`	`73 65 74 20 6F 75 74 70 75 74 20 31 20 67 61 69 6E 20 2D 32 34 0D 0A`
4	**Outputs: Line out 1: Gain (dB) = 12**	`set output 1 gain 12`	`73 65 74 20 6F 75 74 70 75 74 20 31 20 67 61 69 6E 20 31 32 0D 0A`
5	**Outputs: Line out 2: Gain (dB) = {level} (-60 to 12)**	`set output 2 gain {level}`	`the level in place of {level}`
6	**Outputs: Line out 2: Gain (dB) = -60**	`set output 2 gain -60`	`73 65 74 20 6F 75 74 70 75 74 20 32 20 67 61 69 6E 20 2D 36 30 0D 0A`

7	Outputs: Line out 2: Gain (dB) = -24	set output 2 gain -24	73 65 74 20 6F 75 74 70 75 74 20 32 20 67 61 69 6E 20 2D 32 34 0D 0A
8	Outputs: Line out 2: Gain (dB) = 12	set output 2 gain 12	73 65 74 20 6F 75 74 70 75 74 20 32 20 67 61 69 6E 20 31 32 0D 0A
9	Outputs: Line out 3: Gain (dB) = {level} (-60 to 12)	set output 3 gain {level}	the level in place of {level}
10	Outputs: Line out 3: Gain (dB) = -60	set output 3 gain -60	73 65 74 20 6F 75 74 70 75 74 20 33 20 67 61 69 6E 20 2D 36 30 0D 0A
11	Outputs: Line out 3: Gain (dB) = -24	set output 3 gain -24	73 65 74 20 6F 75 74 70 75 74 20 33 20 67 61 69 6E 20 2D 32 34 0D 0A
12	Outputs: Line out 3: Gain (dB) = 12	set output 3 gain 12	73 65 74 20 6F 75 74 70 75 74 20 33 20 67 61 69 6E 20 31 32 0D 0A
13	Outputs: Line out 4: Gain (dB) = {level} (-60 to 12)	set output 4 gain {level}	the level in place of {level}
14	Outputs: Line out 4: Gain (dB) = -60	set output 4 gain -60	73 65 74 20 6F 75 74 70 75 74 20 34 20 67 61 69 6E 20 2D 36 30 0D 0A
15	Outputs: Line out 4: Gain (dB) = -24	set output 4 gain -24	73 65 74 20 6F 75 74 70 75 74 20 34 20 67 61 69 6E 20 2D 32 34 0D 0A
16	Outputs: Line out 4: Gain (dB) = 12	set output 4 gain 12	73 65 74 20 6F 75 74 70 75 74 20 34 20 67 61 69 6E 20 31 32 0D 0A
17	Outputs: Line out 5: Gain (dB) = {level} (-60 to 12)	set output 5 gain {level}	the level in place of {level}
18	Outputs: Line out 5: Gain (dB) = -60	set output 5 gain -60	73 65 74 20 6F 75 74 70 75 74 20 35 20 67 61 69 6E 20 2D 36 30 0D 0A
19	Outputs: Line out 5: Gain (dB) = -24	set output 5 gain -24	73 65 74 20 6F 75 74 70 75 74 20 35 20 67 61 69 6E 20 2D 32 34 0D 0A
20	Outputs: Line out 5: Gain (dB) = 12	set output 5 gain 12	73 65 74 20 6F 75 74 70 75 74 20 35 20 67 61 69 6E 20 31 32 0D 0A
21	Outputs: Line out 6: Gain (dB) = {level} (-60 to 12)	set output 6 gain {level}	the level in place of {level}
22	Outputs: Line out 6: Gain (dB) = -60	set output 6 gain -60	73 65 74 20 6F 75 74 70 75 74 20 36 20 67 61 69 6E 20 2D 36 30 0D 0A
23	Outputs: Line out 6: Gain (dB) = -24	set output 6 gain -24	73 65 74 20 6F 75 74 70 75 74 20 36 20 67 61 69 6E 20 2D 32 34 0D 0A
24	Outputs: Line out 6: Gain (dB) = 12	set output 6 gain 12	73 65 74 20 6F 75 74 70 75 74 20 36 20 67 61 69 6E 20 31 32 0D 0A
25	Outputs: Line out 7: Gain (dB) = {level} (-60 to 12)	set output 7 gain {level}	the level in place of {level}
26	Outputs: Line out 7: Gain (dB) = -60	set output 7 gain -60	73 65 74 20 6F 75 74 70 75 74 20 37 20 67 61 69 6E 20 2D 36 30 0D 0A
27	Outputs: Line out 7: Gain (dB) = -24	set output 7 gain -24	73 65 74 20 6F 75 74 70 75 74 20 37 20 67 61 69 6E 20 2D 32 34 0D 0A
28	Outputs: Line out 7: Gain (dB) = 12	set output 7 gain 12	73 65 74 20 6F 75 74 70 75 74 20 37 20 67 61 69 6E 20 31 32 0D 0A
29	Outputs: Line out 8: Gain (dB) = {level} (-60 to 12)	set output 8 gain {level}	the level in place of {level}
30	Outputs: Line out 8: Gain (dB) = -60	set output 8 gain -60	73 65 74 20 6F 75 74 70 75 74 20 38 20 67 61 69 6E 20 2D 36 30 0D 0A

31	Outputs: Line out 8: Gain (dB) = -24	`set output 8 gain -24`	`73 65 74 20 6F 75 74 70 75 74 20 38 20 67 61 69 6E 20 2D 32 34 0D 0A`
32	Outputs: Line out 8: Gain (dB) = 12	`set output 8 gain 12`	`73 65 74 20 6F 75 74 70 75 74 20 38 20 67 61 69 6E 20 31 32 0D 0A`
33	Outputs: Line out 1: Mute on	`set output 1 mute on`	`73 65 74 20 6F 75 74 70 75 74 20 31 20 6D 75 74 65 20 6F 6E 0D 0A`
34	Outputs: Line out 1: Mute off	`set output 1 mute off`	`73 65 74 20 6F 75 74 70 75 74 20 31 20 6D 75 74 65 20 6F 66 66 0D 0A`
35	Outputs: Line out 2: Mute on	`set output 2 mute on`	`73 65 74 20 6F 75 74 70 75 74 20 32 20 6D 75 74 65 20 6F 6E 0D 0A`
36	Outputs: Line out 2: Mute off	`set output 2 mute off`	`73 65 74 20 6F 75 74 70 75 74 20 32 20 6D 75 74 65 20 6F 66 66 0D 0A`
37	Outputs: Line out 3: Mute on	`set output 3 mute on`	`73 65 74 20 6F 75 74 70 75 74 20 33 20 6D 75 74 65 20 6F 6E 0D 0A`
38	Outputs: Line out 3: Mute off	`set output 3 mute off`	`73 65 74 20 6F 75 74 70 75 74 20 33 20 6D 75 74 65 20 6F 66 66 0D 0A`
39	Outputs: Line out 4: Mute on	`set output 4 mute on`	`73 65 74 20 6F 75 74 70 75 74 20 34 20 6D 75 74 65 20 6F 6E 0D 0A`
40	Outputs: Line out 4: Mute off	`set output 4 mute off`	`73 65 74 20 6F 75 74 70 75 74 20 34 20 6D 75 74 65 20 6F 66 66 0D 0A`
41	Outputs: Line out 5: Mute on	`set output 5 mute on`	`73 65 74 20 6F 75 74 70 75 74 20 35 20 6D 75 74 65 20 6F 6E 0D 0A`
42	Outputs: Line out 5: Mute off	`set output 5 mute off`	`73 65 74 20 6F 75 74 70 75 74 20 35 20 6D 75 74 65 20 6F 66 66 0D 0A`
43	Outputs: Line out 6: Mute on	`set output 6 mute on`	`73 65 74 20 6F 75 74 70 75 74 20 36 20 6D 75 74 65 20 6F 6E 0D 0A`
44	Outputs: Line out 6: Mute off	`set output 6 mute off`	`73 65 74 20 6F 75 74 70 75 74 20 36 20 6D 75 74 65 20 6F 66 66 0D 0A`
45	Outputs: Line out 7: Mute on	`set output 7 mute on`	`73 65 74 20 6F 75 74 70 75 74 20 37 20 6D 75 74 65 20 6F 6E 0D 0A`
46	Outputs: Line out 7: Mute off	`set output 7 mute off`	`73 65 74 20 6F 75 74 70 75 74 20 37 20 6D 75 74 65 20 6F 66 66 0D 0A`
47	Outputs: Line out 8: Mute on	`set output 8 mute on`	`73 65 74 20 6F 75 74 70 75 74 20 38 20 6D 75 74 65 20 6F 6E 0D 0A`
48	Outputs: Line out 8: Mute off	`set output 8 mute off`	`73 65 74 20 6F 75 74 70 75 74 20 38 20 6D 75 74 65 20 6F 66 66 0D 0A`
49	Outputs: Line out 1: Delay (ms) = 0	`set output 1 delay 0`	`73 65 74 20 6F 75 74 70 75 74 20 31 20 64 65 6C 61 79 20 30 0D 0A`
50	Outputs: Line out 1: Delay (ms) = 1	`set output 1 delay 1`	`73 65 74 20 6F 75 74 70 75 74 20 31 20 64 65 6C 61 79 20 31 0D 0A`
51	Outputs: Line out 1: Delay (ms) = 2	`set output 1 delay 2`	`73 65 74 20 6F 75 74 70 75 74 20 31 20 64 65 6C 61 79 20 32 0D 0A`
52	Outputs: Line out 1: Delay (ms) = 3	`set output 1 delay 3`	`73 65 74 20 6F 75 74 70 75 74 20 31 20 64 65 6C 61 79 20 33 0D 0A`
53	Outputs: Line out 1: Delay (ms) = 4	`set output 1 delay 4`	`73 65 74 20 6F 75 74 70 75 74 20 31 20 64 65 6C 61 79 20 34 0D 0A`
54	Outputs: Line out 1: Delay (ms) = 5	`set output 1 delay 5`	`73 65 74 20 6F 75 74 70 75 74 20 31 20 64 65 6C 61 79 20 35 0D 0A`

55	Outputs: Line out 1: Delay (ms) = 6	set output 1 delay 6	73 65 74 20 6F 75 74 70 75 74 20 31 20 64 6 5 6C 61 79 20 36 0D 0A
56	Outputs: Line out 1: Delay (ms) = 7	set output 1 delay 7	73 65 74 20 6F 75 74 70 75 74 20 31 20 64 6 5 6C 61 79 20 37 0D 0A
57	Outputs: Line out 1: Delay (ms) = 8	set output 1 delay 8	73 65 74 20 6F 75 74 70 75 74 20 31 20 64 6 5 6C 61 79 20 38 0D 0A
58	Outputs: Line out 1: Delay (ms) = 9	set output 1 delay 9	73 65 74 20 6F 75 74 70 75 74 20 31 20 64 6 5 6C 61 79 20 39 0D 0A
59	Outputs: Line out 1: Delay (ms) = 10	set output 1 delay 1 0	73 65 74 20 6F 75 74 70 75 74 20 31 20 64 6 5 6C 61 79 20 31 30 0D 0A
60	Outputs: Line out 1: Delay (ms) = 11	set output 1 delay 1 1	73 65 74 20 6F 75 74 70 75 74 20 31 20 64 6 5 6C 61 79 20 31 31 0D 0A
61	Outputs: Line out 1: Delay (ms) = 12	set output 1 delay 1 2	73 65 74 20 6F 75 74 70 75 74 20 31 20 64 6 5 6C 61 79 20 31 32 0D 0A
62	Outputs: Line out 1: Delay (ms) = 13	set output 1 delay 1 3	73 65 74 20 6F 75 74 70 75 74 20 31 20 64 6 5 6C 61 79 20 31 33 0D 0A
63	Outputs: Line out 1: Delay (ms) = 14	set output 1 delay 1 4	73 65 74 20 6F 75 74 70 75 74 20 31 20 64 6 5 6C 61 79 20 31 34 0D 0A
64	Outputs: Line out 1: Delay (ms) = 15	set output 1 delay 1 5	73 65 74 20 6F 75 74 70 75 74 20 31 20 64 6 5 6C 61 79 20 31 35 0D 0A
65	Outputs: Line out 1: Delay (ms) = 16	set output 1 delay 1 6	73 65 74 20 6F 75 74 70 75 74 20 31 20 64 6 5 6C 61 79 20 31 36 0D 0A
66	Outputs: Line out 1: Delay (ms) = 17	set output 1 delay 1 7	73 65 74 20 6F 75 74 70 75 74 20 31 20 64 6 5 6C 61 79 20 31 37 0D 0A
67	Outputs: Line out 1: Delay (ms) = 18	set output 1 delay 1 8	73 65 74 20 6F 75 74 70 75 74 20 31 20 64 6 5 6C 61 79 20 31 38 0D 0A
68	Outputs: Line out 1: Delay (ms) = 19	set output 1 delay 1 9	73 65 74 20 6F 75 74 70 75 74 20 31 20 64 6 5 6C 61 79 20 31 39 0D 0A
69	Outputs: Line out 1: Delay (ms) = 20	set output 1 delay 2 0	73 65 74 20 6F 75 74 70 75 74 20 31 20 64 6 5 6C 61 79 20 32 30 0D 0A
70	Outputs: Line out 1: Delay (ms) = 21	set output 1 delay 2 1	73 65 74 20 6F 75 74 70 75 74 20 31 20 64 6 5 6C 61 79 20 32 31 0D 0A
71	Outputs: Line out 1: Delay (ms) = 22	set output 1 delay 2 2	73 65 74 20 6F 75 74 70 75 74 20 31 20 64 6 5 6C 61 79 20 32 32 0D 0A
72	Outputs: Line out 1: Delay (ms) = 23	set output 1 delay 2 3	73 65 74 20 6F 75 74 70 75 74 20 31 20 64 6 5 6C 61 79 20 32 33 0D 0A
73	Outputs: Line out 1: Delay (ms) = 24	set output 1 delay 2 4	73 65 74 20 6F 75 74 70 75 74 20 31 20 64 6 5 6C 61 79 20 32 34 0D 0A
74	Outputs: Line out 1: Delay (ms) = 25	set output 1 delay 2 5	73 65 74 20 6F 75 74 70 75 74 20 31 20 64 6 5 6C 61 79 20 32 35 0D 0A
75	Outputs: Line out 1: Delay (ms) = 26	set output 1 delay 2 6	73 65 74 20 6F 75 74 70 75 74 20 31 20 64 6 5 6C 61 79 20 32 36 0D 0A
76	Outputs: Line out 1: Delay (ms) = 27	set output 1 delay 2 7	73 65 74 20 6F 75 74 70 75 74 20 31 20 64 6 5 6C 61 79 20 32 37 0D 0A
77	Outputs: Line out 1: Delay (ms) = 28	set output 1 delay 2 8	73 65 74 20 6F 75 74 70 75 74 20 31 20 64 6 5 6C 61 79 20 32 38 0D 0A
78	Outputs: Line out 1: Delay (ms) = 29	set output 1 delay 2 9	73 65 74 20 6F 75 74 70 75 74 20 31 20 64 6 5 6C 61 79 20 32 39 0D 0A

79	Outputs: Line out 1: Delay (ms) = 30	set output 1 delay 30	73 65 74 20 6F 75 74 70 75 74 20 31 20 64 65 6C 61 79 20 33 30 0D 0A
80	Outputs: Line out 1: Delay (ms) = 31	set output 1 delay 31	73 65 74 20 6F 75 74 70 75 74 20 31 20 64 65 6C 61 79 20 33 31 0D 0A
81	Outputs: Line out 1: Delay (ms) = 32	set output 1 delay 32	73 65 74 20 6F 75 74 70 75 74 20 31 20 64 65 6C 61 79 20 33 32 0D 0A
82	Outputs: Line out 1: Delay (ms) = 33	set output 1 delay 33	73 65 74 20 6F 75 74 70 75 74 20 31 20 64 65 6C 61 79 20 33 33 0D 0A
83	Outputs: Line out 1: Delay (ms) = 34	set output 1 delay 34	73 65 74 20 6F 75 74 70 75 74 20 31 20 64 65 6C 61 79 20 33 34 0D 0A
84	Outputs: Line out 1: Delay (ms) = 35	set output 1 delay 35	73 65 74 20 6F 75 74 70 75 74 20 31 20 64 65 6C 61 79 20 33 35 0D 0A
85	Outputs: Line out 1: Delay (ms) = 36	set output 1 delay 36	73 65 74 20 6F 75 74 70 75 74 20 31 20 64 65 6C 61 79 20 33 36 0D 0A
86	Outputs: Line out 1: Delay (ms) = 37	set output 1 delay 37	73 65 74 20 6F 75 74 70 75 74 20 31 20 64 65 6C 61 79 20 33 37 0D 0A
87	Outputs: Line out 1: Delay (ms) = 38	set output 1 delay 38	73 65 74 20 6F 75 74 70 75 74 20 31 20 64 65 6C 61 79 20 33 38 0D 0A
88	Outputs: Line out 1: Delay (ms) = 39	set output 1 delay 39	73 65 74 20 6F 75 74 70 75 74 20 31 20 64 65 6C 61 79 20 33 39 0D 0A
89	Outputs: Line out 1: Delay (ms) = 40	set output 1 delay 40	73 65 74 20 6F 75 74 70 75 74 20 31 20 64 65 6C 61 79 20 34 30 0D 0A
90	Outputs: Line out 2: Delay (ms) = 0	set output 2 delay 0	73 65 74 20 6F 75 74 70 75 74 20 32 20 64 65 6C 61 79 20 30 0D 0A
91	Outputs: Line out 2: Delay (ms) = 1	set output 2 delay 1	73 65 74 20 6F 75 74 70 75 74 20 32 20 64 65 6C 61 79 20 31 0D 0A
92	Outputs: Line out 2: Delay (ms) = 2	set output 2 delay 2	73 65 74 20 6F 75 74 70 75 74 20 32 20 64 65 6C 61 79 20 32 0D 0A
93	Outputs: Line out 2: Delay (ms) = 3	set output 2 delay 3	73 65 74 20 6F 75 74 70 75 74 20 32 20 64 65 6C 61 79 20 33 0D 0A
94	Outputs: Line out 2: Delay (ms) = 4	set output 2 delay 4	73 65 74 20 6F 75 74 70 75 74 20 32 20 64 65 6C 61 79 20 34 0D 0A
95	Outputs: Line out 2: Delay (ms) = 5	set output 2 delay 5	73 65 74 20 6F 75 74 70 75 74 20 32 20 64 65 6C 61 79 20 35 0D 0A
96	Outputs: Line out 2: Delay (ms) = 6	set output 2 delay 6	73 65 74 20 6F 75 74 70 75 74 20 32 20 64 65 6C 61 79 20 36 0D 0A
97	Outputs: Line out 2: Delay (ms) = 7	set output 2 delay 7	73 65 74 20 6F 75 74 70 75 74 20 32 20 64 65 6C 61 79 20 37 0D 0A
98	Outputs: Line out 2: Delay (ms) = 8	set output 2 delay 8	73 65 74 20 6F 75 74 70 75 74 20 32 20 64 65 6C 61 79 20 38 0D 0A
99	Outputs: Line out 2: Delay (ms) = 9	set output 2 delay 9	73 65 74 20 6F 75 74 70 75 74 20 32 20 64 65 6C 61 79 20 39 0D 0A
100	Outputs: Line out 2: Delay (ms) = 10	set output 2 delay 10	73 65 74 20 6F 75 74 70 75 74 20 32 20 64 65 6C 61 79 20 31 30 0D 0A
101	Outputs: Line out 2: Delay (ms) = 11	set output 2 delay 11	73 65 74 20 6F 75 74 70 75 74 20 32 20 64 65 6C 61 79 20 31 31 0D 0A
102	Outputs: Line out 2: Delay (ms) = 12	set output 2 delay 12	73 65 74 20 6F 75 74 70 75 74 20 32 20 64 65 6C 61 79 20 31 32 0D 0A

103	Outputs: Line out 2: Delay (ms) = 13	`set output 2 delay 13`	`73 65 74 20 6F 75 74 70 75 74 20 32 20 64 65 6C 61 79 20 31 33 0D 0A`
104	Outputs: Line out 2: Delay (ms) = 14	`set output 2 delay 14`	`73 65 74 20 6F 75 74 70 75 74 20 32 20 64 65 6C 61 79 20 31 34 0D 0A`
105	Outputs: Line out 2: Delay (ms) = 15	`set output 2 delay 15`	`73 65 74 20 6F 75 74 70 75 74 20 32 20 64 65 6C 61 79 20 31 35 0D 0A`
106	Outputs: Line out 2: Delay (ms) = 16	`set output 2 delay 16`	`73 65 74 20 6F 75 74 70 75 74 20 32 20 64 65 6C 61 79 20 31 36 0D 0A`
107	Outputs: Line out 2: Delay (ms) = 17	`set output 2 delay 17`	`73 65 74 20 6F 75 74 70 75 74 20 32 20 64 65 6C 61 79 20 31 37 0D 0A`
108	Outputs: Line out 2: Delay (ms) = 18	`set output 2 delay 18`	`73 65 74 20 6F 75 74 70 75 74 20 32 20 64 65 6C 61 79 20 31 38 0D 0A`
109	Outputs: Line out 2: Delay (ms) = 19	`set output 2 delay 19`	`73 65 74 20 6F 75 74 70 75 74 20 32 20 64 65 6C 61 79 20 31 39 0D 0A`
110	Outputs: Line out 2: Delay (ms) = 20	`set output 2 delay 20`	`73 65 74 20 6F 75 74 70 75 74 20 32 20 64 65 6C 61 79 20 32 30 0D 0A`
111	Outputs: Line out 2: Delay (ms) = 21	`set output 2 delay 21`	`73 65 74 20 6F 75 74 70 75 74 20 32 20 64 65 6C 61 79 20 32 31 0D 0A`
112	Outputs: Line out 2: Delay (ms) = 22	`set output 2 delay 22`	`73 65 74 20 6F 75 74 70 75 74 20 32 20 64 65 6C 61 79 20 32 32 0D 0A`
113	Outputs: Line out 2: Delay (ms) = 23	`set output 2 delay 23`	`73 65 74 20 6F 75 74 70 75 74 20 32 20 64 65 6C 61 79 20 32 33 0D 0A`
114	Outputs: Line out 2: Delay (ms) = 24	`set output 2 delay 24`	`73 65 74 20 6F 75 74 70 75 74 20 32 20 64 65 6C 61 79 20 32 34 0D 0A`
115	Outputs: Line out 2: Delay (ms) = 25	`set output 2 delay 25`	`73 65 74 20 6F 75 74 70 75 74 20 32 20 64 65 6C 61 79 20 32 35 0D 0A`
116	Outputs: Line out 2: Delay (ms) = 26	`set output 2 delay 26`	`73 65 74 20 6F 75 74 70 75 74 20 32 20 64 65 6C 61 79 20 32 36 0D 0A`
117	Outputs: Line out 2: Delay (ms) = 27	`set output 2 delay 27`	`73 65 74 20 6F 75 74 70 75 74 20 32 20 64 65 6C 61 79 20 32 37 0D 0A`
118	Outputs: Line out 2: Delay (ms) = 28	`set output 2 delay 28`	`73 65 74 20 6F 75 74 70 75 74 20 32 20 64 65 6C 61 79 20 32 38 0D 0A`
119	Outputs: Line out 2: Delay (ms) = 29	`set output 2 delay 29`	`73 65 74 20 6F 75 74 70 75 74 20 32 20 64 65 6C 61 79 20 32 39 0D 0A`
120	Outputs: Line out 2: Delay (ms) = 30	`set output 2 delay 30`	`73 65 74 20 6F 75 74 70 75 74 20 32 20 64 65 6C 61 79 20 33 30 0D 0A`
121	Outputs: Line out 2: Delay (ms) = 31	`set output 2 delay 31`	`73 65 74 20 6F 75 74 70 75 74 20 32 20 64 65 6C 61 79 20 33 31 0D 0A`
122	Outputs: Line out 2: Delay (ms) = 32	`set output 2 delay 32`	`73 65 74 20 6F 75 74 70 75 74 20 32 20 64 65 6C 61 79 20 33 32 0D 0A`
123	Outputs: Line out 2: Delay (ms) = 33	`set output 2 delay 33`	`73 65 74 20 6F 75 74 70 75 74 20 32 20 64 65 6C 61 79 20 33 33 0D 0A`
124	Outputs: Line out 2: Delay (ms) = 34	`set output 2 delay 34`	`73 65 74 20 6F 75 74 70 75 74 20 32 20 64 65 6C 61 79 20 33 34 0D 0A`
125	Outputs: Line out 2: Delay (ms) = 35	`set output 2 delay 35`	`73 65 74 20 6F 75 74 70 75 74 20 32 20 64 65 6C 61 79 20 33 35 0D 0A`
126	Outputs: Line out 2: Delay (ms) = 36	`set output 2 delay 36`	`73 65 74 20 6F 75 74 70 75 74 20 32 20 64 65 6C 61 79 20 33 36 0D 0A`

127	Outputs: Line out 2: Delay (ms) = 37	set output 2 delay 37	73 65 74 20 6F 75 74 70 75 74 20 32 20 64 65 6C 61 79 20 33 37 0D 0A
128	Outputs: Line out 2: Delay (ms) = 38	set output 2 delay 38	73 65 74 20 6F 75 74 70 75 74 20 32 20 64 65 6C 61 79 20 33 38 0D 0A
129	Outputs: Line out 2: Delay (ms) = 39	set output 2 delay 39	73 65 74 20 6F 75 74 70 75 74 20 32 20 64 65 6C 61 79 20 33 39 0D 0A
130	Outputs: Line out 2: Delay (ms) = 40	set output 2 delay 40	73 65 74 20 6F 75 74 70 75 74 20 32 20 64 65 6C 61 79 20 34 30 0D 0A
131	Outputs: Line out 3: Delay (ms) = 0	set output 3 delay 0	73 65 74 20 6F 75 74 70 75 74 20 33 20 64 65 6C 61 79 20 30 0D 0A
132	Outputs: Line out 3: Delay (ms) = 1	set output 3 delay 1	73 65 74 20 6F 75 74 70 75 74 20 33 20 64 65 6C 61 79 20 31 0D 0A
133	Outputs: Line out 3: Delay (ms) = 2	set output 3 delay 2	73 65 74 20 6F 75 74 70 75 74 20 33 20 64 65 6C 61 79 20 32 0D 0A
134	Outputs: Line out 3: Delay (ms) = 3	set output 3 delay 3	73 65 74 20 6F 75 74 70 75 74 20 33 20 64 65 6C 61 79 20 33 0D 0A
135	Outputs: Line out 3: Delay (ms) = 4	set output 3 delay 4	73 65 74 20 6F 75 74 70 75 74 20 33 20 64 65 6C 61 79 20 34 0D 0A
136	Outputs: Line out 3: Delay (ms) = 5	set output 3 delay 5	73 65 74 20 6F 75 74 70 75 74 20 33 20 64 65 6C 61 79 20 35 0D 0A
137	Outputs: Line out 3: Delay (ms) = 6	set output 3 delay 6	73 65 74 20 6F 75 74 70 75 74 20 33 20 64 65 6C 61 79 20 36 0D 0A
138	Outputs: Line out 3: Delay (ms) = 7	set output 3 delay 7	73 65 74 20 6F 75 74 70 75 74 20 33 20 64 65 6C 61 79 20 37 0D 0A
139	Outputs: Line out 3: Delay (ms) = 8	set output 3 delay 8	73 65 74 20 6F 75 74 70 75 74 20 33 20 64 65 6C 61 79 20 38 0D 0A
140	Outputs: Line out 3: Delay (ms) = 9	set output 3 delay 9	73 65 74 20 6F 75 74 70 75 74 20 33 20 64 65 6C 61 79 20 39 0D 0A
141	Outputs: Line out 3: Delay (ms) = 10	set output 3 delay 10	73 65 74 20 6F 75 74 70 75 74 20 33 20 64 65 6C 61 79 20 31 30 0D 0A
142	Outputs: Line out 3: Delay (ms) = 11	set output 3 delay 11	73 65 74 20 6F 75 74 70 75 74 20 33 20 64 65 6C 61 79 20 31 31 0D 0A
143	Outputs: Line out 3: Delay (ms) = 12	set output 3 delay 12	73 65 74 20 6F 75 74 70 75 74 20 33 20 64 65 6C 61 79 20 31 32 0D 0A
144	Outputs: Line out 3: Delay (ms) = 13	set output 3 delay 13	73 65 74 20 6F 75 74 70 75 74 20 33 20 64 65 6C 61 79 20 31 33 0D 0A
145	Outputs: Line out 3: Delay (ms) = 14	set output 3 delay 14	73 65 74 20 6F 75 74 70 75 74 20 33 20 64 65 6C 61 79 20 31 34 0D 0A
146	Outputs: Line out 3: Delay (ms) = 15	set output 3 delay 15	73 65 74 20 6F 75 74 70 75 74 20 33 20 64 65 6C 61 79 20 31 35 0D 0A
147	Outputs: Line out 3: Delay (ms) = 16	set output 3 delay 16	73 65 74 20 6F 75 74 70 75 74 20 33 20 64 65 6C 61 79 20 31 36 0D 0A
148	Outputs: Line out 3: Delay (ms) = 17	set output 3 delay 17	73 65 74 20 6F 75 74 70 75 74 20 33 20 64 65 6C 61 79 20 31 37 0D 0A
149	Outputs: Line out 3: Delay (ms) = 18	set output 3 delay 18	73 65 74 20 6F 75 74 70 75 74 20 33 20 64 65 6C 61 79 20 31 38 0D 0A
150	Outputs: Line out 3: Delay (ms) = 19	set output 3 delay 19	73 65 74 20 6F 75 74 70 75 74 20 33 20 64 65 6C 61 79 20 31 39 0D 0A

151	Outputs: Line out 3: Delay (ms) = 20	set output 3 delay 20	73 65 74 20 6F 75 74 70 75 74 20 33 20 64 65 6C 61 79 20 32 30 0D 0A
152	Outputs: Line out 3: Delay (ms) = 21	set output 3 delay 21	73 65 74 20 6F 75 74 70 75 74 20 33 20 64 65 6C 61 79 20 32 31 0D 0A
153	Outputs: Line out 3: Delay (ms) = 22	set output 3 delay 22	73 65 74 20 6F 75 74 70 75 74 20 33 20 64 65 6C 61 79 20 32 32 0D 0A
154	Outputs: Line out 3: Delay (ms) = 23	set output 3 delay 23	73 65 74 20 6F 75 74 70 75 74 20 33 20 64 65 6C 61 79 20 32 33 0D 0A
155	Outputs: Line out 3: Delay (ms) = 24	set output 3 delay 24	73 65 74 20 6F 75 74 70 75 74 20 33 20 64 65 6C 61 79 20 32 34 0D 0A
156	Outputs: Line out 3: Delay (ms) = 25	set output 3 delay 25	73 65 74 20 6F 75 74 70 75 74 20 33 20 64 65 6C 61 79 20 32 35 0D 0A
157	Outputs: Line out 3: Delay (ms) = 26	set output 3 delay 26	73 65 74 20 6F 75 74 70 75 74 20 33 20 64 65 6C 61 79 20 32 36 0D 0A
158	Outputs: Line out 3: Delay (ms) = 27	set output 3 delay 27	73 65 74 20 6F 75 74 70 75 74 20 33 20 64 65 6C 61 79 20 32 37 0D 0A
159	Outputs: Line out 3: Delay (ms) = 28	set output 3 delay 28	73 65 74 20 6F 75 74 70 75 74 20 33 20 64 65 6C 61 79 20 32 38 0D 0A
160	Outputs: Line out 3: Delay (ms) = 29	set output 3 delay 29	73 65 74 20 6F 75 74 70 75 74 20 33 20 64 65 6C 61 79 20 32 39 0D 0A
161	Outputs: Line out 3: Delay (ms) = 30	set output 3 delay 30	73 65 74 20 6F 75 74 70 75 74 20 33 20 64 65 6C 61 79 20 33 30 0D 0A
162	Outputs: Line out 3: Delay (ms) = 31	set output 3 delay 31	73 65 74 20 6F 75 74 70 75 74 20 33 20 64 65 6C 61 79 20 33 31 0D 0A
163	Outputs: Line out 3: Delay (ms) = 32	set output 3 delay 32	73 65 74 20 6F 75 74 70 75 74 20 33 20 64 65 6C 61 79 20 33 32 0D 0A
164	Outputs: Line out 3: Delay (ms) = 33	set output 3 delay 33	73 65 74 20 6F 75 74 70 75 74 20 33 20 64 65 6C 61 79 20 33 33 0D 0A
165	Outputs: Line out 3: Delay (ms) = 34	set output 3 delay 34	73 65 74 20 6F 75 74 70 75 74 20 33 20 64 65 6C 61 79 20 33 34 0D 0A
166	Outputs: Line out 3: Delay (ms) = 35	set output 3 delay 35	73 65 74 20 6F 75 74 70 75 74 20 33 20 64 65 6C 61 79 20 33 35 0D 0A
167	Outputs: Line out 3: Delay (ms) = 36	set output 3 delay 36	73 65 74 20 6F 75 74 70 75 74 20 33 20 64 65 6C 61 79 20 33 36 0D 0A
168	Outputs: Line out 3: Delay (ms) = 37	set output 3 delay 37	73 65 74 20 6F 75 74 70 75 74 20 33 20 64 65 6C 61 79 20 33 37 0D 0A
169	Outputs: Line out 3: Delay (ms) = 38	set output 3 delay 38	73 65 74 20 6F 75 74 70 75 74 20 33 20 64 65 6C 61 79 20 33 38 0D 0A
170	Outputs: Line out 3: Delay (ms) = 39	set output 3 delay 39	73 65 74 20 6F 75 74 70 75 74 20 33 20 64 65 6C 61 79 20 33 39 0D 0A
171	Outputs: Line out 3: Delay (ms) = 40	set output 3 delay 40	73 65 74 20 6F 75 74 70 75 74 20 33 20 64 65 6C 61 79 20 34 30 0D 0A
172	Outputs: Line out 4: Delay (ms) = 0	set output 4 delay 0	73 65 74 20 6F 75 74 70 75 74 20 34 20 64 65 6C 61 79 20 30 0D 0A
173	Outputs: Line out 4: Delay (ms) = 1	set output 4 delay 1	73 65 74 20 6F 75 74 70 75 74 20 34 20 64 65 6C 61 79 20 31 0D 0A
174	Outputs: Line out 4: Delay (ms) = 2	set output 4 delay 2	73 65 74 20 6F 75 74 70 75 74 20 34 20 64 65 6C 61 79 20 32 0D 0A

175	Outputs: Line out 4: Delay (ms) = 3	set output 4 delay 3	73 65 74 20 6F 75 74 70 75 74 20 34 20 64 6 5 6C 61 79 20 33 0D 0A
176	Outputs: Line out 4: Delay (ms) = 4	set output 4 delay 4	73 65 74 20 6F 75 74 70 75 74 20 34 20 64 6 5 6C 61 79 20 34 0D 0A
177	Outputs: Line out 4: Delay (ms) = 5	set output 4 delay 5	73 65 74 20 6F 75 74 70 75 74 20 34 20 64 6 5 6C 61 79 20 35 0D 0A
178	Outputs: Line out 4: Delay (ms) = 6	set output 4 delay 6	73 65 74 20 6F 75 74 70 75 74 20 34 20 64 6 5 6C 61 79 20 36 0D 0A
179	Outputs: Line out 4: Delay (ms) = 7	set output 4 delay 7	73 65 74 20 6F 75 74 70 75 74 20 34 20 64 6 5 6C 61 79 20 37 0D 0A
180	Outputs: Line out 4: Delay (ms) = 8	set output 4 delay 8	73 65 74 20 6F 75 74 70 75 74 20 34 20 64 6 5 6C 61 79 20 38 0D 0A
181	Outputs: Line out 4: Delay (ms) = 9	set output 4 delay 9	73 65 74 20 6F 75 74 70 75 74 20 34 20 64 6 5 6C 61 79 20 39 0D 0A
182	Outputs: Line out 4: Delay (ms) = 10	set output 4 delay 1 0	73 65 74 20 6F 75 74 70 75 74 20 34 20 64 6 5 6C 61 79 20 31 30 0D 0A
183	Outputs: Line out 4: Delay (ms) = 11	set output 4 delay 1 1	73 65 74 20 6F 75 74 70 75 74 20 34 20 64 6 5 6C 61 79 20 31 31 0D 0A
184	Outputs: Line out 4: Delay (ms) = 12	set output 4 delay 1 2	73 65 74 20 6F 75 74 70 75 74 20 34 20 64 6 5 6C 61 79 20 31 32 0D 0A
185	Outputs: Line out 4: Delay (ms) = 13	set output 4 delay 1 3	73 65 74 20 6F 75 74 70 75 74 20 34 20 64 6 5 6C 61 79 20 31 33 0D 0A
186	Outputs: Line out 4: Delay (ms) = 14	set output 4 delay 1 4	73 65 74 20 6F 75 74 70 75 74 20 34 20 64 6 5 6C 61 79 20 31 34 0D 0A
187	Outputs: Line out 4: Delay (ms) = 15	set output 4 delay 1 5	73 65 74 20 6F 75 74 70 75 74 20 34 20 64 6 5 6C 61 79 20 31 35 0D 0A
188	Outputs: Line out 4: Delay (ms) = 16	set output 4 delay 1 6	73 65 74 20 6F 75 74 70 75 74 20 34 20 64 6 5 6C 61 79 20 31 36 0D 0A
189	Outputs: Line out 4: Delay (ms) = 17	set output 4 delay 1 7	73 65 74 20 6F 75 74 70 75 74 20 34 20 64 6 5 6C 61 79 20 31 37 0D 0A
190	Outputs: Line out 4: Delay (ms) = 18	set output 4 delay 1 8	73 65 74 20 6F 75 74 70 75 74 20 34 20 64 6 5 6C 61 79 20 31 38 0D 0A
191	Outputs: Line out 4: Delay (ms) = 19	set output 4 delay 1 9	73 65 74 20 6F 75 74 70 75 74 20 34 20 64 6 5 6C 61 79 20 31 39 0D 0A
192	Outputs: Line out 4: Delay (ms) = 20	set output 4 delay 2 0	73 65 74 20 6F 75 74 70 75 74 20 34 20 64 6 5 6C 61 79 20 32 30 0D 0A
193	Outputs: Line out 4: Delay (ms) = 21	set output 4 delay 2 1	73 65 74 20 6F 75 74 70 75 74 20 34 20 64 6 5 6C 61 79 20 32 31 0D 0A
194	Outputs: Line out 4: Delay (ms) = 22	set output 4 delay 2 2	73 65 74 20 6F 75 74 70 75 74 20 34 20 64 6 5 6C 61 79 20 32 32 0D 0A
195	Outputs: Line out 4: Delay (ms) = 23	set output 4 delay 2 3	73 65 74 20 6F 75 74 70 75 74 20 34 20 64 6 5 6C 61 79 20 32 33 0D 0A
196	Outputs: Line out 4: Delay (ms) = 24	set output 4 delay 2 4	73 65 74 20 6F 75 74 70 75 74 20 34 20 64 6 5 6C 61 79 20 32 34 0D 0A
197	Outputs: Line out 4: Delay (ms) = 25	set output 4 delay 2 5	73 65 74 20 6F 75 74 70 75 74 20 34 20 64 6 5 6C 61 79 20 32 35 0D 0A
198	Outputs: Line out 4: Delay (ms) = 26	set output 4 delay 2 6	73 65 74 20 6F 75 74 70 75 74 20 34 20 64 6 5 6C 61 79 20 32 36 0D 0A

199	Outputs: Line out 4: Delay (ms) = 27	set output 4 delay 27	73 65 74 20 6F 75 74 70 75 74 20 34 20 64 65 6C 61 79 20 32 37 0D 0A
200	Outputs: Line out 4: Delay (ms) = 28	set output 4 delay 28	73 65 74 20 6F 75 74 70 75 74 20 34 20 64 65 6C 61 79 20 32 38 0D 0A
201	Outputs: Line out 4: Delay (ms) = 29	set output 4 delay 29	73 65 74 20 6F 75 74 70 75 74 20 34 20 64 65 6C 61 79 20 32 39 0D 0A
202	Outputs: Line out 4: Delay (ms) = 30	set output 4 delay 30	73 65 74 20 6F 75 74 70 75 74 20 34 20 64 65 6C 61 79 20 33 30 0D 0A
203	Outputs: Line out 4: Delay (ms) = 31	set output 4 delay 31	73 65 74 20 6F 75 74 70 75 74 20 34 20 64 65 6C 61 79 20 33 31 0D 0A
204	Outputs: Line out 4: Delay (ms) = 32	set output 4 delay 32	73 65 74 20 6F 75 74 70 75 74 20 34 20 64 65 6C 61 79 20 33 32 0D 0A
205	Outputs: Line out 4: Delay (ms) = 33	set output 4 delay 33	73 65 74 20 6F 75 74 70 75 74 20 34 20 64 65 6C 61 79 20 33 33 0D 0A
206	Outputs: Line out 4: Delay (ms) = 34	set output 4 delay 34	73 65 74 20 6F 75 74 70 75 74 20 34 20 64 65 6C 61 79 20 33 34 0D 0A
207	Outputs: Line out 4: Delay (ms) = 35	set output 4 delay 35	73 65 74 20 6F 75 74 70 75 74 20 34 20 64 65 6C 61 79 20 33 35 0D 0A
208	Outputs: Line out 4: Delay (ms) = 36	set output 4 delay 36	73 65 74 20 6F 75 74 70 75 74 20 34 20 64 65 6C 61 79 20 33 36 0D 0A
209	Outputs: Line out 4: Delay (ms) = 37	set output 4 delay 37	73 65 74 20 6F 75 74 70 75 74 20 34 20 64 65 6C 61 79 20 33 37 0D 0A
210	Outputs: Line out 4: Delay (ms) = 38	set output 4 delay 38	73 65 74 20 6F 75 74 70 75 74 20 34 20 64 65 6C 61 79 20 33 38 0D 0A
211	Outputs: Line out 4: Delay (ms) = 39	set output 4 delay 39	73 65 74 20 6F 75 74 70 75 74 20 34 20 64 65 6C 61 79 20 33 39 0D 0A
212	Outputs: Line out 4: Delay (ms) = 40	set output 4 delay 40	73 65 74 20 6F 75 74 70 75 74 20 34 20 64 65 6C 61 79 20 34 30 0D 0A
213	Outputs: Line out 5: Delay (ms) = 0	set output 5 delay 0	73 65 74 20 6F 75 74 70 75 74 20 35 20 64 65 6C 61 79 20 30 0D 0A
214	Outputs: Line out 5: Delay (ms) = 1	set output 5 delay 1	73 65 74 20 6F 75 74 70 75 74 20 35 20 64 65 6C 61 79 20 31 0D 0A
215	Outputs: Line out 5: Delay (ms) = 2	set output 5 delay 2	73 65 74 20 6F 75 74 70 75 74 20 35 20 64 65 6C 61 79 20 32 0D 0A
216	Outputs: Line out 5: Delay (ms) = 3	set output 5 delay 3	73 65 74 20 6F 75 74 70 75 74 20 35 20 64 65 6C 61 79 20 33 0D 0A
217	Outputs: Line out 5: Delay (ms) = 4	set output 5 delay 4	73 65 74 20 6F 75 74 70 75 74 20 35 20 64 65 6C 61 79 20 34 0D 0A
218	Outputs: Line out 5: Delay (ms) = 5	set output 5 delay 5	73 65 74 20 6F 75 74 70 75 74 20 35 20 64 65 6C 61 79 20 35 0D 0A
219	Outputs: Line out 5: Delay (ms) = 6	set output 5 delay 6	73 65 74 20 6F 75 74 70 75 74 20 35 20 64 65 6C 61 79 20 36 0D 0A
220	Outputs: Line out 5: Delay (ms) = 7	set output 5 delay 7	73 65 74 20 6F 75 74 70 75 74 20 35 20 64 65 6C 61 79 20 37 0D 0A
221	Outputs: Line out 5: Delay (ms) = 8	set output 5 delay 8	73 65 74 20 6F 75 74 70 75 74 20 35 20 64 65 6C 61 79 20 38 0D 0A
222	Outputs: Line out 5: Delay (ms) = 9	set output 5 delay 9	73 65 74 20 6F 75 74 70 75 74 20 35 20 64 65 6C 61 79 20 39 0D 0A

223	Outputs: Line out 5: Delay (ms) = 10	set output 5 delay 10	73 65 74 20 6F 75 74 70 75 74 20 35 20 64 65 6C 61 79 20 31 30 0D 0A
224	Outputs: Line out 5: Delay (ms) = 11	set output 5 delay 11	73 65 74 20 6F 75 74 70 75 74 20 35 20 64 65 6C 61 79 20 31 31 0D 0A
225	Outputs: Line out 5: Delay (ms) = 12	set output 5 delay 12	73 65 74 20 6F 75 74 70 75 74 20 35 20 64 65 6C 61 79 20 31 32 0D 0A
226	Outputs: Line out 5: Delay (ms) = 13	set output 5 delay 13	73 65 74 20 6F 75 74 70 75 74 20 35 20 64 65 6C 61 79 20 31 33 0D 0A
227	Outputs: Line out 5: Delay (ms) = 14	set output 5 delay 14	73 65 74 20 6F 75 74 70 75 74 20 35 20 64 65 6C 61 79 20 31 34 0D 0A
228	Outputs: Line out 5: Delay (ms) = 15	set output 5 delay 15	73 65 74 20 6F 75 74 70 75 74 20 35 20 64 65 6C 61 79 20 31 35 0D 0A
229	Outputs: Line out 5: Delay (ms) = 16	set output 5 delay 16	73 65 74 20 6F 75 74 70 75 74 20 35 20 64 65 6C 61 79 20 31 36 0D 0A
230	Outputs: Line out 5: Delay (ms) = 17	set output 5 delay 17	73 65 74 20 6F 75 74 70 75 74 20 35 20 64 65 6C 61 79 20 31 37 0D 0A
231	Outputs: Line out 5: Delay (ms) = 18	set output 5 delay 18	73 65 74 20 6F 75 74 70 75 74 20 35 20 64 65 6C 61 79 20 31 38 0D 0A
232	Outputs: Line out 5: Delay (ms) = 19	set output 5 delay 19	73 65 74 20 6F 75 74 70 75 74 20 35 20 64 65 6C 61 79 20 31 39 0D 0A
233	Outputs: Line out 5: Delay (ms) = 20	set output 5 delay 20	73 65 74 20 6F 75 74 70 75 74 20 35 20 64 65 6C 61 79 20 32 30 0D 0A
234	Outputs: Line out 5: Delay (ms) = 21	set output 5 delay 21	73 65 74 20 6F 75 74 70 75 74 20 35 20 64 65 6C 61 79 20 32 31 0D 0A
235	Outputs: Line out 5: Delay (ms) = 22	set output 5 delay 22	73 65 74 20 6F 75 74 70 75 74 20 35 20 64 65 6C 61 79 20 32 32 0D 0A
236	Outputs: Line out 5: Delay (ms) = 23	set output 5 delay 23	73 65 74 20 6F 75 74 70 75 74 20 35 20 64 65 6C 61 79 20 32 33 0D 0A
237	Outputs: Line out 5: Delay (ms) = 24	set output 5 delay 24	73 65 74 20 6F 75 74 70 75 74 20 35 20 64 65 6C 61 79 20 32 34 0D 0A
238	Outputs: Line out 5: Delay (ms) = 25	set output 5 delay 25	73 65 74 20 6F 75 74 70 75 74 20 35 20 64 65 6C 61 79 20 32 35 0D 0A
239	Outputs: Line out 5: Delay (ms) = 26	set output 5 delay 26	73 65 74 20 6F 75 74 70 75 74 20 35 20 64 65 6C 61 79 20 32 36 0D 0A
240	Outputs: Line out 5: Delay (ms) = 27	set output 5 delay 27	73 65 74 20 6F 75 74 70 75 74 20 35 20 64 65 6C 61 79 20 32 37 0D 0A
241	Outputs: Line out 5: Delay (ms) = 28	set output 5 delay 28	73 65 74 20 6F 75 74 70 75 74 20 35 20 64 65 6C 61 79 20 32 38 0D 0A
242	Outputs: Line out 5: Delay (ms) = 29	set output 5 delay 29	73 65 74 20 6F 75 74 70 75 74 20 35 20 64 65 6C 61 79 20 32 39 0D 0A
243	Outputs: Line out 5: Delay (ms) = 30	set output 5 delay 30	73 65 74 20 6F 75 74 70 75 74 20 35 20 64 65 6C 61 79 20 33 30 0D 0A
244	Outputs: Line out 5: Delay (ms) = 31	set output 5 delay 31	73 65 74 20 6F 75 74 70 75 74 20 35 20 64 65 6C 61 79 20 33 31 0D 0A
245	Outputs: Line out 5: Delay (ms) = 32	set output 5 delay 32	73 65 74 20 6F 75 74 70 75 74 20 35 20 64 65 6C 61 79 20 33 32 0D 0A
246	Outputs: Line out 5: Delay (ms) = 33	set output 5 delay 33	73 65 74 20 6F 75 74 70 75 74 20 35 20 64 65 6C 61 79 20 33 33 0D 0A

247	Outputs: Line out 5: Delay (ms) = 34	set output 5 delay 34	73 65 74 20 6F 75 74 70 75 74 20 35 20 64 65 6C 61 79 20 33 34 0D 0A
248	Outputs: Line out 5: Delay (ms) = 35	set output 5 delay 35	73 65 74 20 6F 75 74 70 75 74 20 35 20 64 65 6C 61 79 20 33 35 0D 0A
249	Outputs: Line out 5: Delay (ms) = 36	set output 5 delay 36	73 65 74 20 6F 75 74 70 75 74 20 35 20 64 65 6C 61 79 20 33 36 0D 0A
250	Outputs: Line out 5: Delay (ms) = 37	set output 5 delay 37	73 65 74 20 6F 75 74 70 75 74 20 35 20 64 65 6C 61 79 20 33 37 0D 0A
251	Outputs: Line out 5: Delay (ms) = 38	set output 5 delay 38	73 65 74 20 6F 75 74 70 75 74 20 35 20 64 65 6C 61 79 20 33 38 0D 0A
252	Outputs: Line out 5: Delay (ms) = 39	set output 5 delay 39	73 65 74 20 6F 75 74 70 75 74 20 35 20 64 65 6C 61 79 20 33 39 0D 0A
253	Outputs: Line out 5: Delay (ms) = 40	set output 5 delay 40	73 65 74 20 6F 75 74 70 75 74 20 35 20 64 65 6C 61 79 20 34 30 0D 0A
254	Outputs: Line out 6: Delay (ms) = 0	set output 6 delay 0	73 65 74 20 6F 75 74 70 75 74 20 36 20 64 65 6C 61 79 20 30 0D 0A
255	Outputs: Line out 6: Delay (ms) = 1	set output 6 delay 1	73 65 74 20 6F 75 74 70 75 74 20 36 20 64 65 6C 61 79 20 31 0D 0A
256	Outputs: Line out 6: Delay (ms) = 2	set output 6 delay 2	73 65 74 20 6F 75 74 70 75 74 20 36 20 64 65 6C 61 79 20 32 0D 0A
257	Outputs: Line out 6: Delay (ms) = 3	set output 6 delay 3	73 65 74 20 6F 75 74 70 75 74 20 36 20 64 65 6C 61 79 20 33 0D 0A
258	Outputs: Line out 6: Delay (ms) = 4	set output 6 delay 4	73 65 74 20 6F 75 74 70 75 74 20 36 20 64 65 6C 61 79 20 34 0D 0A
259	Outputs: Line out 6: Delay (ms) = 5	set output 6 delay 5	73 65 74 20 6F 75 74 70 75 74 20 36 20 64 65 6C 61 79 20 35 0D 0A
260	Outputs: Line out 6: Delay (ms) = 6	set output 6 delay 6	73 65 74 20 6F 75 74 70 75 74 20 36 20 64 65 6C 61 79 20 36 0D 0A
261	Outputs: Line out 6: Delay (ms) = 7	set output 6 delay 7	73 65 74 20 6F 75 74 70 75 74 20 36 20 64 65 6C 61 79 20 37 0D 0A
262	Outputs: Line out 6: Delay (ms) = 8	set output 6 delay 8	73 65 74 20 6F 75 74 70 75 74 20 36 20 64 65 6C 61 79 20 38 0D 0A
263	Outputs: Line out 6: Delay (ms) = 9	set output 6 delay 9	73 65 74 20 6F 75 74 70 75 74 20 36 20 64 65 6C 61 79 20 39 0D 0A
264	Outputs: Line out 6: Delay (ms) = 10	set output 6 delay 10	73 65 74 20 6F 75 74 70 75 74 20 36 20 64 65 6C 61 79 20 31 30 0D 0A
265	Outputs: Line out 6: Delay (ms) = 11	set output 6 delay 11	73 65 74 20 6F 75 74 70 75 74 20 36 20 64 65 6C 61 79 20 31 31 0D 0A
266	Outputs: Line out 6: Delay (ms) = 12	set output 6 delay 12	73 65 74 20 6F 75 74 70 75 74 20 36 20 64 65 6C 61 79 20 31 32 0D 0A
267	Outputs: Line out 6: Delay (ms) = 13	set output 6 delay 13	73 65 74 20 6F 75 74 70 75 74 20 36 20 64 65 6C 61 79 20 31 33 0D 0A
268	Outputs: Line out 6: Delay (ms) = 14	set output 6 delay 14	73 65 74 20 6F 75 74 70 75 74 20 36 20 64 65 6C 61 79 20 31 34 0D 0A
269	Outputs: Line out 6: Delay (ms) = 15	set output 6 delay 15	73 65 74 20 6F 75 74 70 75 74 20 36 20 64 65 6C 61 79 20 31 35 0D 0A
270	Outputs: Line out 6: Delay (ms) = 16	set output 6 delay 16	73 65 74 20 6F 75 74 70 75 74 20 36 20 64 65 6C 61 79 20 31 36 0D 0A

271	Outputs: Line out 6: Delay (ms) = 17	set output 6 delay 17	73 65 74 20 6F 75 74 70 75 74 20 36 20 64 65 6C 61 79 20 31 37 0D 0A
272	Outputs: Line out 6: Delay (ms) = 18	set output 6 delay 18	73 65 74 20 6F 75 74 70 75 74 20 36 20 64 65 6C 61 79 20 31 38 0D 0A
273	Outputs: Line out 6: Delay (ms) = 19	set output 6 delay 19	73 65 74 20 6F 75 74 70 75 74 20 36 20 64 65 6C 61 79 20 31 39 0D 0A
274	Outputs: Line out 6: Delay (ms) = 20	set output 6 delay 20	73 65 74 20 6F 75 74 70 75 74 20 36 20 64 65 6C 61 79 20 32 30 0D 0A
275	Outputs: Line out 6: Delay (ms) = 21	set output 6 delay 21	73 65 74 20 6F 75 74 70 75 74 20 36 20 64 65 6C 61 79 20 32 31 0D 0A
276	Outputs: Line out 6: Delay (ms) = 22	set output 6 delay 22	73 65 74 20 6F 75 74 70 75 74 20 36 20 64 65 6C 61 79 20 32 32 0D 0A
277	Outputs: Line out 6: Delay (ms) = 23	set output 6 delay 23	73 65 74 20 6F 75 74 70 75 74 20 36 20 64 65 6C 61 79 20 32 33 0D 0A
278	Outputs: Line out 6: Delay (ms) = 24	set output 6 delay 24	73 65 74 20 6F 75 74 70 75 74 20 36 20 64 65 6C 61 79 20 32 34 0D 0A
279	Outputs: Line out 6: Delay (ms) = 25	set output 6 delay 25	73 65 74 20 6F 75 74 70 75 74 20 36 20 64 65 6C 61 79 20 32 35 0D 0A
280	Outputs: Line out 6: Delay (ms) = 26	set output 6 delay 26	73 65 74 20 6F 75 74 70 75 74 20 36 20 64 65 6C 61 79 20 32 36 0D 0A
281	Outputs: Line out 6: Delay (ms) = 27	set output 6 delay 27	73 65 74 20 6F 75 74 70 75 74 20 36 20 64 65 6C 61 79 20 32 37 0D 0A
282	Outputs: Line out 6: Delay (ms) = 28	set output 6 delay 28	73 65 74 20 6F 75 74 70 75 74 20 36 20 64 65 6C 61 79 20 32 38 0D 0A
283	Outputs: Line out 6: Delay (ms) = 29	set output 6 delay 29	73 65 74 20 6F 75 74 70 75 74 20 36 20 64 65 6C 61 79 20 32 39 0D 0A
284	Outputs: Line out 6: Delay (ms) = 30	set output 6 delay 30	73 65 74 20 6F 75 74 70 75 74 20 36 20 64 65 6C 61 79 20 33 30 0D 0A
285	Outputs: Line out 6: Delay (ms) = 31	set output 6 delay 31	73 65 74 20 6F 75 74 70 75 74 20 36 20 64 65 6C 61 79 20 33 31 0D 0A
286	Outputs: Line out 6: Delay (ms) = 32	set output 6 delay 32	73 65 74 20 6F 75 74 70 75 74 20 36 20 64 65 6C 61 79 20 33 32 0D 0A
287	Outputs: Line out 6: Delay (ms) = 33	set output 6 delay 33	73 65 74 20 6F 75 74 70 75 74 20 36 20 64 65 6C 61 79 20 33 33 0D 0A
288	Outputs: Line out 6: Delay (ms) = 34	set output 6 delay 34	73 65 74 20 6F 75 74 70 75 74 20 36 20 64 65 6C 61 79 20 33 34 0D 0A
289	Outputs: Line out 6: Delay (ms) = 35	set output 6 delay 35	73 65 74 20 6F 75 74 70 75 74 20 36 20 64 65 6C 61 79 20 33 35 0D 0A
290	Outputs: Line out 6: Delay (ms) = 36	set output 6 delay 36	73 65 74 20 6F 75 74 70 75 74 20 36 20 64 65 6C 61 79 20 33 36 0D 0A
291	Outputs: Line out 6: Delay (ms) = 37	set output 6 delay 37	73 65 74 20 6F 75 74 70 75 74 20 36 20 64 65 6C 61 79 20 33 37 0D 0A
292	Outputs: Line out 6: Delay (ms) = 38	set output 6 delay 38	73 65 74 20 6F 75 74 70 75 74 20 36 20 64 65 6C 61 79 20 33 38 0D 0A
293	Outputs: Line out 6: Delay (ms) = 39	set output 6 delay 39	73 65 74 20 6F 75 74 70 75 74 20 36 20 64 65 6C 61 79 20 33 39 0D 0A
294	Outputs: Line out 6: Delay (ms) = 40	set output 6 delay 40	73 65 74 20 6F 75 74 70 75 74 20 36 20 64 65 6C 61 79 20 34 30 0D 0A

295	Outputs: Line out 7: Delay (ms) = 0	`set output 7 delay 0`	`73 65 74 20 6F 75 74 70 75 74 20 37 20 64 6 5 6C 61 79 20 30 0D 0A`
296	Outputs: Line out 7: Delay (ms) = 1	`set output 7 delay 1`	`73 65 74 20 6F 75 74 70 75 74 20 37 20 64 6 5 6C 61 79 20 31 0D 0A`
297	Outputs: Line out 7: Delay (ms) = 2	`set output 7 delay 2`	`73 65 74 20 6F 75 74 70 75 74 20 37 20 64 6 5 6C 61 79 20 32 0D 0A`
298	Outputs: Line out 7: Delay (ms) = 3	`set output 7 delay 3`	`73 65 74 20 6F 75 74 70 75 74 20 37 20 64 6 5 6C 61 79 20 33 0D 0A`
299	Outputs: Line out 7: Delay (ms) = 4	`set output 7 delay 4`	`73 65 74 20 6F 75 74 70 75 74 20 37 20 64 6 5 6C 61 79 20 34 0D 0A`
300	Outputs: Line out 7: Delay (ms) = 5	`set output 7 delay 5`	`73 65 74 20 6F 75 74 70 75 74 20 37 20 64 6 5 6C 61 79 20 35 0D 0A`
301	Outputs: Line out 7: Delay (ms) = 6	`set output 7 delay 6`	`73 65 74 20 6F 75 74 70 75 74 20 37 20 64 6 5 6C 61 79 20 36 0D 0A`
302	Outputs: Line out 7: Delay (ms) = 7	`set output 7 delay 7`	`73 65 74 20 6F 75 74 70 75 74 20 37 20 64 6 5 6C 61 79 20 37 0D 0A`
303	Outputs: Line out 7: Delay (ms) = 8	`set output 7 delay 8`	`73 65 74 20 6F 75 74 70 75 74 20 37 20 64 6 5 6C 61 79 20 38 0D 0A`
304	Outputs: Line out 7: Delay (ms) = 9	`set output 7 delay 9`	`73 65 74 20 6F 75 74 70 75 74 20 37 20 64 6 5 6C 61 79 20 39 0D 0A`
305	Outputs: Line out 7: Delay (ms) = 10	`set output 7 delay 1 0`	`73 65 74 20 6F 75 74 70 75 74 20 37 20 64 6 5 6C 61 79 20 31 30 0D 0A`
306	Outputs: Line out 7: Delay (ms) = 11	`set output 7 delay 1 1`	`73 65 74 20 6F 75 74 70 75 74 20 37 20 64 6 5 6C 61 79 20 31 31 0D 0A`
307	Outputs: Line out 7: Delay (ms) = 12	`set output 7 delay 1 2`	`73 65 74 20 6F 75 74 70 75 74 20 37 20 64 6 5 6C 61 79 20 31 32 0D 0A`
308	Outputs: Line out 7: Delay (ms) = 13	`set output 7 delay 1 3`	`73 65 74 20 6F 75 74 70 75 74 20 37 20 64 6 5 6C 61 79 20 31 33 0D 0A`
309	Outputs: Line out 7: Delay (ms) = 14	`set output 7 delay 1 4`	`73 65 74 20 6F 75 74 70 75 74 20 37 20 64 6 5 6C 61 79 20 31 34 0D 0A`
310	Outputs: Line out 7: Delay (ms) = 15	`set output 7 delay 1 5`	`73 65 74 20 6F 75 74 70 75 74 20 37 20 64 6 5 6C 61 79 20 31 35 0D 0A`
311	Outputs: Line out 7: Delay (ms) = 16	`set output 7 delay 1 6`	`73 65 74 20 6F 75 74 70 75 74 20 37 20 64 6 5 6C 61 79 20 31 36 0D 0A`
312	Outputs: Line out 7: Delay (ms) = 17	`set output 7 delay 1 7`	`73 65 74 20 6F 75 74 70 75 74 20 37 20 64 6 5 6C 61 79 20 31 37 0D 0A`
313	Outputs: Line out 7: Delay (ms) = 18	`set output 7 delay 1 8`	`73 65 74 20 6F 75 74 70 75 74 20 37 20 64 6 5 6C 61 79 20 31 38 0D 0A`
314	Outputs: Line out 7: Delay (ms) = 19	`set output 7 delay 1 9`	`73 65 74 20 6F 75 74 70 75 74 20 37 20 64 6 5 6C 61 79 20 31 39 0D 0A`
315	Outputs: Line out 7: Delay (ms) = 20	`set output 7 delay 2 0`	`73 65 74 20 6F 75 74 70 75 74 20 37 20 64 6 5 6C 61 79 20 32 30 0D 0A`
316	Outputs: Line out 7: Delay (ms) = 21	`set output 7 delay 2 1`	`73 65 74 20 6F 75 74 70 75 74 20 37 20 64 6 5 6C 61 79 20 32 31 0D 0A`
317	Outputs: Line out 7: Delay (ms) = 22	`set output 7 delay 2 2`	`73 65 74 20 6F 75 74 70 75 74 20 37 20 64 6 5 6C 61 79 20 32 32 0D 0A`
318	Outputs: Line out 7: Delay (ms) = 23	`set output 7 delay 2 3`	`73 65 74 20 6F 75 74 70 75 74 20 37 20 64 6 5 6C 61 79 20 32 33 0D 0A`

319	Outputs: Line out 7: Delay (ms) = 24	set output 7 delay 24	73 65 74 20 6F 75 74 70 75 74 20 37 20 64 65 6C 61 79 20 32 34 0D 0A
320	Outputs: Line out 7: Delay (ms) = 25	set output 7 delay 25	73 65 74 20 6F 75 74 70 75 74 20 37 20 64 65 6C 61 79 20 32 35 0D 0A
321	Outputs: Line out 7: Delay (ms) = 26	set output 7 delay 26	73 65 74 20 6F 75 74 70 75 74 20 37 20 64 65 6C 61 79 20 32 36 0D 0A
322	Outputs: Line out 7: Delay (ms) = 27	set output 7 delay 27	73 65 74 20 6F 75 74 70 75 74 20 37 20 64 65 6C 61 79 20 32 37 0D 0A
323	Outputs: Line out 7: Delay (ms) = 28	set output 7 delay 28	73 65 74 20 6F 75 74 70 75 74 20 37 20 64 65 6C 61 79 20 32 38 0D 0A
324	Outputs: Line out 7: Delay (ms) = 29	set output 7 delay 29	73 65 74 20 6F 75 74 70 75 74 20 37 20 64 65 6C 61 79 20 32 39 0D 0A
325	Outputs: Line out 7: Delay (ms) = 30	set output 7 delay 30	73 65 74 20 6F 75 74 70 75 74 20 37 20 64 65 6C 61 79 20 33 30 0D 0A
326	Outputs: Line out 7: Delay (ms) = 31	set output 7 delay 31	73 65 74 20 6F 75 74 70 75 74 20 37 20 64 65 6C 61 79 20 33 31 0D 0A
327	Outputs: Line out 7: Delay (ms) = 32	set output 7 delay 32	73 65 74 20 6F 75 74 70 75 74 20 37 20 64 65 6C 61 79 20 33 32 0D 0A
328	Outputs: Line out 7: Delay (ms) = 33	set output 7 delay 33	73 65 74 20 6F 75 74 70 75 74 20 37 20 64 65 6C 61 79 20 33 33 0D 0A
329	Outputs: Line out 7: Delay (ms) = 34	set output 7 delay 34	73 65 74 20 6F 75 74 70 75 74 20 37 20 64 65 6C 61 79 20 33 34 0D 0A
330	Outputs: Line out 7: Delay (ms) = 35	set output 7 delay 35	73 65 74 20 6F 75 74 70 75 74 20 37 20 64 65 6C 61 79 20 33 35 0D 0A
331	Outputs: Line out 7: Delay (ms) = 36	set output 7 delay 36	73 65 74 20 6F 75 74 70 75 74 20 37 20 64 65 6C 61 79 20 33 36 0D 0A
332	Outputs: Line out 7: Delay (ms) = 37	set output 7 delay 37	73 65 74 20 6F 75 74 70 75 74 20 37 20 64 65 6C 61 79 20 33 37 0D 0A
333	Outputs: Line out 7: Delay (ms) = 38	set output 7 delay 38	73 65 74 20 6F 75 74 70 75 74 20 37 20 64 65 6C 61 79 20 33 38 0D 0A
334	Outputs: Line out 7: Delay (ms) = 39	set output 7 delay 39	73 65 74 20 6F 75 74 70 75 74 20 37 20 64 65 6C 61 79 20 33 39 0D 0A
335	Outputs: Line out 7: Delay (ms) = 40	set output 7 delay 40	73 65 74 20 6F 75 74 70 75 74 20 37 20 64 65 6C 61 79 20 34 30 0D 0A
336	Outputs: Line out 8: Delay (ms) = 0	set output 8 delay 0	73 65 74 20 6F 75 74 70 75 74 20 38 20 64 65 6C 61 79 20 30 0D 0A
337	Outputs: Line out 8: Delay (ms) = 1	set output 8 delay 1	73 65 74 20 6F 75 74 70 75 74 20 38 20 64 65 6C 61 79 20 31 0D 0A
338	Outputs: Line out 8: Delay (ms) = 2	set output 8 delay 2	73 65 74 20 6F 75 74 70 75 74 20 38 20 64 65 6C 61 79 20 32 0D 0A
339	Outputs: Line out 8: Delay (ms) = 3	set output 8 delay 3	73 65 74 20 6F 75 74 70 75 74 20 38 20 64 65 6C 61 79 20 33 0D 0A
340	Outputs: Line out 8: Delay (ms) = 4	set output 8 delay 4	73 65 74 20 6F 75 74 70 75 74 20 38 20 64 65 6C 61 79 20 34 0D 0A
341	Outputs: Line out 8: Delay (ms) = 5	set output 8 delay 5	73 65 74 20 6F 75 74 70 75 74 20 38 20 64 65 6C 61 79 20 35 0D 0A
342	Outputs: Line out 8: Delay (ms) = 6	set output 8 delay 6	73 65 74 20 6F 75 74 70 75 74 20 38 20 64 65 6C 61 79 20 36 0D 0A

343	Outputs: Line out 8: Delay (ms) = 7	set output 8 delay 7	73 65 74 20 6F 75 74 70 75 74 20 38 20 64 6 5 6C 61 79 20 37 0D 0A
344	Outputs: Line out 8: Delay (ms) = 8	set output 8 delay 8	73 65 74 20 6F 75 74 70 75 74 20 38 20 64 6 5 6C 61 79 20 38 0D 0A
345	Outputs: Line out 8: Delay (ms) = 9	set output 8 delay 9	73 65 74 20 6F 75 74 70 75 74 20 38 20 64 6 5 6C 61 79 20 39 0D 0A
346	Outputs: Line out 8: Delay (ms) = 10	set output 8 delay 1 0	73 65 74 20 6F 75 74 70 75 74 20 38 20 64 6 5 6C 61 79 20 31 30 0D 0A
347	Outputs: Line out 8: Delay (ms) = 11	set output 8 delay 1 1	73 65 74 20 6F 75 74 70 75 74 20 38 20 64 6 5 6C 61 79 20 31 31 0D 0A
348	Outputs: Line out 8: Delay (ms) = 12	set output 8 delay 1 2	73 65 74 20 6F 75 74 70 75 74 20 38 20 64 6 5 6C 61 79 20 31 32 0D 0A
349	Outputs: Line out 8: Delay (ms) = 13	set output 8 delay 1 3	73 65 74 20 6F 75 74 70 75 74 20 38 20 64 6 5 6C 61 79 20 31 33 0D 0A
350	Outputs: Line out 8: Delay (ms) = 14	set output 8 delay 1 4	73 65 74 20 6F 75 74 70 75 74 20 38 20 64 6 5 6C 61 79 20 31 34 0D 0A
351	Outputs: Line out 8: Delay (ms) = 15	set output 8 delay 1 5	73 65 74 20 6F 75 74 70 75 74 20 38 20 64 6 5 6C 61 79 20 31 35 0D 0A
352	Outputs: Line out 8: Delay (ms) = 16	set output 8 delay 1 6	73 65 74 20 6F 75 74 70 75 74 20 38 20 64 6 5 6C 61 79 20 31 36 0D 0A
353	Outputs: Line out 8: Delay (ms) = 17	set output 8 delay 1 7	73 65 74 20 6F 75 74 70 75 74 20 38 20 64 6 5 6C 61 79 20 31 37 0D 0A
354	Outputs: Line out 8: Delay (ms) = 18	set output 8 delay 1 8	73 65 74 20 6F 75 74 70 75 74 20 38 20 64 6 5 6C 61 79 20 31 38 0D 0A
355	Outputs: Line out 8: Delay (ms) = 19	set output 8 delay 1 9	73 65 74 20 6F 75 74 70 75 74 20 38 20 64 6 5 6C 61 79 20 31 39 0D 0A
356	Outputs: Line out 8: Delay (ms) = 20	set output 8 delay 2 0	73 65 74 20 6F 75 74 70 75 74 20 38 20 64 6 5 6C 61 79 20 32 30 0D 0A
357	Outputs: Line out 8: Delay (ms) = 21	set output 8 delay 2 1	73 65 74 20 6F 75 74 70 75 74 20 38 20 64 6 5 6C 61 79 20 32 31 0D 0A
358	Outputs: Line out 8: Delay (ms) = 22	set output 8 delay 2 2	73 65 74 20 6F 75 74 70 75 74 20 38 20 64 6 5 6C 61 79 20 32 32 0D 0A
359	Outputs: Line out 8: Delay (ms) = 23	set output 8 delay 2 3	73 65 74 20 6F 75 74 70 75 74 20 38 20 64 6 5 6C 61 79 20 32 33 0D 0A
360	Outputs: Line out 8: Delay (ms) = 24	set output 8 delay 2 4	73 65 74 20 6F 75 74 70 75 74 20 38 20 64 6 5 6C 61 79 20 32 34 0D 0A
361	Outputs: Line out 8: Delay (ms) = 25	set output 8 delay 2 5	73 65 74 20 6F 75 74 70 75 74 20 38 20 64 6 5 6C 61 79 20 32 35 0D 0A
362	Outputs: Line out 8: Delay (ms) = 26	set output 8 delay 2 6	73 65 74 20 6F 75 74 70 75 74 20 38 20 64 6 5 6C 61 79 20 32 36 0D 0A
363	Outputs: Line out 8: Delay (ms) = 27	set output 8 delay 2 7	73 65 74 20 6F 75 74 70 75 74 20 38 20 64 6 5 6C 61 79 20 32 37 0D 0A
364	Outputs: Line out 8: Delay (ms) = 28	set output 8 delay 2 8	73 65 74 20 6F 75 74 70 75 74 20 38 20 64 6 5 6C 61 79 20 32 38 0D 0A
365	Outputs: Line out 8: Delay (ms) = 29	set output 8 delay 2 9	73 65 74 20 6F 75 74 70 75 74 20 38 20 64 6 5 6C 61 79 20 32 39 0D 0A
366	Outputs: Line out 8: Delay (ms) = 30	set output 8 delay 3 0	73 65 74 20 6F 75 74 70 75 74 20 38 20 64 6 5 6C 61 79 20 33 30 0D 0A

367	Outputs: Line out 8: Delay (ms) = 31	set output 8 delay 31	73 65 74 20 6F 75 74 70 75 74 20 38 20 64 65 6C 61 79 20 33 31 0D 0A
368	Outputs: Line out 8: Delay (ms) = 32	set output 8 delay 32	73 65 74 20 6F 75 74 70 75 74 20 38 20 64 65 6C 61 79 20 33 32 0D 0A
369	Outputs: Line out 8: Delay (ms) = 33	set output 8 delay 33	73 65 74 20 6F 75 74 70 75 74 20 38 20 64 65 6C 61 79 20 33 33 0D 0A
370	Outputs: Line out 8: Delay (ms) = 34	set output 8 delay 34	73 65 74 20 6F 75 74 70 75 74 20 38 20 64 65 6C 61 79 20 33 34 0D 0A
371	Outputs: Line out 8: Delay (ms) = 35	set output 8 delay 35	73 65 74 20 6F 75 74 70 75 74 20 38 20 64 65 6C 61 79 20 33 35 0D 0A
372	Outputs: Line out 8: Delay (ms) = 36	set output 8 delay 36	73 65 74 20 6F 75 74 70 75 74 20 38 20 64 65 6C 61 79 20 33 36 0D 0A
373	Outputs: Line out 8: Delay (ms) = 37	set output 8 delay 37	73 65 74 20 6F 75 74 70 75 74 20 38 20 64 65 6C 61 79 20 33 37 0D 0A
374	Outputs: Line out 8: Delay (ms) = 38	set output 8 delay 38	73 65 74 20 6F 75 74 70 75 74 20 38 20 64 65 6C 61 79 20 33 38 0D 0A
375	Outputs: Line out 8: Delay (ms) = 39	set output 8 delay 39	73 65 74 20 6F 75 74 70 75 74 20 38 20 64 65 6C 61 79 20 33 39 0D 0A
376	Outputs: Line out 8: Delay (ms) = 40	set output 8 delay 40	73 65 74 20 6F 75 74 70 75 74 20 38 20 64 65 6C 61 79 20 34 30 0D 0A
377	Outputs: Line out 1: Output level = +20 dBu	set output 1 sensitivity 1	73 65 74 20 6F 75 74 70 75 74 20 31 20 73 65 6E 73 69 74 69 76 69 74 79 20 31 0D 0A
378	Outputs: Line out 1: Output level = +14 dBu	set output 1 sensitivity 2	73 65 74 20 6F 75 74 70 75 74 20 31 20 73 65 6E 73 69 74 69 76 69 74 79 20 32 0D 0A
379	Outputs: Line out 1: Output level = +4 dBu	set output 1 sensitivity 3	73 65 74 20 6F 75 74 70 75 74 20 31 20 73 65 6E 73 69 74 69 76 69 74 79 20 33 0D 0A
380	Outputs: Line out 1: Output level = 0 dBV	set output 1 sensitivity 4	73 65 74 20 6F 75 74 70 75 74 20 31 20 73 65 6E 73 69 74 69 76 69 74 79 20 34 0D 0A
381	Outputs: Line out 1: Output level = -18 dBV	set output 1 sensitivity 5	73 65 74 20 6F 75 74 70 75 74 20 31 20 73 65 6E 73 69 74 69 76 69 74 79 20 35 0D 0A
382	Outputs: Line out 2: Output level = +20 dBu	set output 2 sensitivity 1	73 65 74 20 6F 75 74 70 75 74 20 32 20 73 65 6E 73 69 74 69 76 69 74 79 20 31 0D 0A
383	Outputs: Line out 2: Output level = +14 dBu	set output 2 sensitivity 2	73 65 74 20 6F 75 74 70 75 74 20 32 20 73 65 6E 73 69 74 69 76 69 74 79 20 32 0D 0A
384	Outputs: Line out 2: Output level = +4 dBu	set output 2 sensitivity 3	73 65 74 20 6F 75 74 70 75 74 20 32 20 73 65 6E 73 69 74 69 76 69 74 79 20 33 0D 0A
385	Outputs: Line out 2: Output level = 0 dBV	set output 2 sensitivity 4	73 65 74 20 6F 75 74 70 75 74 20 32 20 73 65 6E 73 69 74 69 76 69 74 79 20 34 0D 0A
386	Outputs: Line out 2: Output level = -18 dBV	set output 2 sensitivity 5	73 65 74 20 6F 75 74 70 75 74 20 32 20 73 65 6E 73 69 74 69 76 69 74 79 20 35 0D 0A
387	Outputs: Line out 3: Output level = +20 dBu	set output 3 sensitivity 1	73 65 74 20 6F 75 74 70 75 74 20 33 20 73 65 6E 73 69 74 69 76 69 74 79 20 31 0D 0A
388	Outputs: Line out 3: Output level = +14 dBu	set output 3 sensitivity 2	73 65 74 20 6F 75 74 70 75 74 20 33 20 73 65 6E 73 69 74 69 76 69 74 79 20 32 0D 0A
389	Outputs: Line out 3: Output level = +4 dBu	set output 3 sensitivity 3	73 65 74 20 6F 75 74 70 75 74 20 33 20 73 65 6E 73 69 74 69 76 69 74 79 20 33 0D 0A
390	Outputs: Line out 3: Output level = 0 dBV	set output 3 sensitivity 4	73 65 74 20 6F 75 74 70 75 74 20 33 20 73 65 6E 73 69 74 69 76 69 74 79 20 34 0D 0A

391	Outputs: Line out 3: Output level = -18 dBV	set output 3 sensitivity 5	73 65 74 20 6F 75 74 70 75 74 20 33 20 73 65 6E 73 69 74 69 76 69 74 79 20 35 0D 0A
392	Outputs: Line out 4: Output level = +20 dBu	set output 4 sensitivity 1	73 65 74 20 6F 75 74 70 75 74 20 34 20 73 65 6E 73 69 74 69 76 69 74 79 20 31 0D 0A
393	Outputs: Line out 4: Output level = +14 dBu	set output 4 sensitivity 2	73 65 74 20 6F 75 74 70 75 74 20 34 20 73 65 6E 73 69 74 69 76 69 74 79 20 32 0D 0A
394	Outputs: Line out 4: Output level = +4 dBu	set output 4 sensitivity 3	73 65 74 20 6F 75 74 70 75 74 20 34 20 73 65 6E 73 69 74 69 76 69 74 79 20 33 0D 0A
395	Outputs: Line out 4: Output level = 0 dBV	set output 4 sensitivity 4	73 65 74 20 6F 75 74 70 75 74 20 34 20 73 65 6E 73 69 74 69 76 69 74 79 20 34 0D 0A
396	Outputs: Line out 4: Output level = -18 dBV	set output 4 sensitivity 5	73 65 74 20 6F 75 74 70 75 74 20 34 20 73 65 6E 73 69 74 69 76 69 74 79 20 35 0D 0A
397	Outputs: Line out 5: Output level = +20 dBu	set output 5 sensitivity 1	73 65 74 20 6F 75 74 70 75 74 20 35 20 73 65 6E 73 69 74 69 76 69 74 79 20 31 0D 0A
398	Outputs: Line out 5: Output level = +14 dBu	set output 5 sensitivity 2	73 65 74 20 6F 75 74 70 75 74 20 35 20 73 65 6E 73 69 74 69 76 69 74 79 20 32 0D 0A
399	Outputs: Line out 5: Output level = +4 dBu	set output 5 sensitivity 3	73 65 74 20 6F 75 74 70 75 74 20 35 20 73 65 6E 73 69 74 69 76 69 74 79 20 33 0D 0A
400	Outputs: Line out 5: Output level = 0 dBV	set output 5 sensitivity 4	73 65 74 20 6F 75 74 70 75 74 20 35 20 73 65 6E 73 69 74 69 76 69 74 79 20 34 0D 0A
401	Outputs: Line out 5: Output level = -18 dBV	set output 5 sensitivity 5	73 65 74 20 6F 75 74 70 75 74 20 35 20 73 65 6E 73 69 74 69 76 69 74 79 20 35 0D 0A
402	Outputs: Line out 6: Output level = +20 dBu	set output 6 sensitivity 1	73 65 74 20 6F 75 74 70 75 74 20 36 20 73 65 6E 73 69 74 69 76 69 74 79 20 31 0D 0A
403	Outputs: Line out 6: Output level = +14 dBu	set output 6 sensitivity 2	73 65 74 20 6F 75 74 70 75 74 20 36 20 73 65 6E 73 69 74 69 76 69 74 79 20 32 0D 0A
404	Outputs: Line out 6: Output level = +4 dBu	set output 6 sensitivity 3	73 65 74 20 6F 75 74 70 75 74 20 36 20 73 65 6E 73 69 74 69 76 69 74 79 20 33 0D 0A
405	Outputs: Line out 6: Output level = 0 dBV	set output 6 sensitivity 4	73 65 74 20 6F 75 74 70 75 74 20 36 20 73 65 6E 73 69 74 69 76 69 74 79 20 34 0D 0A
406	Outputs: Line out 6: Output level = -18 dBV	set output 6 sensitivity 5	73 65 74 20 6F 75 74 70 75 74 20 36 20 73 65 6E 73 69 74 69 76 69 74 79 20 35 0D 0A
407	Outputs: Line out 7: Output level = +20 dBu	set output 7 sensitivity 1	73 65 74 20 6F 75 74 70 75 74 20 37 20 73 65 6E 73 69 74 69 76 69 74 79 20 31 0D 0A
408	Outputs: Line out 7: Output level = +14 dBu	set output 7 sensitivity 2	73 65 74 20 6F 75 74 70 75 74 20 37 20 73 65 6E 73 69 74 69 76 69 74 79 20 32 0D 0A
409	Outputs: Line out 7: Output level = +4 dBu	set output 7 sensitivity 3	73 65 74 20 6F 75 74 70 75 74 20 37 20 73 65 6E 73 69 74 69 76 69 74 79 20 33 0D 0A
410	Outputs: Line out 7: Output level = 0 dBV	set output 7 sensitivity 4	73 65 74 20 6F 75 74 70 75 74 20 37 20 73 65 6E 73 69 74 69 76 69 74 79 20 34 0D 0A
411	Outputs: Line out 7: Output level = -18 dBV	set output 7 sensitivity 5	73 65 74 20 6F 75 74 70 75 74 20 37 20 73 65 6E 73 69 74 69 76 69 74 79 20 35 0D 0A
412	Outputs: Line out 8: Output level = +20 dBu	set output 8 sensitivity 1	73 65 74 20 6F 75 74 70 75 74 20 38 20 73 65 6E 73 69 74 69 76 69 74 79 20 31 0D 0A
413	Outputs: Line out 8: Output level = +14 dBu	set output 8 sensitivity 2	73 65 74 20 6F 75 74 70 75 74 20 38 20 73 65 6E 73 69 74 69 76 69 74 79 20 32 0D 0A
414	Outputs: Line out 8: Output level = +4 dBu	set output 8 sensitivity 3	73 65 74 20 6F 75 74 70 75 74 20 38 20 73 65 6E 73 69 74 69 76 69 74 79 20 33 0D 0A

415	Outputs: Line out 8: Output level = 0 dBV	`set output 8 sensitivity 4`	`73 65 74 20 6F 75 74 70 75 74 20 38 20 73 65 6E 73 69 74 69 76 69 74 79 20 34 0D 0A`
416	Outputs: Line out 8: Output level = -18 dBV	`set output 8 sensitivity 5`	`73 65 74 20 6F 75 74 70 75 74 20 38 20 73 65 6E 73 69 74 69 76 69 74 79 20 35 0D 0A`
417	Inputs: Line in 1: Gain (dB) = {level} (-60 to 12)	`set input 1 gain {level}`	`the level in place of {level}`
418	Inputs: Line in 1: Gain (dB) = -60	`set input 1 gain -60`	`73 65 74 20 69 6E 70 75 74 20 31 20 67 61 69 6E 20 2D 36 30 0D 0A`
419	Inputs: Line in 1: Gain (dB) = -24	`set input 1 gain -24`	`73 65 74 20 69 6E 70 75 74 20 31 20 67 61 69 6E 20 2D 32 34 0D 0A`
420	Inputs: Line in 1: Gain (dB) = 12	`set input 1 gain 12`	`73 65 74 20 69 6E 70 75 74 20 31 20 67 61 69 6E 20 31 32 0D 0A`
421	Inputs: Line in 2: Gain (dB) = {level} (-60 to 12)	`set input 2 gain {level}`	`the level in place of {level}`
422	Inputs: Line in 2: Gain (dB) = -60	`set input 2 gain -60`	`73 65 74 20 69 6E 70 75 74 20 32 20 67 61 69 6E 20 2D 36 30 0D 0A`
423	Inputs: Line in 2: Gain (dB) = -24	`set input 2 gain -24`	`73 65 74 20 69 6E 70 75 74 20 32 20 67 61 69 6E 20 2D 32 34 0D 0A`
424	Inputs: Line in 2: Gain (dB) = 12	`set input 2 gain 12`	`73 65 74 20 69 6E 70 75 74 20 32 20 67 61 69 6E 20 31 32 0D 0A`
425	Inputs: Line in 3: Gain (dB) = {level} (-60 to 12)	`set input 3 gain {level}`	`the level in place of {level}`
426	Inputs: Line in 3: Gain (dB) = -60	`set input 3 gain -60`	`73 65 74 20 69 6E 70 75 74 20 33 20 67 61 69 6E 20 2D 36 30 0D 0A`
427	Inputs: Line in 3: Gain (dB) = -24	`set input 3 gain -24`	`73 65 74 20 69 6E 70 75 74 20 33 20 67 61 69 6E 20 2D 32 34 0D 0A`
428	Inputs: Line in 3: Gain (dB) = 12	`set input 3 gain 12`	`73 65 74 20 69 6E 70 75 74 20 33 20 67 61 69 6E 20 31 32 0D 0A`
429	Inputs: Line in 4: Gain (dB) = {level} (-60 to 12)	`set input 4 gain {level}`	`the level in place of {level}`
430	Inputs: Line in 4: Gain (dB) = -60	`set input 4 gain -60`	`73 65 74 20 69 6E 70 75 74 20 34 20 67 61 69 6E 20 2D 36 30 0D 0A`
431	Inputs: Line in 4: Gain (dB) = -24	`set input 4 gain -24`	`73 65 74 20 69 6E 70 75 74 20 34 20 67 61 69 6E 20 2D 32 34 0D 0A`
432	Inputs: Line in 4: Gain (dB) = 12	`set input 4 gain 12`	`73 65 74 20 69 6E 70 75 74 20 34 20 67 61 69 6E 20 31 32 0D 0A`
433	Inputs: Line in 5: Gain (dB) = {level} (-60 to 12)	`set input 5 gain {level}`	`the level in place of {level}`
434	Inputs: Line in 5: Gain (dB) = -60	`set input 5 gain -60`	`73 65 74 20 69 6E 70 75 74 20 35 20 67 61 69 6E 20 2D 36 30 0D 0A`
435	Inputs: Line in 5: Gain (dB) = -24	`set input 5 gain -24`	`73 65 74 20 69 6E 70 75 74 20 35 20 67 61 69 6E 20 2D 32 34 0D 0A`
436	Inputs: Line in 5: Gain (dB) = 12	`set input 5 gain 12`	`73 65 74 20 69 6E 70 75 74 20 35 20 67 61 69 6E 20 31 32 0D 0A`
437	Inputs: Line in 6: Gain (dB) = {level} (-60 to 12)	`set input 6 gain {level}`	`the level in place of {level}`
438	Inputs: Line in 6: Gain (dB) = -60	`set input 6 gain -60`	`73 65 74 20 69 6E 70 75 74 20 36 20 67 61 69 6E 20 2D 36 30 0D 0A`

439	Inputs: Line in 6: Gain (dB) = -24	`set input 6 gain -24`	`73 65 74 20 69 6E 70 75 74 20 36 20 67 61 6 9 6E 20 2D 32 34 0D 0A`
440	Inputs: Line in 6: Gain (dB) = 12	`set input 6 gain 12`	`73 65 74 20 69 6E 70 75 74 20 36 20 67 61 6 9 6E 20 31 32 0D 0A`
441	Inputs: Line in 7: Gain (dB) = {level} (-60 to 12)	`set input 7 gain {lev el}`	`the level in place of {level}`
442	Inputs: Line in 7: Gain (dB) = -60	`set input 7 gain -60`	`73 65 74 20 69 6E 70 75 74 20 37 20 67 61 6 9 6E 20 2D 36 30 0D 0A`
443	Inputs: Line in 7: Gain (dB) = -24	`set input 7 gain -24`	`73 65 74 20 69 6E 70 75 74 20 37 20 67 61 6 9 6E 20 2D 32 34 0D 0A`
444	Inputs: Line in 7: Gain (dB) = 12	`set input 7 gain 12`	`73 65 74 20 69 6E 70 75 74 20 37 20 67 61 6 9 6E 20 31 32 0D 0A`
445	Inputs: Line in 8: Gain (dB) = {level} (-60 to 12)	`set input 8 gain {lev el}`	`the level in place of {level}`
446	Inputs: Line in 8: Gain (dB) = -60	`set input 8 gain -60`	`73 65 74 20 69 6E 70 75 74 20 38 20 67 61 6 9 6E 20 2D 36 30 0D 0A`
447	Inputs: Line in 8: Gain (dB) = -24	`set input 8 gain -24`	`73 65 74 20 69 6E 70 75 74 20 38 20 67 61 6 9 6E 20 2D 32 34 0D 0A`
448	Inputs: Line in 8: Gain (dB) = 12	`set input 8 gain 12`	`73 65 74 20 69 6E 70 75 74 20 38 20 67 61 6 9 6E 20 31 32 0D 0A`
449	Inputs: Line in 1: Mute on	`set input 1 mute on`	`73 65 74 20 69 6E 70 75 74 20 31 20 6D 75 7 4 65 20 6F 6E 0D 0A`
450	Inputs: Line in 1: Mute off	`set input 1 mute off`	`73 65 74 20 69 6E 70 75 74 20 31 20 6D 75 7 4 65 20 6F 66 66 0D 0A`
451	Inputs: Line in 2: Mute on	`set input 2 mute on`	`73 65 74 20 69 6E 70 75 74 20 32 20 6D 75 7 4 65 20 6F 6E 0D 0A`
452	Inputs: Line in 2: Mute off	`set input 2 mute off`	`73 65 74 20 69 6E 70 75 74 20 32 20 6D 75 7 4 65 20 6F 66 66 0D 0A`
453	Inputs: Line in 3: Mute on	`set input 3 mute on`	`73 65 74 20 69 6E 70 75 74 20 33 20 6D 75 7 4 65 20 6F 6E 0D 0A`
454	Inputs: Line in 3: Mute off	`set input 3 mute off`	`73 65 74 20 69 6E 70 75 74 20 33 20 6D 75 7 4 65 20 6F 66 66 0D 0A`
455	Inputs: Line in 4: Mute on	`set input 4 mute on`	`73 65 74 20 69 6E 70 75 74 20 34 20 6D 75 7 4 65 20 6F 6E 0D 0A`
456	Inputs: Line in 4: Mute off	`set input 4 mute off`	`73 65 74 20 69 6E 70 75 74 20 34 20 6D 75 7 4 65 20 6F 66 66 0D 0A`
457	Inputs: Line in 5: Mute on	`set input 5 mute on`	`73 65 74 20 69 6E 70 75 74 20 35 20 6D 75 7 4 65 20 6F 6E 0D 0A`
458	Inputs: Line in 5: Mute off	`set input 5 mute off`	`73 65 74 20 69 6E 70 75 74 20 35 20 6D 75 7 4 65 20 6F 66 66 0D 0A`
459	Inputs: Line in 6: Mute on	`set input 6 mute on`	`73 65 74 20 69 6E 70 75 74 20 36 20 6D 75 7 4 65 20 6F 6E 0D 0A`
460	Inputs: Line in 6: Mute off	`set input 6 mute off`	`73 65 74 20 69 6E 70 75 74 20 36 20 6D 75 7 4 65 20 6F 66 66 0D 0A`
461	Inputs: Line in 7: Mute on	`set input 7 mute on`	`73 65 74 20 69 6E 70 75 74 20 37 20 6D 75 7 4 65 20 6F 6E 0D 0A`
462	Inputs: Line in 7: Mute off	`set input 7 mute off`	`73 65 74 20 69 6E 70 75 74 20 37 20 6D 75 7 4 65 20 6F 66 66 0D 0A`

463	Inputs: Line in 8: Mute on	set input 8 mute on	73 65 74 20 69 6E 70 75 74 20 38 20 6D 75 74 65 20 6F 6E 0D 0A
464	Inputs: Line in 8: Mute off	set input 8 mute off	73 65 74 20 69 6E 70 75 74 20 38 20 6D 75 74 65 20 6F 66 66 0D 0A
465	Inputs: Line in 1: Sensitivity = +24 dBu	set input 1 sensitivity 1	73 65 74 20 69 6E 70 75 74 20 31 20 73 65 6E 73 69 74 69 76 69 74 79 20 31 0D 0A
466	Inputs: Line in 1: Sensitivity = +14 dBu	set input 1 sensitivity 2	73 65 74 20 69 6E 70 75 74 20 31 20 73 65 6E 73 69 74 69 76 69 74 79 20 32 0D 0A
467	Inputs: Line in 1: Sensitivity = +4 dBu	set input 1 sensitivity 3	73 65 74 20 69 6E 70 75 74 20 31 20 73 65 6E 73 69 74 69 76 69 74 79 20 33 0D 0A
468	Inputs: Line in 1: Sensitivity = 0 dBV	set input 1 sensitivity 4	73 65 74 20 69 6E 70 75 74 20 31 20 73 65 6E 73 69 74 69 76 69 74 79 20 34 0D 0A
469	Inputs: Line in 1: Sensitivity = -18 dBV	set input 1 sensitivity 5	73 65 74 20 69 6E 70 75 74 20 31 20 73 65 6E 73 69 74 69 76 69 74 79 20 35 0D 0A
470	Inputs: Line in 1: Sensitivity = -35 dBV	set input 1 sensitivity 6	73 65 74 20 69 6E 70 75 74 20 31 20 73 65 6E 73 69 74 69 76 69 74 79 20 36 0D 0A
471	Inputs: Line in 2: Sensitivity = +24 dBu	set input 2 sensitivity 1	73 65 74 20 69 6E 70 75 74 20 32 20 73 65 6E 73 69 74 69 76 69 74 79 20 31 0D 0A
472	Inputs: Line in 2: Sensitivity = +14 dBu	set input 2 sensitivity 2	73 65 74 20 69 6E 70 75 74 20 32 20 73 65 6E 73 69 74 69 76 69 74 79 20 32 0D 0A
473	Inputs: Line in 2: Sensitivity = +4 dBu	set input 2 sensitivity 3	73 65 74 20 69 6E 70 75 74 20 32 20 73 65 6E 73 69 74 69 76 69 74 79 20 33 0D 0A
474	Inputs: Line in 2: Sensitivity = 0 dBV	set input 2 sensitivity 4	73 65 74 20 69 6E 70 75 74 20 32 20 73 65 6E 73 69 74 69 76 69 74 79 20 34 0D 0A
475	Inputs: Line in 2: Sensitivity = -18 dBV	set input 2 sensitivity 5	73 65 74 20 69 6E 70 75 74 20 32 20 73 65 6E 73 69 74 69 76 69 74 79 20 35 0D 0A
476	Inputs: Line in 2: Sensitivity = -35 dBV	set input 2 sensitivity 6	73 65 74 20 69 6E 70 75 74 20 32 20 73 65 6E 73 69 74 69 76 69 74 79 20 36 0D 0A
477	Inputs: Line in 3: Sensitivity = +24 dBu	set input 3 sensitivity 1	73 65 74 20 69 6E 70 75 74 20 33 20 73 65 6E 73 69 74 69 76 69 74 79 20 31 0D 0A
478	Inputs: Line in 3: Sensitivity = +14 dBu	set input 3 sensitivity 2	73 65 74 20 69 6E 70 75 74 20 33 20 73 65 6E 73 69 74 69 76 69 74 79 20 32 0D 0A
479	Inputs: Line in 3: Sensitivity = +4 dBu	set input 3 sensitivity 3	73 65 74 20 69 6E 70 75 74 20 33 20 73 65 6E 73 69 74 69 76 69 74 79 20 33 0D 0A
480	Inputs: Line in 3: Sensitivity = 0 dBV	set input 3 sensitivity 4	73 65 74 20 69 6E 70 75 74 20 33 20 73 65 6E 73 69 74 69 76 69 74 79 20 34 0D 0A
481	Inputs: Line in 3: Sensitivity = -18 dBV	set input 3 sensitivity 5	73 65 74 20 69 6E 70 75 74 20 33 20 73 65 6E 73 69 74 69 76 69 74 79 20 35 0D 0A
482	Inputs: Line in 3: Sensitivity = -35 dBV	set input 3 sensitivity 6	73 65 74 20 69 6E 70 75 74 20 33 20 73 65 6E 73 69 74 69 76 69 74 79 20 36 0D 0A
483	Inputs: Line in 4: Sensitivity = +24 dBu	set input 4 sensitivity 1	73 65 74 20 69 6E 70 75 74 20 34 20 73 65 6E 73 69 74 69 76 69 74 79 20 31 0D 0A
484	Inputs: Line in 4: Sensitivity = +14 dBu	set input 4 sensitivity 2	73 65 74 20 69 6E 70 75 74 20 34 20 73 65 6E 73 69 74 69 76 69 74 79 20 32 0D 0A
485	Inputs: Line in 4: Sensitivity = +4 dBu	set input 4 sensitivity 3	73 65 74 20 69 6E 70 75 74 20 34 20 73 65 6E 73 69 74 69 76 69 74 79 20 33 0D 0A
486	Inputs: Line in 4: Sensitivity = 0 dBV	set input 4 sensitivity 4	73 65 74 20 69 6E 70 75 74 20 34 20 73 65 6E 73 69 74 69 76 69 74 79 20 34 0D 0A

487	Inputs: Line in 4: Sensitivity = -18 dBV	set input 4 sensitivity 5	73 65 74 20 69 6E 70 75 74 20 34 20 73 65 6E 73 69 74 69 76 69 74 79 20 35 0D 0A
488	Inputs: Line in 4: Sensitivity = -35 dBV	set input 4 sensitivity 6	73 65 74 20 69 6E 70 75 74 20 34 20 73 65 6E 73 69 74 69 76 69 74 79 20 36 0D 0A
489	Inputs: Line in 5: Sensitivity = +24 dBu	set input 5 sensitivity 1	73 65 74 20 69 6E 70 75 74 20 35 20 73 65 6E 73 69 74 69 76 69 74 79 20 31 0D 0A
490	Inputs: Line in 5: Sensitivity = +14 dBu	set input 5 sensitivity 2	73 65 74 20 69 6E 70 75 74 20 35 20 73 65 6E 73 69 74 69 76 69 74 79 20 32 0D 0A
491	Inputs: Line in 5: Sensitivity = +4 dBu	set input 5 sensitivity 3	73 65 74 20 69 6E 70 75 74 20 35 20 73 65 6E 73 69 74 69 76 69 74 79 20 33 0D 0A
492	Inputs: Line in 5: Sensitivity = 0 dBV	set input 5 sensitivity 4	73 65 74 20 69 6E 70 75 74 20 35 20 73 65 6E 73 69 74 69 76 69 74 79 20 34 0D 0A
493	Inputs: Line in 5: Sensitivity = -18 dBV	set input 5 sensitivity 5	73 65 74 20 69 6E 70 75 74 20 35 20 73 65 6E 73 69 74 69 76 69 74 79 20 35 0D 0A
494	Inputs: Line in 5: Sensitivity = -35 dBV	set input 5 sensitivity 6	73 65 74 20 69 6E 70 75 74 20 35 20 73 65 6E 73 69 74 69 76 69 74 79 20 36 0D 0A
495	Inputs: Line in 6: Sensitivity = +24 dBu	set input 6 sensitivity 1	73 65 74 20 69 6E 70 75 74 20 36 20 73 65 6E 73 69 74 69 76 69 74 79 20 31 0D 0A
496	Inputs: Line in 6: Sensitivity = +14 dBu	set input 6 sensitivity 2	73 65 74 20 69 6E 70 75 74 20 36 20 73 65 6E 73 69 74 69 76 69 74 79 20 32 0D 0A
497	Inputs: Line in 6: Sensitivity = +4 dBu	set input 6 sensitivity 3	73 65 74 20 69 6E 70 75 74 20 36 20 73 65 6E 73 69 74 69 76 69 74 79 20 33 0D 0A
498	Inputs: Line in 6: Sensitivity = 0 dBV	set input 6 sensitivity 4	73 65 74 20 69 6E 70 75 74 20 36 20 73 65 6E 73 69 74 69 76 69 74 79 20 34 0D 0A
499	Inputs: Line in 6: Sensitivity = -18 dBV	set input 6 sensitivity 5	73 65 74 20 69 6E 70 75 74 20 36 20 73 65 6E 73 69 74 69 76 69 74 79 20 35 0D 0A
500	Inputs: Line in 6: Sensitivity = -35 dBV	set input 6 sensitivity 6	73 65 74 20 69 6E 70 75 74 20 36 20 73 65 6E 73 69 74 69 76 69 74 79 20 36 0D 0A
501	Inputs: Line in 7: Sensitivity = +24 dBu	set input 7 sensitivity 1	73 65 74 20 69 6E 70 75 74 20 37 20 73 65 6E 73 69 74 69 76 69 74 79 20 31 0D 0A
502	Inputs: Line in 7: Sensitivity = +14 dBu	set input 7 sensitivity 2	73 65 74 20 69 6E 70 75 74 20 37 20 73 65 6E 73 69 74 69 76 69 74 79 20 32 0D 0A
503	Inputs: Line in 7: Sensitivity = +4 dBu	set input 7 sensitivity 3	73 65 74 20 69 6E 70 75 74 20 37 20 73 65 6E 73 69 74 69 76 69 74 79 20 33 0D 0A
504	Inputs: Line in 7: Sensitivity = 0 dBV	set input 7 sensitivity 4	73 65 74 20 69 6E 70 75 74 20 37 20 73 65 6E 73 69 74 69 76 69 74 79 20 34 0D 0A
505	Inputs: Line in 7: Sensitivity = -18 dBV	set input 7 sensitivity 5	73 65 74 20 69 6E 70 75 74 20 37 20 73 65 6E 73 69 74 69 76 69 74 79 20 35 0D 0A
506	Inputs: Line in 7: Sensitivity = -35 dBV	set input 7 sensitivity 6	73 65 74 20 69 6E 70 75 74 20 37 20 73 65 6E 73 69 74 69 76 69 74 79 20 36 0D 0A
507	Inputs: Line in 8: Sensitivity = +24 dBu	set input 8 sensitivity 1	73 65 74 20 69 6E 70 75 74 20 38 20 73 65 6E 73 69 74 69 76 69 74 79 20 31 0D 0A
508	Inputs: Line in 8: Sensitivity = +14 dBu	set input 8 sensitivity 2	73 65 74 20 69 6E 70 75 74 20 38 20 73 65 6E 73 69 74 69 76 69 74 79 20 32 0D 0A
509	Inputs: Line in 8: Sensitivity = +4 dBu	set input 8 sensitivity 3	73 65 74 20 69 6E 70 75 74 20 38 20 73 65 6E 73 69 74 69 76 69 74 79 20 33 0D 0A
510	Inputs: Line in 8: Sensitivity = 0 dBV	set input 8 sensitivity 4	73 65 74 20 69 6E 70 75 74 20 38 20 73 65 6E 73 69 74 69 76 69 74 79 20 34 0D 0A

511	Inputs: Line in 8: Sensitivity = -18 dBV	`set input 8 sensitivity 5`	`73 65 74 20 69 6E 70 75 74 20 38 20 73 65 6E 73 69 74 69 76 69 74 79 20 35 0D 0A`
512	Inputs: Line in 8: Sensitivity = -35 dBV	`set input 8 sensitivity 6`	`73 65 74 20 69 6E 70 75 74 20 38 20 73 65 6E 73 69 74 69 76 69 74 79 20 36 0D 0A`
513	Inputs: Line in 1: Delay (ms) = 0	`set input 1 delay 0`	`73 65 74 20 69 6E 70 75 74 20 31 20 64 65 6C 61 79 20 30 0D 0A`
514	Inputs: Line in 1: Delay (ms) = 1	`set input 1 delay 1`	`73 65 74 20 69 6E 70 75 74 20 31 20 64 65 6C 61 79 20 31 0D 0A`
515	Inputs: Line in 1: Delay (ms) = 2	`set input 1 delay 2`	`73 65 74 20 69 6E 70 75 74 20 31 20 64 65 6C 61 79 20 32 0D 0A`
516	Inputs: Line in 1: Delay (ms) = 3	`set input 1 delay 3`	`73 65 74 20 69 6E 70 75 74 20 31 20 64 65 6C 61 79 20 33 0D 0A`
517	Inputs: Line in 1: Delay (ms) = 4	`set input 1 delay 4`	`73 65 74 20 69 6E 70 75 74 20 31 20 64 65 6C 61 79 20 34 0D 0A`
518	Inputs: Line in 1: Delay (ms) = 5	`set input 1 delay 5`	`73 65 74 20 69 6E 70 75 74 20 31 20 64 65 6C 61 79 20 35 0D 0A`
519	Inputs: Line in 1: Delay (ms) = 6	`set input 1 delay 6`	`73 65 74 20 69 6E 70 75 74 20 31 20 64 65 6C 61 79 20 36 0D 0A`
520	Inputs: Line in 1: Delay (ms) = 7	`set input 1 delay 7`	`73 65 74 20 69 6E 70 75 74 20 31 20 64 65 6C 61 79 20 37 0D 0A`
521	Inputs: Line in 1: Delay (ms) = 8	`set input 1 delay 8`	`73 65 74 20 69 6E 70 75 74 20 31 20 64 65 6C 61 79 20 38 0D 0A`
522	Inputs: Line in 1: Delay (ms) = 9	`set input 1 delay 9`	`73 65 74 20 69 6E 70 75 74 20 31 20 64 65 6C 61 79 20 39 0D 0A`
523	Inputs: Line in 1: Delay (ms) = 10	`set input 1 delay 10`	`73 65 74 20 69 6E 70 75 74 20 31 20 64 65 6C 61 79 20 31 30 0D 0A`
524	Inputs: Line in 1: Delay (ms) = 11	`set input 1 delay 11`	`73 65 74 20 69 6E 70 75 74 20 31 20 64 65 6C 61 79 20 31 31 0D 0A`
525	Inputs: Line in 1: Delay (ms) = 12	`set input 1 delay 12`	`73 65 74 20 69 6E 70 75 74 20 31 20 64 65 6C 61 79 20 31 32 0D 0A`
526	Inputs: Line in 1: Delay (ms) = 13	`set input 1 delay 13`	`73 65 74 20 69 6E 70 75 74 20 31 20 64 65 6C 61 79 20 31 33 0D 0A`
527	Inputs: Line in 1: Delay (ms) = 14	`set input 1 delay 14`	`73 65 74 20 69 6E 70 75 74 20 31 20 64 65 6C 61 79 20 31 34 0D 0A`
528	Inputs: Line in 1: Delay (ms) = 15	`set input 1 delay 15`	`73 65 74 20 69 6E 70 75 74 20 31 20 64 65 6C 61 79 20 31 35 0D 0A`
529	Inputs: Line in 1: Delay (ms) = 16	`set input 1 delay 16`	`73 65 74 20 69 6E 70 75 74 20 31 20 64 65 6C 61 79 20 31 36 0D 0A`
530	Inputs: Line in 1: Delay (ms) = 17	`set input 1 delay 17`	`73 65 74 20 69 6E 70 75 74 20 31 20 64 65 6C 61 79 20 31 37 0D 0A`
531	Inputs: Line in 1: Delay (ms) = 18	`set input 1 delay 18`	`73 65 74 20 69 6E 70 75 74 20 31 20 64 65 6C 61 79 20 31 38 0D 0A`
532	Inputs: Line in 1: Delay (ms) = 19	`set input 1 delay 19`	`73 65 74 20 69 6E 70 75 74 20 31 20 64 65 6C 61 79 20 31 39 0D 0A`
533	Inputs: Line in 1: Delay (ms) = 20	`set input 1 delay 20`	`73 65 74 20 69 6E 70 75 74 20 31 20 64 65 6C 61 79 20 32 30 0D 0A`
534	Inputs: Line in 1: Delay (ms) = 21	`set input 1 delay 21`	`73 65 74 20 69 6E 70 75 74 20 31 20 64 65 6C 61 79 20 32 31 0D 0A`

535	Inputs: Line in 1: Delay (ms) = 22	set input 1 delay 22	73 65 74 20 69 6E 70 75 74 20 31 20 64 65 6C 61 79 20 32 32 0D 0A
536	Inputs: Line in 1: Delay (ms) = 23	set input 1 delay 23	73 65 74 20 69 6E 70 75 74 20 31 20 64 65 6C 61 79 20 32 33 0D 0A
537	Inputs: Line in 1: Delay (ms) = 24	set input 1 delay 24	73 65 74 20 69 6E 70 75 74 20 31 20 64 65 6C 61 79 20 32 34 0D 0A
538	Inputs: Line in 1: Delay (ms) = 25	set input 1 delay 25	73 65 74 20 69 6E 70 75 74 20 31 20 64 65 6C 61 79 20 32 35 0D 0A
539	Inputs: Line in 1: Delay (ms) = 26	set input 1 delay 26	73 65 74 20 69 6E 70 75 74 20 31 20 64 65 6C 61 79 20 32 36 0D 0A
540	Inputs: Line in 1: Delay (ms) = 27	set input 1 delay 27	73 65 74 20 69 6E 70 75 74 20 31 20 64 65 6C 61 79 20 32 37 0D 0A
541	Inputs: Line in 1: Delay (ms) = 28	set input 1 delay 28	73 65 74 20 69 6E 70 75 74 20 31 20 64 65 6C 61 79 20 32 38 0D 0A
542	Inputs: Line in 1: Delay (ms) = 29	set input 1 delay 29	73 65 74 20 69 6E 70 75 74 20 31 20 64 65 6C 61 79 20 32 39 0D 0A
543	Inputs: Line in 1: Delay (ms) = 30	set input 1 delay 30	73 65 74 20 69 6E 70 75 74 20 31 20 64 65 6C 61 79 20 33 30 0D 0A
544	Inputs: Line in 1: Delay (ms) = 31	set input 1 delay 31	73 65 74 20 69 6E 70 75 74 20 31 20 64 65 6C 61 79 20 33 31 0D 0A
545	Inputs: Line in 1: Delay (ms) = 32	set input 1 delay 32	73 65 74 20 69 6E 70 75 74 20 31 20 64 65 6C 61 79 20 33 32 0D 0A
546	Inputs: Line in 1: Delay (ms) = 33	set input 1 delay 33	73 65 74 20 69 6E 70 75 74 20 31 20 64 65 6C 61 79 20 33 33 0D 0A
547	Inputs: Line in 1: Delay (ms) = 34	set input 1 delay 34	73 65 74 20 69 6E 70 75 74 20 31 20 64 65 6C 61 79 20 33 34 0D 0A
548	Inputs: Line in 1: Delay (ms) = 35	set input 1 delay 35	73 65 74 20 69 6E 70 75 74 20 31 20 64 65 6C 61 79 20 33 35 0D 0A
549	Inputs: Line in 1: Delay (ms) = 36	set input 1 delay 36	73 65 74 20 69 6E 70 75 74 20 31 20 64 65 6C 61 79 20 33 36 0D 0A
550	Inputs: Line in 1: Delay (ms) = 37	set input 1 delay 37	73 65 74 20 69 6E 70 75 74 20 31 20 64 65 6C 61 79 20 33 37 0D 0A
551	Inputs: Line in 1: Delay (ms) = 38	set input 1 delay 38	73 65 74 20 69 6E 70 75 74 20 31 20 64 65 6C 61 79 20 33 38 0D 0A
552	Inputs: Line in 1: Delay (ms) = 39	set input 1 delay 39	73 65 74 20 69 6E 70 75 74 20 31 20 64 65 6C 61 79 20 33 39 0D 0A
553	Inputs: Line in 1: Delay (ms) = 40	set input 1 delay 40	73 65 74 20 69 6E 70 75 74 20 31 20 64 65 6C 61 79 20 34 30 0D 0A
554	Inputs: Line in 2: Delay (ms) = 0	set input 2 delay 0	73 65 74 20 69 6E 70 75 74 20 32 20 64 65 6C 61 79 20 30 0D 0A
555	Inputs: Line in 2: Delay (ms) = 1	set input 2 delay 1	73 65 74 20 69 6E 70 75 74 20 32 20 64 65 6C 61 79 20 31 0D 0A
556	Inputs: Line in 2: Delay (ms) = 2	set input 2 delay 2	73 65 74 20 69 6E 70 75 74 20 32 20 64 65 6C 61 79 20 32 0D 0A
557	Inputs: Line in 2: Delay (ms) = 3	set input 2 delay 3	73 65 74 20 69 6E 70 75 74 20 32 20 64 65 6C 61 79 20 33 0D 0A
558	Inputs: Line in 2: Delay (ms) = 4	set input 2 delay 4	73 65 74 20 69 6E 70 75 74 20 32 20 64 65 6C 61 79 20 34 0D 0A

559	Inputs: Line in 2: Delay (ms) = 5	`set input 2 delay 5`	`73 65 74 20 69 6E 70 75 74 20 32 20 64 65 6C 61 79 20 35 0D 0A`
560	Inputs: Line in 2: Delay (ms) = 6	`set input 2 delay 6`	`73 65 74 20 69 6E 70 75 74 20 32 20 64 65 6C 61 79 20 36 0D 0A`
561	Inputs: Line in 2: Delay (ms) = 7	`set input 2 delay 7`	`73 65 74 20 69 6E 70 75 74 20 32 20 64 65 6C 61 79 20 37 0D 0A`
562	Inputs: Line in 2: Delay (ms) = 8	`set input 2 delay 8`	`73 65 74 20 69 6E 70 75 74 20 32 20 64 65 6C 61 79 20 38 0D 0A`
563	Inputs: Line in 2: Delay (ms) = 9	`set input 2 delay 9`	`73 65 74 20 69 6E 70 75 74 20 32 20 64 65 6C 61 79 20 39 0D 0A`
564	Inputs: Line in 2: Delay (ms) = 10	`set input 2 delay 10`	`73 65 74 20 69 6E 70 75 74 20 32 20 64 65 6C 61 79 20 31 30 0D 0A`
565	Inputs: Line in 2: Delay (ms) = 11	`set input 2 delay 11`	`73 65 74 20 69 6E 70 75 74 20 32 20 64 65 6C 61 79 20 31 31 0D 0A`
566	Inputs: Line in 2: Delay (ms) = 12	`set input 2 delay 12`	`73 65 74 20 69 6E 70 75 74 20 32 20 64 65 6C 61 79 20 31 32 0D 0A`
567	Inputs: Line in 2: Delay (ms) = 13	`set input 2 delay 13`	`73 65 74 20 69 6E 70 75 74 20 32 20 64 65 6C 61 79 20 31 33 0D 0A`
568	Inputs: Line in 2: Delay (ms) = 14	`set input 2 delay 14`	`73 65 74 20 69 6E 70 75 74 20 32 20 64 65 6C 61 79 20 31 34 0D 0A`
569	Inputs: Line in 2: Delay (ms) = 15	`set input 2 delay 15`	`73 65 74 20 69 6E 70 75 74 20 32 20 64 65 6C 61 79 20 31 35 0D 0A`
570	Inputs: Line in 2: Delay (ms) = 16	`set input 2 delay 16`	`73 65 74 20 69 6E 70 75 74 20 32 20 64 65 6C 61 79 20 31 36 0D 0A`
571	Inputs: Line in 2: Delay (ms) = 17	`set input 2 delay 17`	`73 65 74 20 69 6E 70 75 74 20 32 20 64 65 6C 61 79 20 31 37 0D 0A`
572	Inputs: Line in 2: Delay (ms) = 18	`set input 2 delay 18`	`73 65 74 20 69 6E 70 75 74 20 32 20 64 65 6C 61 79 20 31 38 0D 0A`
573	Inputs: Line in 2: Delay (ms) = 19	`set input 2 delay 19`	`73 65 74 20 69 6E 70 75 74 20 32 20 64 65 6C 61 79 20 31 39 0D 0A`
574	Inputs: Line in 2: Delay (ms) = 20	`set input 2 delay 20`	`73 65 74 20 69 6E 70 75 74 20 32 20 64 65 6C 61 79 20 32 30 0D 0A`
575	Inputs: Line in 2: Delay (ms) = 21	`set input 2 delay 21`	`73 65 74 20 69 6E 70 75 74 20 32 20 64 65 6C 61 79 20 32 31 0D 0A`
576	Inputs: Line in 2: Delay (ms) = 22	`set input 2 delay 22`	`73 65 74 20 69 6E 70 75 74 20 32 20 64 65 6C 61 79 20 32 32 0D 0A`
577	Inputs: Line in 2: Delay (ms) = 23	`set input 2 delay 23`	`73 65 74 20 69 6E 70 75 74 20 32 20 64 65 6C 61 79 20 32 33 0D 0A`
578	Inputs: Line in 2: Delay (ms) = 24	`set input 2 delay 24`	`73 65 74 20 69 6E 70 75 74 20 32 20 64 65 6C 61 79 20 32 34 0D 0A`
579	Inputs: Line in 2: Delay (ms) = 25	`set input 2 delay 25`	`73 65 74 20 69 6E 70 75 74 20 32 20 64 65 6C 61 79 20 32 35 0D 0A`
580	Inputs: Line in 2: Delay (ms) = 26	`set input 2 delay 26`	`73 65 74 20 69 6E 70 75 74 20 32 20 64 65 6C 61 79 20 32 36 0D 0A`
581	Inputs: Line in 2: Delay (ms) = 27	`set input 2 delay 27`	`73 65 74 20 69 6E 70 75 74 20 32 20 64 65 6C 61 79 20 32 37 0D 0A`
582	Inputs: Line in 2: Delay (ms) = 28	`set input 2 delay 28`	`73 65 74 20 69 6E 70 75 74 20 32 20 64 65 6C 61 79 20 32 38 0D 0A`

583	Inputs: Line in 2: Delay (ms) = 29	set input 2 delay 29	73 65 74 20 69 6E 70 75 74 20 32 20 64 65 6C 61 79 20 32 39 0D 0A
584	Inputs: Line in 2: Delay (ms) = 30	set input 2 delay 30	73 65 74 20 69 6E 70 75 74 20 32 20 64 65 6C 61 79 20 33 30 0D 0A
585	Inputs: Line in 2: Delay (ms) = 31	set input 2 delay 31	73 65 74 20 69 6E 70 75 74 20 32 20 64 65 6C 61 79 20 33 31 0D 0A
586	Inputs: Line in 2: Delay (ms) = 32	set input 2 delay 32	73 65 74 20 69 6E 70 75 74 20 32 20 64 65 6C 61 79 20 33 32 0D 0A
587	Inputs: Line in 2: Delay (ms) = 33	set input 2 delay 33	73 65 74 20 69 6E 70 75 74 20 32 20 64 65 6C 61 79 20 33 33 0D 0A
588	Inputs: Line in 2: Delay (ms) = 34	set input 2 delay 34	73 65 74 20 69 6E 70 75 74 20 32 20 64 65 6C 61 79 20 33 34 0D 0A
589	Inputs: Line in 2: Delay (ms) = 35	set input 2 delay 35	73 65 74 20 69 6E 70 75 74 20 32 20 64 65 6C 61 79 20 33 35 0D 0A
590	Inputs: Line in 2: Delay (ms) = 36	set input 2 delay 36	73 65 74 20 69 6E 70 75 74 20 32 20 64 65 6C 61 79 20 33 36 0D 0A
591	Inputs: Line in 2: Delay (ms) = 37	set input 2 delay 37	73 65 74 20 69 6E 70 75 74 20 32 20 64 65 6C 61 79 20 33 37 0D 0A
592	Inputs: Line in 2: Delay (ms) = 38	set input 2 delay 38	73 65 74 20 69 6E 70 75 74 20 32 20 64 65 6C 61 79 20 33 38 0D 0A
593	Inputs: Line in 2: Delay (ms) = 39	set input 2 delay 39	73 65 74 20 69 6E 70 75 74 20 32 20 64 65 6C 61 79 20 33 39 0D 0A
594	Inputs: Line in 2: Delay (ms) = 40	set input 2 delay 40	73 65 74 20 69 6E 70 75 74 20 32 20 64 65 6C 61 79 20 34 30 0D 0A
595	Inputs: Line in 3: Delay (ms) = 0	set input 3 delay 0	73 65 74 20 69 6E 70 75 74 20 33 20 64 65 6C 61 79 20 30 0D 0A
596	Inputs: Line in 3: Delay (ms) = 1	set input 3 delay 1	73 65 74 20 69 6E 70 75 74 20 33 20 64 65 6C 61 79 20 31 0D 0A
597	Inputs: Line in 3: Delay (ms) = 2	set input 3 delay 2	73 65 74 20 69 6E 70 75 74 20 33 20 64 65 6C 61 79 20 32 0D 0A
598	Inputs: Line in 3: Delay (ms) = 3	set input 3 delay 3	73 65 74 20 69 6E 70 75 74 20 33 20 64 65 6C 61 79 20 33 0D 0A
599	Inputs: Line in 3: Delay (ms) = 4	set input 3 delay 4	73 65 74 20 69 6E 70 75 74 20 33 20 64 65 6C 61 79 20 34 0D 0A
600	Inputs: Line in 3: Delay (ms) = 5	set input 3 delay 5	73 65 74 20 69 6E 70 75 74 20 33 20 64 65 6C 61 79 20 35 0D 0A
601	Inputs: Line in 3: Delay (ms) = 6	set input 3 delay 6	73 65 74 20 69 6E 70 75 74 20 33 20 64 65 6C 61 79 20 36 0D 0A
602	Inputs: Line in 3: Delay (ms) = 7	set input 3 delay 7	73 65 74 20 69 6E 70 75 74 20 33 20 64 65 6C 61 79 20 37 0D 0A
603	Inputs: Line in 3: Delay (ms) = 8	set input 3 delay 8	73 65 74 20 69 6E 70 75 74 20 33 20 64 65 6C 61 79 20 38 0D 0A
604	Inputs: Line in 3: Delay (ms) = 9	set input 3 delay 9	73 65 74 20 69 6E 70 75 74 20 33 20 64 65 6C 61 79 20 39 0D 0A
605	Inputs: Line in 3: Delay (ms) = 10	set input 3 delay 10	73 65 74 20 69 6E 70 75 74 20 33 20 64 65 6C 61 79 20 31 30 0D 0A
606	Inputs: Line in 3: Delay (ms) = 11	set input 3 delay 11	73 65 74 20 69 6E 70 75 74 20 33 20 64 65 6C 61 79 20 31 31 0D 0A

607	Inputs: Line in 3: Delay (ms) = 12	`set input 3 delay 12`	`73 65 74 20 69 6E 70 75 74 20 33 20 64 65 6C 61 79 20 31 32 0D 0A`
608	Inputs: Line in 3: Delay (ms) = 13	`set input 3 delay 13`	`73 65 74 20 69 6E 70 75 74 20 33 20 64 65 6C 61 79 20 31 33 0D 0A`
609	Inputs: Line in 3: Delay (ms) = 14	`set input 3 delay 14`	`73 65 74 20 69 6E 70 75 74 20 33 20 64 65 6C 61 79 20 31 34 0D 0A`
610	Inputs: Line in 3: Delay (ms) = 15	`set input 3 delay 15`	`73 65 74 20 69 6E 70 75 74 20 33 20 64 65 6C 61 79 20 31 35 0D 0A`
611	Inputs: Line in 3: Delay (ms) = 16	`set input 3 delay 16`	`73 65 74 20 69 6E 70 75 74 20 33 20 64 65 6C 61 79 20 31 36 0D 0A`
612	Inputs: Line in 3: Delay (ms) = 17	`set input 3 delay 17`	`73 65 74 20 69 6E 70 75 74 20 33 20 64 65 6C 61 79 20 31 37 0D 0A`
613	Inputs: Line in 3: Delay (ms) = 18	`set input 3 delay 18`	`73 65 74 20 69 6E 70 75 74 20 33 20 64 65 6C 61 79 20 31 38 0D 0A`
614	Inputs: Line in 3: Delay (ms) = 19	`set input 3 delay 19`	`73 65 74 20 69 6E 70 75 74 20 33 20 64 65 6C 61 79 20 31 39 0D 0A`
615	Inputs: Line in 3: Delay (ms) = 20	`set input 3 delay 20`	`73 65 74 20 69 6E 70 75 74 20 33 20 64 65 6C 61 79 20 32 30 0D 0A`
616	Inputs: Line in 3: Delay (ms) = 21	`set input 3 delay 21`	`73 65 74 20 69 6E 70 75 74 20 33 20 64 65 6C 61 79 20 32 31 0D 0A`
617	Inputs: Line in 3: Delay (ms) = 22	`set input 3 delay 22`	`73 65 74 20 69 6E 70 75 74 20 33 20 64 65 6C 61 79 20 32 32 0D 0A`
618	Inputs: Line in 3: Delay (ms) = 23	`set input 3 delay 23`	`73 65 74 20 69 6E 70 75 74 20 33 20 64 65 6C 61 79 20 32 33 0D 0A`
619	Inputs: Line in 3: Delay (ms) = 24	`set input 3 delay 24`	`73 65 74 20 69 6E 70 75 74 20 33 20 64 65 6C 61 79 20 32 34 0D 0A`
620	Inputs: Line in 3: Delay (ms) = 25	`set input 3 delay 25`	`73 65 74 20 69 6E 70 75 74 20 33 20 64 65 6C 61 79 20 32 35 0D 0A`
621	Inputs: Line in 3: Delay (ms) = 26	`set input 3 delay 26`	`73 65 74 20 69 6E 70 75 74 20 33 20 64 65 6C 61 79 20 32 36 0D 0A`
622	Inputs: Line in 3: Delay (ms) = 27	`set input 3 delay 27`	`73 65 74 20 69 6E 70 75 74 20 33 20 64 65 6C 61 79 20 32 37 0D 0A`
623	Inputs: Line in 3: Delay (ms) = 28	`set input 3 delay 28`	`73 65 74 20 69 6E 70 75 74 20 33 20 64 65 6C 61 79 20 32 38 0D 0A`
624	Inputs: Line in 3: Delay (ms) = 29	`set input 3 delay 29`	`73 65 74 20 69 6E 70 75 74 20 33 20 64 65 6C 61 79 20 32 39 0D 0A`
625	Inputs: Line in 3: Delay (ms) = 30	`set input 3 delay 30`	`73 65 74 20 69 6E 70 75 74 20 33 20 64 65 6C 61 79 20 33 30 0D 0A`
626	Inputs: Line in 3: Delay (ms) = 31	`set input 3 delay 31`	`73 65 74 20 69 6E 70 75 74 20 33 20 64 65 6C 61 79 20 33 31 0D 0A`
627	Inputs: Line in 3: Delay (ms) = 32	`set input 3 delay 32`	`73 65 74 20 69 6E 70 75 74 20 33 20 64 65 6C 61 79 20 33 32 0D 0A`
628	Inputs: Line in 3: Delay (ms) = 33	`set input 3 delay 33`	`73 65 74 20 69 6E 70 75 74 20 33 20 64 65 6C 61 79 20 33 33 0D 0A`
629	Inputs: Line in 3: Delay (ms) = 34	`set input 3 delay 34`	`73 65 74 20 69 6E 70 75 74 20 33 20 64 65 6C 61 79 20 33 34 0D 0A`
630	Inputs: Line in 3: Delay (ms) = 35	`set input 3 delay 35`	`73 65 74 20 69 6E 70 75 74 20 33 20 64 65 6C 61 79 20 33 35 0D 0A`

631	Inputs: Line in 3: Delay (ms) = 36	`set input 3 delay 36`	`73 65 74 20 69 6E 70 75 74 20 33 20 64 65 6C 61 79 20 33 36 0D 0A`
632	Inputs: Line in 3: Delay (ms) = 37	`set input 3 delay 37`	`73 65 74 20 69 6E 70 75 74 20 33 20 64 65 6C 61 79 20 33 37 0D 0A`
633	Inputs: Line in 3: Delay (ms) = 38	`set input 3 delay 38`	`73 65 74 20 69 6E 70 75 74 20 33 20 64 65 6C 61 79 20 33 38 0D 0A`
634	Inputs: Line in 3: Delay (ms) = 39	`set input 3 delay 39`	`73 65 74 20 69 6E 70 75 74 20 33 20 64 65 6C 61 79 20 33 39 0D 0A`
635	Inputs: Line in 3: Delay (ms) = 40	`set input 3 delay 40`	`73 65 74 20 69 6E 70 75 74 20 33 20 64 65 6C 61 79 20 34 30 0D 0A`
636	Inputs: Line in 4: Delay (ms) = 0	`set input 4 delay 0`	`73 65 74 20 69 6E 70 75 74 20 34 20 64 65 6C 61 79 20 30 0D 0A`
637	Inputs: Line in 4: Delay (ms) = 1	`set input 4 delay 1`	`73 65 74 20 69 6E 70 75 74 20 34 20 64 65 6C 61 79 20 31 0D 0A`
638	Inputs: Line in 4: Delay (ms) = 2	`set input 4 delay 2`	`73 65 74 20 69 6E 70 75 74 20 34 20 64 65 6C 61 79 20 32 0D 0A`
639	Inputs: Line in 4: Delay (ms) = 3	`set input 4 delay 3`	`73 65 74 20 69 6E 70 75 74 20 34 20 64 65 6C 61 79 20 33 0D 0A`
640	Inputs: Line in 4: Delay (ms) = 4	`set input 4 delay 4`	`73 65 74 20 69 6E 70 75 74 20 34 20 64 65 6C 61 79 20 34 0D 0A`
641	Inputs: Line in 4: Delay (ms) = 5	`set input 4 delay 5`	`73 65 74 20 69 6E 70 75 74 20 34 20 64 65 6C 61 79 20 35 0D 0A`
642	Inputs: Line in 4: Delay (ms) = 6	`set input 4 delay 6`	`73 65 74 20 69 6E 70 75 74 20 34 20 64 65 6C 61 79 20 36 0D 0A`
643	Inputs: Line in 4: Delay (ms) = 7	`set input 4 delay 7`	`73 65 74 20 69 6E 70 75 74 20 34 20 64 65 6C 61 79 20 37 0D 0A`
644	Inputs: Line in 4: Delay (ms) = 8	`set input 4 delay 8`	`73 65 74 20 69 6E 70 75 74 20 34 20 64 65 6C 61 79 20 38 0D 0A`
645	Inputs: Line in 4: Delay (ms) = 9	`set input 4 delay 9`	`73 65 74 20 69 6E 70 75 74 20 34 20 64 65 6C 61 79 20 39 0D 0A`
646	Inputs: Line in 4: Delay (ms) = 10	`set input 4 delay 10`	`73 65 74 20 69 6E 70 75 74 20 34 20 64 65 6C 61 79 20 31 30 0D 0A`
647	Inputs: Line in 4: Delay (ms) = 11	`set input 4 delay 11`	`73 65 74 20 69 6E 70 75 74 20 34 20 64 65 6C 61 79 20 31 31 0D 0A`
648	Inputs: Line in 4: Delay (ms) = 12	`set input 4 delay 12`	`73 65 74 20 69 6E 70 75 74 20 34 20 64 65 6C 61 79 20 31 32 0D 0A`
649	Inputs: Line in 4: Delay (ms) = 13	`set input 4 delay 13`	`73 65 74 20 69 6E 70 75 74 20 34 20 64 65 6C 61 79 20 31 33 0D 0A`
650	Inputs: Line in 4: Delay (ms) = 14	`set input 4 delay 14`	`73 65 74 20 69 6E 70 75 74 20 34 20 64 65 6C 61 79 20 31 34 0D 0A`
651	Inputs: Line in 4: Delay (ms) = 15	`set input 4 delay 15`	`73 65 74 20 69 6E 70 75 74 20 34 20 64 65 6C 61 79 20 31 35 0D 0A`
652	Inputs: Line in 4: Delay (ms) = 16	`set input 4 delay 16`	`73 65 74 20 69 6E 70 75 74 20 34 20 64 65 6C 61 79 20 31 36 0D 0A`
653	Inputs: Line in 4: Delay (ms) = 17	`set input 4 delay 17`	`73 65 74 20 69 6E 70 75 74 20 34 20 64 65 6C 61 79 20 31 37 0D 0A`
654	Inputs: Line in 4: Delay (ms) = 18	`set input 4 delay 18`	`73 65 74 20 69 6E 70 75 74 20 34 20 64 65 6C 61 79 20 31 38 0D 0A`

655	Inputs: Line in 4: Delay (ms) = 19	`set input 4 delay 19`	`73 65 74 20 69 6E 70 75 74 20 34 20 64 65 6C 61 79 20 31 39 0D 0A`
656	Inputs: Line in 4: Delay (ms) = 20	`set input 4 delay 20`	`73 65 74 20 69 6E 70 75 74 20 34 20 64 65 6C 61 79 20 32 30 0D 0A`
657	Inputs: Line in 4: Delay (ms) = 21	`set input 4 delay 21`	`73 65 74 20 69 6E 70 75 74 20 34 20 64 65 6C 61 79 20 32 31 0D 0A`
658	Inputs: Line in 4: Delay (ms) = 22	`set input 4 delay 22`	`73 65 74 20 69 6E 70 75 74 20 34 20 64 65 6C 61 79 20 32 32 0D 0A`
659	Inputs: Line in 4: Delay (ms) = 23	`set input 4 delay 23`	`73 65 74 20 69 6E 70 75 74 20 34 20 64 65 6C 61 79 20 32 33 0D 0A`
660	Inputs: Line in 4: Delay (ms) = 24	`set input 4 delay 24`	`73 65 74 20 69 6E 70 75 74 20 34 20 64 65 6C 61 79 20 32 34 0D 0A`
661	Inputs: Line in 4: Delay (ms) = 25	`set input 4 delay 25`	`73 65 74 20 69 6E 70 75 74 20 34 20 64 65 6C 61 79 20 32 35 0D 0A`
662	Inputs: Line in 4: Delay (ms) = 26	`set input 4 delay 26`	`73 65 74 20 69 6E 70 75 74 20 34 20 64 65 6C 61 79 20 32 36 0D 0A`
663	Inputs: Line in 4: Delay (ms) = 27	`set input 4 delay 27`	`73 65 74 20 69 6E 70 75 74 20 34 20 64 65 6C 61 79 20 32 37 0D 0A`
664	Inputs: Line in 4: Delay (ms) = 28	`set input 4 delay 28`	`73 65 74 20 69 6E 70 75 74 20 34 20 64 65 6C 61 79 20 32 38 0D 0A`
665	Inputs: Line in 4: Delay (ms) = 29	`set input 4 delay 29`	`73 65 74 20 69 6E 70 75 74 20 34 20 64 65 6C 61 79 20 32 39 0D 0A`
666	Inputs: Line in 4: Delay (ms) = 30	`set input 4 delay 30`	`73 65 74 20 69 6E 70 75 74 20 34 20 64 65 6C 61 79 20 33 30 0D 0A`
667	Inputs: Line in 4: Delay (ms) = 31	`set input 4 delay 31`	`73 65 74 20 69 6E 70 75 74 20 34 20 64 65 6C 61 79 20 33 31 0D 0A`
668	Inputs: Line in 4: Delay (ms) = 32	`set input 4 delay 32`	`73 65 74 20 69 6E 70 75 74 20 34 20 64 65 6C 61 79 20 33 32 0D 0A`
669	Inputs: Line in 4: Delay (ms) = 33	`set input 4 delay 33`	`73 65 74 20 69 6E 70 75 74 20 34 20 64 65 6C 61 79 20 33 33 0D 0A`
670	Inputs: Line in 4: Delay (ms) = 34	`set input 4 delay 34`	`73 65 74 20 69 6E 70 75 74 20 34 20 64 65 6C 61 79 20 33 34 0D 0A`
671	Inputs: Line in 4: Delay (ms) = 35	`set input 4 delay 35`	`73 65 74 20 69 6E 70 75 74 20 34 20 64 65 6C 61 79 20 33 35 0D 0A`
672	Inputs: Line in 4: Delay (ms) = 36	`set input 4 delay 36`	`73 65 74 20 69 6E 70 75 74 20 34 20 64 65 6C 61 79 20 33 36 0D 0A`
673	Inputs: Line in 4: Delay (ms) = 37	`set input 4 delay 37`	`73 65 74 20 69 6E 70 75 74 20 34 20 64 65 6C 61 79 20 33 37 0D 0A`
674	Inputs: Line in 4: Delay (ms) = 38	`set input 4 delay 38`	`73 65 74 20 69 6E 70 75 74 20 34 20 64 65 6C 61 79 20 33 38 0D 0A`
675	Inputs: Line in 4: Delay (ms) = 39	`set input 4 delay 39`	`73 65 74 20 69 6E 70 75 74 20 34 20 64 65 6C 61 79 20 33 39 0D 0A`
676	Inputs: Line in 4: Delay (ms) = 40	`set input 4 delay 40`	`73 65 74 20 69 6E 70 75 74 20 34 20 64 65 6C 61 79 20 34 30 0D 0A`
677	Inputs: Line in 5: Delay (ms) = 0	`set input 5 delay 0`	`73 65 74 20 69 6E 70 75 74 20 35 20 64 65 6C 61 79 20 30 0D 0A`
678	Inputs: Line in 5: Delay (ms) = 1	`set input 5 delay 1`	`73 65 74 20 69 6E 70 75 74 20 35 20 64 65 6C 61 79 20 31 0D 0A`

679	Inputs: Line in 5: Delay (ms) = 2	set input 5 delay 2	73 65 74 20 69 6E 70 75 74 20 35 20 64 65 6C 61 79 20 32 0D 0A
680	Inputs: Line in 5: Delay (ms) = 3	set input 5 delay 3	73 65 74 20 69 6E 70 75 74 20 35 20 64 65 6C 61 79 20 33 0D 0A
681	Inputs: Line in 5: Delay (ms) = 4	set input 5 delay 4	73 65 74 20 69 6E 70 75 74 20 35 20 64 65 6C 61 79 20 34 0D 0A
682	Inputs: Line in 5: Delay (ms) = 5	set input 5 delay 5	73 65 74 20 69 6E 70 75 74 20 35 20 64 65 6C 61 79 20 35 0D 0A
683	Inputs: Line in 5: Delay (ms) = 6	set input 5 delay 6	73 65 74 20 69 6E 70 75 74 20 35 20 64 65 6C 61 79 20 36 0D 0A
684	Inputs: Line in 5: Delay (ms) = 7	set input 5 delay 7	73 65 74 20 69 6E 70 75 74 20 35 20 64 65 6C 61 79 20 37 0D 0A
685	Inputs: Line in 5: Delay (ms) = 8	set input 5 delay 8	73 65 74 20 69 6E 70 75 74 20 35 20 64 65 6C 61 79 20 38 0D 0A
686	Inputs: Line in 5: Delay (ms) = 9	set input 5 delay 9	73 65 74 20 69 6E 70 75 74 20 35 20 64 65 6C 61 79 20 39 0D 0A
687	Inputs: Line in 5: Delay (ms) = 10	set input 5 delay 10	73 65 74 20 69 6E 70 75 74 20 35 20 64 65 6C 61 79 20 31 30 0D 0A
688	Inputs: Line in 5: Delay (ms) = 11	set input 5 delay 11	73 65 74 20 69 6E 70 75 74 20 35 20 64 65 6C 61 79 20 31 31 0D 0A
689	Inputs: Line in 5: Delay (ms) = 12	set input 5 delay 12	73 65 74 20 69 6E 70 75 74 20 35 20 64 65 6C 61 79 20 31 32 0D 0A
690	Inputs: Line in 5: Delay (ms) = 13	set input 5 delay 13	73 65 74 20 69 6E 70 75 74 20 35 20 64 65 6C 61 79 20 31 33 0D 0A
691	Inputs: Line in 5: Delay (ms) = 14	set input 5 delay 14	73 65 74 20 69 6E 70 75 74 20 35 20 64 65 6C 61 79 20 31 34 0D 0A
692	Inputs: Line in 5: Delay (ms) = 15	set input 5 delay 15	73 65 74 20 69 6E 70 75 74 20 35 20 64 65 6C 61 79 20 31 35 0D 0A
693	Inputs: Line in 5: Delay (ms) = 16	set input 5 delay 16	73 65 74 20 69 6E 70 75 74 20 35 20 64 65 6C 61 79 20 31 36 0D 0A
694	Inputs: Line in 5: Delay (ms) = 17	set input 5 delay 17	73 65 74 20 69 6E 70 75 74 20 35 20 64 65 6C 61 79 20 31 37 0D 0A
695	Inputs: Line in 5: Delay (ms) = 18	set input 5 delay 18	73 65 74 20 69 6E 70 75 74 20 35 20 64 65 6C 61 79 20 31 38 0D 0A
696	Inputs: Line in 5: Delay (ms) = 19	set input 5 delay 19	73 65 74 20 69 6E 70 75 74 20 35 20 64 65 6C 61 79 20 31 39 0D 0A
697	Inputs: Line in 5: Delay (ms) = 20	set input 5 delay 20	73 65 74 20 69 6E 70 75 74 20 35 20 64 65 6C 61 79 20 32 30 0D 0A
698	Inputs: Line in 5: Delay (ms) = 21	set input 5 delay 21	73 65 74 20 69 6E 70 75 74 20 35 20 64 65 6C 61 79 20 32 31 0D 0A
699	Inputs: Line in 5: Delay (ms) = 22	set input 5 delay 22	73 65 74 20 69 6E 70 75 74 20 35 20 64 65 6C 61 79 20 32 32 0D 0A
700	Inputs: Line in 5: Delay (ms) = 23	set input 5 delay 23	73 65 74 20 69 6E 70 75 74 20 35 20 64 65 6C 61 79 20 32 33 0D 0A
701	Inputs: Line in 5: Delay (ms) = 24	set input 5 delay 24	73 65 74 20 69 6E 70 75 74 20 35 20 64 65 6C 61 79 20 32 34 0D 0A
702	Inputs: Line in 5: Delay (ms) = 25	set input 5 delay 25	73 65 74 20 69 6E 70 75 74 20 35 20 64 65 6C 61 79 20 32 35 0D 0A

703	Inputs: Line in 5: Delay (ms) = 26	`set input 5 delay 26`	`73 65 74 20 69 6E 70 75 74 20 35 20 64 65 6C 61 79 20 32 36 0D 0A`
704	Inputs: Line in 5: Delay (ms) = 27	`set input 5 delay 27`	`73 65 74 20 69 6E 70 75 74 20 35 20 64 65 6C 61 79 20 32 37 0D 0A`
705	Inputs: Line in 5: Delay (ms) = 28	`set input 5 delay 28`	`73 65 74 20 69 6E 70 75 74 20 35 20 64 65 6C 61 79 20 32 38 0D 0A`
706	Inputs: Line in 5: Delay (ms) = 29	`set input 5 delay 29`	`73 65 74 20 69 6E 70 75 74 20 35 20 64 65 6C 61 79 20 32 39 0D 0A`
707	Inputs: Line in 5: Delay (ms) = 30	`set input 5 delay 30`	`73 65 74 20 69 6E 70 75 74 20 35 20 64 65 6C 61 79 20 33 30 0D 0A`
708	Inputs: Line in 5: Delay (ms) = 31	`set input 5 delay 31`	`73 65 74 20 69 6E 70 75 74 20 35 20 64 65 6C 61 79 20 33 31 0D 0A`
709	Inputs: Line in 5: Delay (ms) = 32	`set input 5 delay 32`	`73 65 74 20 69 6E 70 75 74 20 35 20 64 65 6C 61 79 20 33 32 0D 0A`
710	Inputs: Line in 5: Delay (ms) = 33	`set input 5 delay 33`	`73 65 74 20 69 6E 70 75 74 20 35 20 64 65 6C 61 79 20 33 33 0D 0A`
711	Inputs: Line in 5: Delay (ms) = 34	`set input 5 delay 34`	`73 65 74 20 69 6E 70 75 74 20 35 20 64 65 6C 61 79 20 33 34 0D 0A`
712	Inputs: Line in 5: Delay (ms) = 35	`set input 5 delay 35`	`73 65 74 20 69 6E 70 75 74 20 35 20 64 65 6C 61 79 20 33 35 0D 0A`
713	Inputs: Line in 5: Delay (ms) = 36	`set input 5 delay 36`	`73 65 74 20 69 6E 70 75 74 20 35 20 64 65 6C 61 79 20 33 36 0D 0A`
714	Inputs: Line in 5: Delay (ms) = 37	`set input 5 delay 37`	`73 65 74 20 69 6E 70 75 74 20 35 20 64 65 6C 61 79 20 33 37 0D 0A`
715	Inputs: Line in 5: Delay (ms) = 38	`set input 5 delay 38`	`73 65 74 20 69 6E 70 75 74 20 35 20 64 65 6C 61 79 20 33 38 0D 0A`
716	Inputs: Line in 5: Delay (ms) = 39	`set input 5 delay 39`	`73 65 74 20 69 6E 70 75 74 20 35 20 64 65 6C 61 79 20 33 39 0D 0A`
717	Inputs: Line in 5: Delay (ms) = 40	`set input 5 delay 40`	`73 65 74 20 69 6E 70 75 74 20 35 20 64 65 6C 61 79 20 34 30 0D 0A`
718	Inputs: Line in 6: Delay (ms) = 0	`set input 6 delay 0`	`73 65 74 20 69 6E 70 75 74 20 36 20 64 65 6C 61 79 20 30 0D 0A`
719	Inputs: Line in 6: Delay (ms) = 1	`set input 6 delay 1`	`73 65 74 20 69 6E 70 75 74 20 36 20 64 65 6C 61 79 20 31 0D 0A`
720	Inputs: Line in 6: Delay (ms) = 2	`set input 6 delay 2`	`73 65 74 20 69 6E 70 75 74 20 36 20 64 65 6C 61 79 20 32 0D 0A`
721	Inputs: Line in 6: Delay (ms) = 3	`set input 6 delay 3`	`73 65 74 20 69 6E 70 75 74 20 36 20 64 65 6C 61 79 20 33 0D 0A`
722	Inputs: Line in 6: Delay (ms) = 4	`set input 6 delay 4`	`73 65 74 20 69 6E 70 75 74 20 36 20 64 65 6C 61 79 20 34 0D 0A`
723	Inputs: Line in 6: Delay (ms) = 5	`set input 6 delay 5`	`73 65 74 20 69 6E 70 75 74 20 36 20 64 65 6C 61 79 20 35 0D 0A`
724	Inputs: Line in 6: Delay (ms) = 6	`set input 6 delay 6`	`73 65 74 20 69 6E 70 75 74 20 36 20 64 65 6C 61 79 20 36 0D 0A`
725	Inputs: Line in 6: Delay (ms) = 7	`set input 6 delay 7`	`73 65 74 20 69 6E 70 75 74 20 36 20 64 65 6C 61 79 20 37 0D 0A`
726	Inputs: Line in 6: Delay (ms) = 8	`set input 6 delay 8`	`73 65 74 20 69 6E 70 75 74 20 36 20 64 65 6C 61 79 20 38 0D 0A`

727	Inputs: Line in 6: Delay (ms) = 9	`set input 6 delay 9`	`73 65 74 20 69 6E 70 75 74 20 36 20 64 65 6C 61 79 20 39 0D 0A`
728	Inputs: Line in 6: Delay (ms) = 10	`set input 6 delay 10`	`73 65 74 20 69 6E 70 75 74 20 36 20 64 65 6C 61 79 20 31 30 0D 0A`
729	Inputs: Line in 6: Delay (ms) = 11	`set input 6 delay 11`	`73 65 74 20 69 6E 70 75 74 20 36 20 64 65 6C 61 79 20 31 31 0D 0A`
730	Inputs: Line in 6: Delay (ms) = 12	`set input 6 delay 12`	`73 65 74 20 69 6E 70 75 74 20 36 20 64 65 6C 61 79 20 31 32 0D 0A`
731	Inputs: Line in 6: Delay (ms) = 13	`set input 6 delay 13`	`73 65 74 20 69 6E 70 75 74 20 36 20 64 65 6C 61 79 20 31 33 0D 0A`
732	Inputs: Line in 6: Delay (ms) = 14	`set input 6 delay 14`	`73 65 74 20 69 6E 70 75 74 20 36 20 64 65 6C 61 79 20 31 34 0D 0A`
733	Inputs: Line in 6: Delay (ms) = 15	`set input 6 delay 15`	`73 65 74 20 69 6E 70 75 74 20 36 20 64 65 6C 61 79 20 31 35 0D 0A`
734	Inputs: Line in 6: Delay (ms) = 16	`set input 6 delay 16`	`73 65 74 20 69 6E 70 75 74 20 36 20 64 65 6C 61 79 20 31 36 0D 0A`
735	Inputs: Line in 6: Delay (ms) = 17	`set input 6 delay 17`	`73 65 74 20 69 6E 70 75 74 20 36 20 64 65 6C 61 79 20 31 37 0D 0A`
736	Inputs: Line in 6: Delay (ms) = 18	`set input 6 delay 18`	`73 65 74 20 69 6E 70 75 74 20 36 20 64 65 6C 61 79 20 31 38 0D 0A`
737	Inputs: Line in 6: Delay (ms) = 19	`set input 6 delay 19`	`73 65 74 20 69 6E 70 75 74 20 36 20 64 65 6C 61 79 20 31 39 0D 0A`
738	Inputs: Line in 6: Delay (ms) = 20	`set input 6 delay 20`	`73 65 74 20 69 6E 70 75 74 20 36 20 64 65 6C 61 79 20 32 30 0D 0A`
739	Inputs: Line in 6: Delay (ms) = 21	`set input 6 delay 21`	`73 65 74 20 69 6E 70 75 74 20 36 20 64 65 6C 61 79 20 32 31 0D 0A`
740	Inputs: Line in 6: Delay (ms) = 22	`set input 6 delay 22`	`73 65 74 20 69 6E 70 75 74 20 36 20 64 65 6C 61 79 20 32 32 0D 0A`
741	Inputs: Line in 6: Delay (ms) = 23	`set input 6 delay 23`	`73 65 74 20 69 6E 70 75 74 20 36 20 64 65 6C 61 79 20 32 33 0D 0A`
742	Inputs: Line in 6: Delay (ms) = 24	`set input 6 delay 24`	`73 65 74 20 69 6E 70 75 74 20 36 20 64 65 6C 61 79 20 32 34 0D 0A`
743	Inputs: Line in 6: Delay (ms) = 25	`set input 6 delay 25`	`73 65 74 20 69 6E 70 75 74 20 36 20 64 65 6C 61 79 20 32 35 0D 0A`
744	Inputs: Line in 6: Delay (ms) = 26	`set input 6 delay 26`	`73 65 74 20 69 6E 70 75 74 20 36 20 64 65 6C 61 79 20 32 36 0D 0A`
745	Inputs: Line in 6: Delay (ms) = 27	`set input 6 delay 27`	`73 65 74 20 69 6E 70 75 74 20 36 20 64 65 6C 61 79 20 32 37 0D 0A`
746	Inputs: Line in 6: Delay (ms) = 28	`set input 6 delay 28`	`73 65 74 20 69 6E 70 75 74 20 36 20 64 65 6C 61 79 20 32 38 0D 0A`
747	Inputs: Line in 6: Delay (ms) = 29	`set input 6 delay 29`	`73 65 74 20 69 6E 70 75 74 20 36 20 64 65 6C 61 79 20 32 39 0D 0A`
748	Inputs: Line in 6: Delay (ms) = 30	`set input 6 delay 30`	`73 65 74 20 69 6E 70 75 74 20 36 20 64 65 6C 61 79 20 33 30 0D 0A`
749	Inputs: Line in 6: Delay (ms) = 31	`set input 6 delay 31`	`73 65 74 20 69 6E 70 75 74 20 36 20 64 65 6C 61 79 20 33 31 0D 0A`
750	Inputs: Line in 6: Delay (ms) = 32	`set input 6 delay 32`	`73 65 74 20 69 6E 70 75 74 20 36 20 64 65 6C 61 79 20 33 32 0D 0A`

751	Inputs: Line in 6: Delay (ms) = 33	`set input 6 delay 33`	`73 65 74 20 69 6E 70 75 74 20 36 20 64 65 6C 61 79 20 33 33 0D 0A`
752	Inputs: Line in 6: Delay (ms) = 34	`set input 6 delay 34`	`73 65 74 20 69 6E 70 75 74 20 36 20 64 65 6C 61 79 20 33 34 0D 0A`
753	Inputs: Line in 6: Delay (ms) = 35	`set input 6 delay 35`	`73 65 74 20 69 6E 70 75 74 20 36 20 64 65 6C 61 79 20 33 35 0D 0A`
754	Inputs: Line in 6: Delay (ms) = 36	`set input 6 delay 36`	`73 65 74 20 69 6E 70 75 74 20 36 20 64 65 6C 61 79 20 33 36 0D 0A`
755	Inputs: Line in 6: Delay (ms) = 37	`set input 6 delay 37`	`73 65 74 20 69 6E 70 75 74 20 36 20 64 65 6C 61 79 20 33 37 0D 0A`
756	Inputs: Line in 6: Delay (ms) = 38	`set input 6 delay 38`	`73 65 74 20 69 6E 70 75 74 20 36 20 64 65 6C 61 79 20 33 38 0D 0A`
757	Inputs: Line in 6: Delay (ms) = 39	`set input 6 delay 39`	`73 65 74 20 69 6E 70 75 74 20 36 20 64 65 6C 61 79 20 33 39 0D 0A`
758	Inputs: Line in 6: Delay (ms) = 40	`set input 6 delay 40`	`73 65 74 20 69 6E 70 75 74 20 36 20 64 65 6C 61 79 20 34 30 0D 0A`
759	Inputs: Line in 7: Delay (ms) = 0	`set input 7 delay 0`	`73 65 74 20 69 6E 70 75 74 20 37 20 64 65 6C 61 79 20 30 0D 0A`
760	Inputs: Line in 7: Delay (ms) = 1	`set input 7 delay 1`	`73 65 74 20 69 6E 70 75 74 20 37 20 64 65 6C 61 79 20 31 0D 0A`
761	Inputs: Line in 7: Delay (ms) = 2	`set input 7 delay 2`	`73 65 74 20 69 6E 70 75 74 20 37 20 64 65 6C 61 79 20 32 0D 0A`
762	Inputs: Line in 7: Delay (ms) = 3	`set input 7 delay 3`	`73 65 74 20 69 6E 70 75 74 20 37 20 64 65 6C 61 79 20 33 0D 0A`
763	Inputs: Line in 7: Delay (ms) = 4	`set input 7 delay 4`	`73 65 74 20 69 6E 70 75 74 20 37 20 64 65 6C 61 79 20 34 0D 0A`
764	Inputs: Line in 7: Delay (ms) = 5	`set input 7 delay 5`	`73 65 74 20 69 6E 70 75 74 20 37 20 64 65 6C 61 79 20 35 0D 0A`
765	Inputs: Line in 7: Delay (ms) = 6	`set input 7 delay 6`	`73 65 74 20 69 6E 70 75 74 20 37 20 64 65 6C 61 79 20 36 0D 0A`
766	Inputs: Line in 7: Delay (ms) = 7	`set input 7 delay 7`	`73 65 74 20 69 6E 70 75 74 20 37 20 64 65 6C 61 79 20 37 0D 0A`
767	Inputs: Line in 7: Delay (ms) = 8	`set input 7 delay 8`	`73 65 74 20 69 6E 70 75 74 20 37 20 64 65 6C 61 79 20 38 0D 0A`
768	Inputs: Line in 7: Delay (ms) = 9	`set input 7 delay 9`	`73 65 74 20 69 6E 70 75 74 20 37 20 64 65 6C 61 79 20 39 0D 0A`
769	Inputs: Line in 7: Delay (ms) = 10	`set input 7 delay 10`	`73 65 74 20 69 6E 70 75 74 20 37 20 64 65 6C 61 79 20 31 30 0D 0A`
770	Inputs: Line in 7: Delay (ms) = 11	`set input 7 delay 11`	`73 65 74 20 69 6E 70 75 74 20 37 20 64 65 6C 61 79 20 31 31 0D 0A`
771	Inputs: Line in 7: Delay (ms) = 12	`set input 7 delay 12`	`73 65 74 20 69 6E 70 75 74 20 37 20 64 65 6C 61 79 20 31 32 0D 0A`
772	Inputs: Line in 7: Delay (ms) = 13	`set input 7 delay 13`	`73 65 74 20 69 6E 70 75 74 20 37 20 64 65 6C 61 79 20 31 33 0D 0A`
773	Inputs: Line in 7: Delay (ms) = 14	`set input 7 delay 14`	`73 65 74 20 69 6E 70 75 74 20 37 20 64 65 6C 61 79 20 31 34 0D 0A`
774	Inputs: Line in 7: Delay (ms) = 15	`set input 7 delay 15`	`73 65 74 20 69 6E 70 75 74 20 37 20 64 65 6C 61 79 20 31 35 0D 0A`

775	Inputs: Line in 7: Delay (ms) = 16	set input 7 delay 16	73 65 74 20 69 6E 70 75 74 20 37 20 64 65 6C 61 79 20 31 36 0D 0A
776	Inputs: Line in 7: Delay (ms) = 17	set input 7 delay 17	73 65 74 20 69 6E 70 75 74 20 37 20 64 65 6C 61 79 20 31 37 0D 0A
777	Inputs: Line in 7: Delay (ms) = 18	set input 7 delay 18	73 65 74 20 69 6E 70 75 74 20 37 20 64 65 6C 61 79 20 31 38 0D 0A
778	Inputs: Line in 7: Delay (ms) = 19	set input 7 delay 19	73 65 74 20 69 6E 70 75 74 20 37 20 64 65 6C 61 79 20 31 39 0D 0A
779	Inputs: Line in 7: Delay (ms) = 20	set input 7 delay 20	73 65 74 20 69 6E 70 75 74 20 37 20 64 65 6C 61 79 20 32 30 0D 0A
780	Inputs: Line in 7: Delay (ms) = 21	set input 7 delay 21	73 65 74 20 69 6E 70 75 74 20 37 20 64 65 6C 61 79 20 32 31 0D 0A
781	Inputs: Line in 7: Delay (ms) = 22	set input 7 delay 22	73 65 74 20 69 6E 70 75 74 20 37 20 64 65 6C 61 79 20 32 32 0D 0A
782	Inputs: Line in 7: Delay (ms) = 23	set input 7 delay 23	73 65 74 20 69 6E 70 75 74 20 37 20 64 65 6C 61 79 20 32 33 0D 0A
783	Inputs: Line in 7: Delay (ms) = 24	set input 7 delay 24	73 65 74 20 69 6E 70 75 74 20 37 20 64 65 6C 61 79 20 32 34 0D 0A
784	Inputs: Line in 7: Delay (ms) = 25	set input 7 delay 25	73 65 74 20 69 6E 70 75 74 20 37 20 64 65 6C 61 79 20 32 35 0D 0A
785	Inputs: Line in 7: Delay (ms) = 26	set input 7 delay 26	73 65 74 20 69 6E 70 75 74 20 37 20 64 65 6C 61 79 20 32 36 0D 0A
786	Inputs: Line in 7: Delay (ms) = 27	set input 7 delay 27	73 65 74 20 69 6E 70 75 74 20 37 20 64 65 6C 61 79 20 32 37 0D 0A
787	Inputs: Line in 7: Delay (ms) = 28	set input 7 delay 28	73 65 74 20 69 6E 70 75 74 20 37 20 64 65 6C 61 79 20 32 38 0D 0A
788	Inputs: Line in 7: Delay (ms) = 29	set input 7 delay 29	73 65 74 20 69 6E 70 75 74 20 37 20 64 65 6C 61 79 20 32 39 0D 0A
789	Inputs: Line in 7: Delay (ms) = 30	set input 7 delay 30	73 65 74 20 69 6E 70 75 74 20 37 20 64 65 6C 61 79 20 33 30 0D 0A
790	Inputs: Line in 7: Delay (ms) = 31	set input 7 delay 31	73 65 74 20 69 6E 70 75 74 20 37 20 64 65 6C 61 79 20 33 31 0D 0A
791	Inputs: Line in 7: Delay (ms) = 32	set input 7 delay 32	73 65 74 20 69 6E 70 75 74 20 37 20 64 65 6C 61 79 20 33 32 0D 0A
792	Inputs: Line in 7: Delay (ms) = 33	set input 7 delay 33	73 65 74 20 69 6E 70 75 74 20 37 20 64 65 6C 61 79 20 33 33 0D 0A
793	Inputs: Line in 7: Delay (ms) = 34	set input 7 delay 34	73 65 74 20 69 6E 70 75 74 20 37 20 64 65 6C 61 79 20 33 34 0D 0A
794	Inputs: Line in 7: Delay (ms) = 35	set input 7 delay 35	73 65 74 20 69 6E 70 75 74 20 37 20 64 65 6C 61 79 20 33 35 0D 0A
795	Inputs: Line in 7: Delay (ms) = 36	set input 7 delay 36	73 65 74 20 69 6E 70 75 74 20 37 20 64 65 6C 61 79 20 33 36 0D 0A
796	Inputs: Line in 7: Delay (ms) = 37	set input 7 delay 37	73 65 74 20 69 6E 70 75 74 20 37 20 64 65 6C 61 79 20 33 37 0D 0A
797	Inputs: Line in 7: Delay (ms) = 38	set input 7 delay 38	73 65 74 20 69 6E 70 75 74 20 37 20 64 65 6C 61 79 20 33 38 0D 0A
798	Inputs: Line in 7: Delay (ms) = 39	set input 7 delay 39	73 65 74 20 69 6E 70 75 74 20 37 20 64 65 6C 61 79 20 33 39 0D 0A

799	Inputs: Line in 7: Delay (ms) = 40	`set input 7 delay 40`	`73 65 74 20 69 6E 70 75 74 20 37 20 64 65 6C 61 79 20 34 30 0D 0A`
800	Inputs: Line in 8: Delay (ms) = 0	`set input 8 delay 0`	`73 65 74 20 69 6E 70 75 74 20 38 20 64 65 6C 61 79 20 30 0D 0A`
801	Inputs: Line in 8: Delay (ms) = 1	`set input 8 delay 1`	`73 65 74 20 69 6E 70 75 74 20 38 20 64 65 6C 61 79 20 31 0D 0A`
802	Inputs: Line in 8: Delay (ms) = 2	`set input 8 delay 2`	`73 65 74 20 69 6E 70 75 74 20 38 20 64 65 6C 61 79 20 32 0D 0A`
803	Inputs: Line in 8: Delay (ms) = 3	`set input 8 delay 3`	`73 65 74 20 69 6E 70 75 74 20 38 20 64 65 6C 61 79 20 33 0D 0A`
804	Inputs: Line in 8: Delay (ms) = 4	`set input 8 delay 4`	`73 65 74 20 69 6E 70 75 74 20 38 20 64 65 6C 61 79 20 34 0D 0A`
805	Inputs: Line in 8: Delay (ms) = 5	`set input 8 delay 5`	`73 65 74 20 69 6E 70 75 74 20 38 20 64 65 6C 61 79 20 35 0D 0A`
806	Inputs: Line in 8: Delay (ms) = 6	`set input 8 delay 6`	`73 65 74 20 69 6E 70 75 74 20 38 20 64 65 6C 61 79 20 36 0D 0A`
807	Inputs: Line in 8: Delay (ms) = 7	`set input 8 delay 7`	`73 65 74 20 69 6E 70 75 74 20 38 20 64 65 6C 61 79 20 37 0D 0A`
808	Inputs: Line in 8: Delay (ms) = 8	`set input 8 delay 8`	`73 65 74 20 69 6E 70 75 74 20 38 20 64 65 6C 61 79 20 38 0D 0A`
809	Inputs: Line in 8: Delay (ms) = 9	`set input 8 delay 9`	`73 65 74 20 69 6E 70 75 74 20 38 20 64 65 6C 61 79 20 39 0D 0A`
810	Inputs: Line in 8: Delay (ms) = 10	`set input 8 delay 10`	`73 65 74 20 69 6E 70 75 74 20 38 20 64 65 6C 61 79 20 31 30 0D 0A`
811	Inputs: Line in 8: Delay (ms) = 11	`set input 8 delay 11`	`73 65 74 20 69 6E 70 75 74 20 38 20 64 65 6C 61 79 20 31 31 0D 0A`
812	Inputs: Line in 8: Delay (ms) = 12	`set input 8 delay 12`	`73 65 74 20 69 6E 70 75 74 20 38 20 64 65 6C 61 79 20 31 32 0D 0A`
813	Inputs: Line in 8: Delay (ms) = 13	`set input 8 delay 13`	`73 65 74 20 69 6E 70 75 74 20 38 20 64 65 6C 61 79 20 31 33 0D 0A`
814	Inputs: Line in 8: Delay (ms) = 14	`set input 8 delay 14`	`73 65 74 20 69 6E 70 75 74 20 38 20 64 65 6C 61 79 20 31 34 0D 0A`
815	Inputs: Line in 8: Delay (ms) = 15	`set input 8 delay 15`	`73 65 74 20 69 6E 70 75 74 20 38 20 64 65 6C 61 79 20 31 35 0D 0A`
816	Inputs: Line in 8: Delay (ms) = 16	`set input 8 delay 16`	`73 65 74 20 69 6E 70 75 74 20 38 20 64 65 6C 61 79 20 31 36 0D 0A`
817	Inputs: Line in 8: Delay (ms) = 17	`set input 8 delay 17`	`73 65 74 20 69 6E 70 75 74 20 38 20 64 65 6C 61 79 20 31 37 0D 0A`
818	Inputs: Line in 8: Delay (ms) = 18	`set input 8 delay 18`	`73 65 74 20 69 6E 70 75 74 20 38 20 64 65 6C 61 79 20 31 38 0D 0A`
819	Inputs: Line in 8: Delay (ms) = 19	`set input 8 delay 19`	`73 65 74 20 69 6E 70 75 74 20 38 20 64 65 6C 61 79 20 31 39 0D 0A`
820	Inputs: Line in 8: Delay (ms) = 20	`set input 8 delay 20`	`73 65 74 20 69 6E 70 75 74 20 38 20 64 65 6C 61 79 20 32 30 0D 0A`
821	Inputs: Line in 8: Delay (ms) = 21	`set input 8 delay 21`	`73 65 74 20 69 6E 70 75 74 20 38 20 64 65 6C 61 79 20 32 31 0D 0A`
822	Inputs: Line in 8: Delay (ms) = 22	`set input 8 delay 22`	`73 65 74 20 69 6E 70 75 74 20 38 20 64 65 6C 61 79 20 32 32 0D 0A`

823	Inputs: Line in 8: Delay (ms) = 23	set input 8 delay 23	73 65 74 20 69 6E 70 75 74 20 38 20 64 65 6C 61 79 20 32 33 0D 0A
824	Inputs: Line in 8: Delay (ms) = 24	set input 8 delay 24	73 65 74 20 69 6E 70 75 74 20 38 20 64 65 6C 61 79 20 32 34 0D 0A
825	Inputs: Line in 8: Delay (ms) = 25	set input 8 delay 25	73 65 74 20 69 6E 70 75 74 20 38 20 64 65 6C 61 79 20 32 35 0D 0A
826	Inputs: Line in 8: Delay (ms) = 26	set input 8 delay 26	73 65 74 20 69 6E 70 75 74 20 38 20 64 65 6C 61 79 20 32 36 0D 0A
827	Inputs: Line in 8: Delay (ms) = 27	set input 8 delay 27	73 65 74 20 69 6E 70 75 74 20 38 20 64 65 6C 61 79 20 32 37 0D 0A
828	Inputs: Line in 8: Delay (ms) = 28	set input 8 delay 28	73 65 74 20 69 6E 70 75 74 20 38 20 64 65 6C 61 79 20 32 38 0D 0A
829	Inputs: Line in 8: Delay (ms) = 29	set input 8 delay 29	73 65 74 20 69 6E 70 75 74 20 38 20 64 65 6C 61 79 20 32 39 0D 0A
830	Inputs: Line in 8: Delay (ms) = 30	set input 8 delay 30	73 65 74 20 69 6E 70 75 74 20 38 20 64 65 6C 61 79 20 33 30 0D 0A
831	Inputs: Line in 8: Delay (ms) = 31	set input 8 delay 31	73 65 74 20 69 6E 70 75 74 20 38 20 64 65 6C 61 79 20 33 31 0D 0A
832	Inputs: Line in 8: Delay (ms) = 32	set input 8 delay 32	73 65 74 20 69 6E 70 75 74 20 38 20 64 65 6C 61 79 20 33 32 0D 0A
833	Inputs: Line in 8: Delay (ms) = 33	set input 8 delay 33	73 65 74 20 69 6E 70 75 74 20 38 20 64 65 6C 61 79 20 33 33 0D 0A
834	Inputs: Line in 8: Delay (ms) = 34	set input 8 delay 34	73 65 74 20 69 6E 70 75 74 20 38 20 64 65 6C 61 79 20 33 34 0D 0A
835	Inputs: Line in 8: Delay (ms) = 35	set input 8 delay 35	73 65 74 20 69 6E 70 75 74 20 38 20 64 65 6C 61 79 20 33 35 0D 0A
836	Inputs: Line in 8: Delay (ms) = 36	set input 8 delay 36	73 65 74 20 69 6E 70 75 74 20 38 20 64 65 6C 61 79 20 33 36 0D 0A
837	Inputs: Line in 8: Delay (ms) = 37	set input 8 delay 37	73 65 74 20 69 6E 70 75 74 20 38 20 64 65 6C 61 79 20 33 37 0D 0A
838	Inputs: Line in 8: Delay (ms) = 38	set input 8 delay 38	73 65 74 20 69 6E 70 75 74 20 38 20 64 65 6C 61 79 20 33 38 0D 0A
839	Inputs: Line in 8: Delay (ms) = 39	set input 8 delay 39	73 65 74 20 69 6E 70 75 74 20 38 20 64 65 6C 61 79 20 33 39 0D 0A
840	Inputs: Line in 8: Delay (ms) = 40	set input 8 delay 40	73 65 74 20 69 6E 70 75 74 20 38 20 64 65 6C 61 79 20 34 30 0D 0A
841	DCA groups: Input DCA 1: Volume = {level} (0 to 100)	set input dca 1 vol {level}	the level in place of {level}
842	DCA groups: Input DCA 1: Volume = 0	set input dca 1 vol 0	73 65 74 20 69 6E 70 75 74 20 64 63 61 20 31 20 76 6F 6C 20 30 0D 0A
843	DCA groups: Input DCA 1: Volume = 50	set input dca 1 vol 50	73 65 74 20 69 6E 70 75 74 20 64 63 61 20 31 20 76 6F 6C 20 35 30 0D 0A
844	DCA groups: Input DCA 1: Volume = 100	set input dca 1 vol 100	73 65 74 20 69 6E 70 75 74 20 64 63 61 20 31 20 76 6F 6C 20 31 30 30 0D 0A
845	DCA groups: Input DCA 2: Volume = {level} (0 to 100)	set input dca 2 vol {level}	the level in place of {level}
846	DCA groups: Input DCA 2: Volume = 0	set input dca 2 vol 0	73 65 74 20 69 6E 70 75 74 20 64 63 61 20 32 20 76 6F 6C 20 30 0D 0A

847	DCA groups: Input DCA 2: Volume = 50	`set input dca 2 vol 50`	`73 65 74 20 69 6E 70 75 74 20 64 63 61 20 32 20 76 6F 6C 20 35 30 0D 0A`
848	DCA groups: Input DCA 2: Volume = 100	`set input dca 2 vol 100`	`73 65 74 20 69 6E 70 75 74 20 64 63 61 20 32 20 76 6F 6C 20 31 30 30 0D 0A`
849	DCA groups: Input DCA 3: Volume = {level} (0 to 100)	`set input dca 3 vol {level}`	`the level in place of {level}`
850	DCA groups: Input DCA 3: Volume = 0	`set input dca 3 vol 0`	`73 65 74 20 69 6E 70 75 74 20 64 63 61 20 33 20 76 6F 6C 20 30 0D 0A`
851	DCA groups: Input DCA 3: Volume = 50	`set input dca 3 vol 50`	`73 65 74 20 69 6E 70 75 74 20 64 63 61 20 33 20 76 6F 6C 20 35 30 0D 0A`
852	DCA groups: Input DCA 3: Volume = 100	`set input dca 3 vol 100`	`73 65 74 20 69 6E 70 75 74 20 64 63 61 20 33 20 76 6F 6C 20 31 30 30 0D 0A`
853	DCA groups: Input DCA 4: Volume = {level} (0 to 100)	`set input dca 4 vol {level}`	`the level in place of {level}`
854	DCA groups: Input DCA 4: Volume = 0	`set input dca 4 vol 0`	`73 65 74 20 69 6E 70 75 74 20 64 63 61 20 34 20 76 6F 6C 20 30 0D 0A`
855	DCA groups: Input DCA 4: Volume = 50	`set input dca 4 vol 50`	`73 65 74 20 69 6E 70 75 74 20 64 63 61 20 34 20 76 6F 6C 20 35 30 0D 0A`
856	DCA groups: Input DCA 4: Volume = 100	`set input dca 4 vol 100`	`73 65 74 20 69 6E 70 75 74 20 64 63 61 20 34 20 76 6F 6C 20 31 30 30 0D 0A`
857	DCA groups: Input DCA 1: Mute on	`set input dca 1 mute on`	`73 65 74 20 69 6E 70 75 74 20 64 63 61 20 31 20 6D 75 74 65 20 6F 6E 0D 0A`
858	DCA groups: Input DCA 1: Mute off	`set input dca 1 mute off`	`73 65 74 20 69 6E 70 75 74 20 64 63 61 20 31 20 6D 75 74 65 20 6F 66 66 0D 0A`
859	DCA groups: Input DCA 2: Mute on	`set input dca 2 mute on`	`73 65 74 20 69 6E 70 75 74 20 64 63 61 20 32 20 6D 75 74 65 20 6F 6E 0D 0A`
860	DCA groups: Input DCA 2: Mute off	`set input dca 2 mute off`	`73 65 74 20 69 6E 70 75 74 20 64 63 61 20 32 20 6D 75 74 65 20 6F 66 66 0D 0A`
861	DCA groups: Input DCA 3: Mute on	`set input dca 3 mute on`	`73 65 74 20 69 6E 70 75 74 20 64 63 61 20 33 20 6D 75 74 65 20 6F 6E 0D 0A`
862	DCA groups: Input DCA 3: Mute off	`set input dca 3 mute off`	`73 65 74 20 69 6E 70 75 74 20 64 63 61 20 33 20 6D 75 74 65 20 6F 66 66 0D 0A`
863	DCA groups: Input DCA 4: Mute on	`set input dca 4 mute on`	`73 65 74 20 69 6E 70 75 74 20 64 63 61 20 34 20 6D 75 74 65 20 6F 6E 0D 0A`
864	DCA groups: Input DCA 4: Mute off	`set input dca 4 mute off`	`73 65 74 20 69 6E 70 75 74 20 64 63 61 20 34 20 6D 75 74 65 20 6F 66 66 0D 0A`
865	DCA groups: Output DCA 1: Volume = {level} (0 to 100)	`set output dca 1 vol {level}`	`the level in place of {level}`
866	DCA groups: Output DCA 1: Volume = 0	`set output dca 1 vol 0`	`73 65 74 20 6F 75 74 70 75 74 20 64 63 61 20 31 20 76 6F 6C 20 30 0D 0A`
867	DCA groups: Output DCA 1: Volume = 50	`set output dca 1 vol 50`	`73 65 74 20 6F 75 74 70 75 74 20 64 63 61 20 31 20 76 6F 6C 20 35 30 0D 0A`
868	DCA groups: Output DCA 1: Volume = 100	`set output dca 1 vol 100`	`73 65 74 20 6F 75 74 70 75 74 20 64 63 61 20 31 20 76 6F 6C 20 31 30 30 0D 0A`
869	DCA groups: Output DCA 2: Volume = {level} (0 to 100)	`set output dca 2 vol {level}`	`the level in place of {level}`
870	DCA groups: Output DCA 2: Volume = 0	`set output dca 2 vol 0`	`73 65 74 20 6F 75 74 70 75 74 20 64 63 61 20 32 20 76 6F 6C 20 30 0D 0A`

871	DCA groups: Output DCA 2: Volume = 50	`set output dca 2 vol 50`	`73 65 74 20 6F 75 74 70 75 74 20 64 63 61 20 32 20 76 6F 6C 20 35 30 0D 0A`
872	DCA groups: Output DCA 2: Volume = 100	`set output dca 2 vol 100`	`73 65 74 20 6F 75 74 70 75 74 20 64 63 61 20 32 20 76 6F 6C 20 31 30 30 0D 0A`
873	DCA groups: Output DCA 3: Volume = {level} (0 to 100)	`set output dca 3 vol {level}`	`the level in place of {level}`
874	DCA groups: Output DCA 3: Volume = 0	`set output dca 3 vol 0`	`73 65 74 20 6F 75 74 70 75 74 20 64 63 61 20 33 20 76 6F 6C 20 30 0D 0A`
875	DCA groups: Output DCA 3: Volume = 50	`set output dca 3 vol 50`	`73 65 74 20 6F 75 74 70 75 74 20 64 63 61 20 33 20 76 6F 6C 20 35 30 0D 0A`
876	DCA groups: Output DCA 3: Volume = 100	`set output dca 3 vol 100`	`73 65 74 20 6F 75 74 70 75 74 20 64 63 61 20 33 20 76 6F 6C 20 31 30 30 0D 0A`
877	DCA groups: Output DCA 4: Volume = {level} (0 to 100)	`set output dca 4 vol {level}`	`the level in place of {level}`
878	DCA groups: Output DCA 4: Volume = 0	`set output dca 4 vol 0`	`73 65 74 20 6F 75 74 70 75 74 20 64 63 61 20 34 20 76 6F 6C 20 30 0D 0A`
879	DCA groups: Output DCA 4: Volume = 50	`set output dca 4 vol 50`	`73 65 74 20 6F 75 74 70 75 74 20 64 63 61 20 34 20 76 6F 6C 20 35 30 0D 0A`
880	DCA groups: Output DCA 4: Volume = 100	`set output dca 4 vol 100`	`73 65 74 20 6F 75 74 70 75 74 20 64 63 61 20 34 20 76 6F 6C 20 31 30 30 0D 0A`
881	DCA groups: Output DCA 1: Mute on	`set output dca 1 mute on`	`73 65 74 20 6F 75 74 70 75 74 20 64 63 61 20 31 20 6D 75 74 65 20 6F 6E 0D 0A`
882	DCA groups: Output DCA 1: Mute off	`set output dca 1 mute off`	`73 65 74 20 6F 75 74 70 75 74 20 64 63 61 20 31 20 6D 75 74 65 20 6F 66 66 0D 0A`
883	DCA groups: Output DCA 2: Mute on	`set output dca 2 mute on`	`73 65 74 20 6F 75 74 70 75 74 20 64 63 61 20 32 20 6D 75 74 65 20 6F 6E 0D 0A`
884	DCA groups: Output DCA 2: Mute off	`set output dca 2 mute off`	`73 65 74 20 6F 75 74 70 75 74 20 64 63 61 20 32 20 6D 75 74 65 20 6F 66 66 0D 0A`
885	DCA groups: Output DCA 3: Mute on	`set output dca 3 mute on`	`73 65 74 20 6F 75 74 70 75 74 20 64 63 61 20 33 20 6D 75 74 65 20 6F 6E 0D 0A`
886	DCA groups: Output DCA 3: Mute off	`set output dca 3 mute off`	`73 65 74 20 6F 75 74 70 75 74 20 64 63 61 20 33 20 6D 75 74 65 20 6F 66 66 0D 0A`
887	DCA groups: Output DCA 4: Mute on	`set output dca 4 mute on`	`73 65 74 20 6F 75 74 70 75 74 20 64 63 61 20 34 20 6D 75 74 65 20 6F 6E 0D 0A`
888	DCA groups: Output DCA 4: Mute off	`set output dca 4 mute off`	`73 65 74 20 6F 75 74 70 75 74 20 64 63 61 20 34 20 6D 75 74 65 20 6F 66 66 0D 0A`
889	EQ: Line out 1: EQ on on	`set output 1 eq active on`	`73 65 74 20 6F 75 74 70 75 74 20 31 20 65 71 20 61 63 74 69 76 65 20 6F 6E 0D 0A`
890	EQ: Line out 1: EQ on off	`set output 1 eq active off`	`73 65 74 20 6F 75 74 70 75 74 20 31 20 65 71 20 61 63 74 69 76 65 20 6F 66 66 0D 0A`
891	EQ: Line out 2: EQ on on	`set output 2 eq active on`	`73 65 74 20 6F 75 74 70 75 74 20 32 20 65 71 20 61 63 74 69 76 65 20 6F 6E 0D 0A`
892	EQ: Line out 2: EQ on off	`set output 2 eq active off`	`73 65 74 20 6F 75 74 70 75 74 20 32 20 65 71 20 61 63 74 69 76 65 20 6F 66 66 0D 0A`
893	EQ: Line out 3: EQ on on	`set output 3 eq active on`	`73 65 74 20 6F 75 74 70 75 74 20 33 20 65 71 20 61 63 74 69 76 65 20 6F 6E 0D 0A`
894	EQ: Line out 3: EQ on off	`set output 3 eq active off`	`73 65 74 20 6F 75 74 70 75 74 20 33 20 65 71 20 61 63 74 69 76 65 20 6F 66 66 0D 0A`

895	EQ: Line out 4: EQ on on	set output 4 eq active on	73 65 74 20 6F 75 74 70 75 74 20 34 20 65 71 20 61 63 74 69 76 65 20 6F 6E 0D 0A
896	EQ: Line out 4: EQ on off	set output 4 eq active off	73 65 74 20 6F 75 74 70 75 74 20 34 20 65 71 20 61 63 74 69 76 65 20 6F 66 66 0D 0A
897	EQ: Line out 5: EQ on on	set output 5 eq active on	73 65 74 20 6F 75 74 70 75 74 20 35 20 65 71 20 61 63 74 69 76 65 20 6F 6E 0D 0A
898	EQ: Line out 5: EQ on off	set output 5 eq active off	73 65 74 20 6F 75 74 70 75 74 20 35 20 65 71 20 61 63 74 69 76 65 20 6F 66 66 0D 0A
899	EQ: Line out 6: EQ on on	set output 6 eq active on	73 65 74 20 6F 75 74 70 75 74 20 36 20 65 71 20 61 63 74 69 76 65 20 6F 6E 0D 0A
900	EQ: Line out 6: EQ on off	set output 6 eq active off	73 65 74 20 6F 75 74 70 75 74 20 36 20 65 71 20 61 63 74 69 76 65 20 6F 66 66 0D 0A
901	EQ: Line out 7: EQ on on	set output 7 eq active on	73 65 74 20 6F 75 74 70 75 74 20 37 20 65 71 20 61 63 74 69 76 65 20 6F 6E 0D 0A
902	EQ: Line out 7: EQ on off	set output 7 eq active off	73 65 74 20 6F 75 74 70 75 74 20 37 20 65 71 20 61 63 74 69 76 65 20 6F 66 66 0D 0A
903	EQ: Line out 8: EQ on on	set output 8 eq active on	73 65 74 20 6F 75 74 70 75 74 20 38 20 65 71 20 61 63 74 69 76 65 20 6F 6E 0D 0A
904	EQ: Line out 8: EQ on off	set output 8 eq active off	73 65 74 20 6F 75 74 70 75 74 20 38 20 65 71 20 61 63 74 69 76 65 20 6F 66 66 0D 0A
905	EQ: Line out 1: Clear the EQ	set output 1 eq clear	73 65 74 20 6F 75 74 70 75 74 20 31 20 65 71 20 63 6C 65 61 72 0D 0A
906	EQ: Line out 2: Clear the EQ	set output 2 eq clear	73 65 74 20 6F 75 74 70 75 74 20 32 20 65 71 20 63 6C 65 61 72 0D 0A
907	EQ: Line out 3: Clear the EQ	set output 3 eq clear	73 65 74 20 6F 75 74 70 75 74 20 33 20 65 71 20 63 6C 65 61 72 0D 0A
908	EQ: Line out 4: Clear the EQ	set output 4 eq clear	73 65 74 20 6F 75 74 70 75 74 20 34 20 65 71 20 63 6C 65 61 72 0D 0A
909	EQ: Line out 5: Clear the EQ	set output 5 eq clear	73 65 74 20 6F 75 74 70 75 74 20 35 20 65 71 20 63 6C 65 61 72 0D 0A
910	EQ: Line out 6: Clear the EQ	set output 6 eq clear	73 65 74 20 6F 75 74 70 75 74 20 36 20 65 71 20 63 6C 65 61 72 0D 0A
911	EQ: Line out 7: Clear the EQ	set output 7 eq clear	73 65 74 20 6F 75 74 70 75 74 20 37 20 65 71 20 63 6C 65 61 72 0D 0A
912	EQ: Line out 8: Clear the EQ	set output 8 eq clear	73 65 74 20 6F 75 74 70 75 74 20 38 20 65 71 20 63 6C 65 61 72 0D 0A
913	Input EQ: Line in 1: EQ on on	set input 1 eq active on	73 65 74 20 69 6E 70 75 74 20 31 20 65 71 20 61 63 74 69 76 65 20 6F 6E 0D 0A
914	Input EQ: Line in 1: EQ on off	set input 1 eq active off	73 65 74 20 69 6E 70 75 74 20 31 20 65 71 20 61 63 74 69 76 65 20 6F 66 66 0D 0A
915	Input EQ: Line in 2: EQ on on	set input 2 eq active on	73 65 74 20 69 6E 70 75 74 20 32 20 65 71 20 61 63 74 69 76 65 20 6F 6E 0D 0A
916	Input EQ: Line in 2: EQ on off	set input 2 eq active off	73 65 74 20 69 6E 70 75 74 20 32 20 65 71 20 61 63 74 69 76 65 20 6F 66 66 0D 0A
917	Input EQ: Line in 3: EQ on on	set input 3 eq active on	73 65 74 20 69 6E 70 75 74 20 33 20 65 71 20 61 63 74 69 76 65 20 6F 6E 0D 0A
918	Input EQ: Line in 3: EQ on off	set input 3 eq active off	73 65 74 20 69 6E 70 75 74 20 33 20 65 71 20 61 63 74 69 76 65 20 6F 66 66 0D 0A

919	Input EQ: Line in 4: EQ on on	`set input 4 eq active on`	`73 65 74 20 69 6E 70 75 74 20 34 20 65 71 20 61 63 74 69 76 65 20 6F 6E 0D 0A`
920	Input EQ: Line in 4: EQ on off	`set input 4 eq active off`	`73 65 74 20 69 6E 70 75 74 20 34 20 65 71 20 61 63 74 69 76 65 20 6F 66 66 0D 0A`
921	Input EQ: Line in 5: EQ on on	`set input 5 eq active on`	`73 65 74 20 69 6E 70 75 74 20 35 20 65 71 20 61 63 74 69 76 65 20 6F 6E 0D 0A`
922	Input EQ: Line in 5: EQ on off	`set input 5 eq active off`	`73 65 74 20 69 6E 70 75 74 20 35 20 65 71 20 61 63 74 69 76 65 20 6F 66 66 0D 0A`
923	Input EQ: Line in 6: EQ on on	`set input 6 eq active on`	`73 65 74 20 69 6E 70 75 74 20 36 20 65 71 20 61 63 74 69 76 65 20 6F 6E 0D 0A`
924	Input EQ: Line in 6: EQ on off	`set input 6 eq active off`	`73 65 74 20 69 6E 70 75 74 20 36 20 65 71 20 61 63 74 69 76 65 20 6F 66 66 0D 0A`
925	Input EQ: Line in 7: EQ on on	`set input 7 eq active on`	`73 65 74 20 69 6E 70 75 74 20 37 20 65 71 20 61 63 74 69 76 65 20 6F 6E 0D 0A`
926	Input EQ: Line in 7: EQ on off	`set input 7 eq active off`	`73 65 74 20 69 6E 70 75 74 20 37 20 65 71 20 61 63 74 69 76 65 20 6F 66 66 0D 0A`
927	Input EQ: Line in 8: EQ on on	`set input 8 eq active on`	`73 65 74 20 69 6E 70 75 74 20 38 20 65 71 20 61 63 74 69 76 65 20 6F 6E 0D 0A`
928	Input EQ: Line in 8: EQ on off	`set input 8 eq active off`	`73 65 74 20 69 6E 70 75 74 20 38 20 65 71 20 61 63 74 69 76 65 20 6F 66 66 0D 0A`
929	Input EQ: Line in 1: Clear the EQ	`set input 1 eq clear`	`73 65 74 20 69 6E 70 75 74 20 31 20 65 71 20 63 6C 65 61 72 0D 0A`
930	Input EQ: Line in 2: Clear the EQ	`set input 2 eq clear`	`73 65 74 20 69 6E 70 75 74 20 32 20 65 71 20 63 6C 65 61 72 0D 0A`
931	Input EQ: Line in 3: Clear the EQ	`set input 3 eq clear`	`73 65 74 20 69 6E 70 75 74 20 33 20 65 71 20 63 6C 65 61 72 0D 0A`
932	Input EQ: Line in 4: Clear the EQ	`set input 4 eq clear`	`73 65 74 20 69 6E 70 75 74 20 34 20 65 71 20 63 6C 65 61 72 0D 0A`
933	Input EQ: Line in 5: Clear the EQ	`set input 5 eq clear`	`73 65 74 20 69 6E 70 75 74 20 35 20 65 71 20 63 6C 65 61 72 0D 0A`
934	Input EQ: Line in 6: Clear the EQ	`set input 6 eq clear`	`73 65 74 20 69 6E 70 75 74 20 36 20 65 71 20 63 6C 65 61 72 0D 0A`
935	Input EQ: Line in 7: Clear the EQ	`set input 7 eq clear`	`73 65 74 20 69 6E 70 75 74 20 37 20 65 71 20 63 6C 65 61 72 0D 0A`
936	Input EQ: Line in 8: Clear the EQ	`set input 8 eq clear`	`73 65 74 20 69 6E 70 75 74 20 38 20 65 71 20 63 6C 65 61 72 0D 0A`
937	Expander: Line in 1: Expander on on	`set input 1 exp active on`	`73 65 74 20 69 6E 70 75 74 20 31 20 65 78 70 20 61 63 74 69 76 65 20 6F 6E 0D 0A`
938	Expander: Line in 1: Expander on off	`set input 1 exp active off`	`73 65 74 20 69 6E 70 75 74 20 31 20 65 78 70 20 61 63 74 69 76 65 20 6F 66 66 0D 0A`
939	Expander: Line in 2: Expander on on	`set input 2 exp active on`	`73 65 74 20 69 6E 70 75 74 20 32 20 65 78 70 20 61 63 74 69 76 65 20 6F 6E 0D 0A`
940	Expander: Line in 2: Expander on off	`set input 2 exp active off`	`73 65 74 20 69 6E 70 75 74 20 32 20 65 78 70 20 61 63 74 69 76 65 20 6F 66 66 0D 0A`
941	Expander: Line in 3: Expander on on	`set input 3 exp active on`	`73 65 74 20 69 6E 70 75 74 20 33 20 65 78 70 20 61 63 74 69 76 65 20 6F 6E 0D 0A`
942	Expander: Line in 3: Expander on off	`set input 3 exp active off`	`73 65 74 20 69 6E 70 75 74 20 33 20 65 78 70 20 61 63 74 69 76 65 20 6F 66 66 0D 0A`

943	Expander: Line in 4: Expander on on	`set input 4 exp active on`	`73 65 74 20 69 6E 70 75 74 20 34 20 65 78 70 20 61 63 74 69 76 65 20 6F 6E 0D 0A`
944	Expander: Line in 4: Expander on off	`set input 4 exp active off`	`73 65 74 20 69 6E 70 75 74 20 34 20 65 78 70 20 61 63 74 69 76 65 20 6F 66 66 0D 0A`
945	Expander: Line in 5: Expander on on	`set input 5 exp active on`	`73 65 74 20 69 6E 70 75 74 20 35 20 65 78 70 20 61 63 74 69 76 65 20 6F 6E 0D 0A`
946	Expander: Line in 5: Expander on off	`set input 5 exp active off`	`73 65 74 20 69 6E 70 75 74 20 35 20 65 78 70 20 61 63 74 69 76 65 20 6F 66 66 0D 0A`
947	Expander: Line in 6: Expander on on	`set input 6 exp active on`	`73 65 74 20 69 6E 70 75 74 20 36 20 65 78 70 20 61 63 74 69 76 65 20 6F 6E 0D 0A`
948	Expander: Line in 6: Expander on off	`set input 6 exp active off`	`73 65 74 20 69 6E 70 75 74 20 36 20 65 78 70 20 61 63 74 69 76 65 20 6F 66 66 0D 0A`
949	Expander: Line in 7: Expander on on	`set input 7 exp active on`	`73 65 74 20 69 6E 70 75 74 20 37 20 65 78 70 20 61 63 74 69 76 65 20 6F 6E 0D 0A`
950	Expander: Line in 7: Expander on off	`set input 7 exp active off`	`73 65 74 20 69 6E 70 75 74 20 37 20 65 78 70 20 61 63 74 69 76 65 20 6F 66 66 0D 0A`
951	Expander: Line in 8: Expander on on	`set input 8 exp active on`	`73 65 74 20 69 6E 70 75 74 20 38 20 65 78 70 20 61 63 74 69 76 65 20 6F 6E 0D 0A`
952	Expander: Line in 8: Expander on off	`set input 8 exp active off`	`73 65 74 20 69 6E 70 75 74 20 38 20 65 78 70 20 61 63 74 69 76 65 20 6F 66 66 0D 0A`
953	Expander: Line in 1: Clear the expander	`set input 1 exp clear`	`73 65 74 20 69 6E 70 75 74 20 31 20 65 78 70 20 63 6C 65 61 72 0D 0A`
954	Expander: Line in 2: Clear the expander	`set input 2 exp clear`	`73 65 74 20 69 6E 70 75 74 20 32 20 65 78 70 20 63 6C 65 61 72 0D 0A`
955	Expander: Line in 3: Clear the expander	`set input 3 exp clear`	`73 65 74 20 69 6E 70 75 74 20 33 20 65 78 70 20 63 6C 65 61 72 0D 0A`
956	Expander: Line in 4: Clear the expander	`set input 4 exp clear`	`73 65 74 20 69 6E 70 75 74 20 34 20 65 78 70 20 63 6C 65 61 72 0D 0A`
957	Expander: Line in 5: Clear the expander	`set input 5 exp clear`	`73 65 74 20 69 6E 70 75 74 20 35 20 65 78 70 20 63 6C 65 61 72 0D 0A`
958	Expander: Line in 6: Clear the expander	`set input 6 exp clear`	`73 65 74 20 69 6E 70 75 74 20 36 20 65 78 70 20 63 6C 65 61 72 0D 0A`
959	Expander: Line in 7: Clear the expander	`set input 7 exp clear`	`73 65 74 20 69 6E 70 75 74 20 37 20 65 78 70 20 63 6C 65 61 72 0D 0A`
960	Expander: Line in 8: Clear the expander	`set input 8 exp clear`	`73 65 74 20 69 6E 70 75 74 20 38 20 65 78 70 20 63 6C 65 61 72 0D 0A`
961	Limiter: Line out 1: Limiter on on	`set output 1 lim active on`	`73 65 74 20 6F 75 74 70 75 74 20 31 20 6C 69 6D 20 61 63 74 69 76 65 20 6F 6E 0D 0A`
962	Limiter: Line out 1: Limiter on off	`set output 1 lim active off`	`73 65 74 20 6F 75 74 70 75 74 20 31 20 6C 69 6D 20 61 63 74 69 76 65 20 6F 66 66 0D 0A`
963	Limiter: Line out 2: Limiter on on	`set output 2 lim active on`	`73 65 74 20 6F 75 74 70 75 74 20 32 20 6C 69 6D 20 61 63 74 69 76 65 20 6F 6E 0D 0A`
964	Limiter: Line out 2: Limiter on off	`set output 2 lim active off`	`73 65 74 20 6F 75 74 70 75 74 20 32 20 6C 69 6D 20 61 63 74 69 76 65 20 6F 66 66 0D 0A`
965	Limiter: Line out 3: Limiter on on	`set output 3 lim active on`	`73 65 74 20 6F 75 74 70 75 74 20 33 20 6C 69 6D 20 61 63 74 69 76 65 20 6F 6E 0D 0A`
966	Limiter: Line out 3: Limiter on off	`set output 3 lim active off`	`73 65 74 20 6F 75 74 70 75 74 20 33 20 6C 69 6D 20 61 63 74 69 76 65 20 6F 66 66 0D 0A`

967	Limiter: Line out 4: Limiter on on	`set output 4 lim active on`	`73 65 74 20 6F 75 74 70 75 74 20 34 20 6C 69 6D 20 61 63 74 69 76 65 20 6F 6E 0D 0A`
968	Limiter: Line out 4: Limiter on off	`set output 4 lim active off`	`73 65 74 20 6F 75 74 70 75 74 20 34 20 6C 69 6D 20 61 63 74 69 76 65 20 6F 66 66 0D 0A`
969	Limiter: Line out 5: Limiter on on	`set output 5 lim active on`	`73 65 74 20 6F 75 74 70 75 74 20 35 20 6C 69 6D 20 61 63 74 69 76 65 20 6F 6E 0D 0A`
970	Limiter: Line out 5: Limiter on off	`set output 5 lim active off`	`73 65 74 20 6F 75 74 70 75 74 20 35 20 6C 69 6D 20 61 63 74 69 76 65 20 6F 66 66 0D 0A`
971	Limiter: Line out 6: Limiter on on	`set output 6 lim active on`	`73 65 74 20 6F 75 74 70 75 74 20 36 20 6C 69 6D 20 61 63 74 69 76 65 20 6F 6E 0D 0A`
972	Limiter: Line out 6: Limiter on off	`set output 6 lim active off`	`73 65 74 20 6F 75 74 70 75 74 20 36 20 6C 69 6D 20 61 63 74 69 76 65 20 6F 66 66 0D 0A`
973	Limiter: Line out 7: Limiter on on	`set output 7 lim active on`	`73 65 74 20 6F 75 74 70 75 74 20 37 20 6C 69 6D 20 61 63 74 69 76 65 20 6F 6E 0D 0A`
974	Limiter: Line out 7: Limiter on off	`set output 7 lim active off`	`73 65 74 20 6F 75 74 70 75 74 20 37 20 6C 69 6D 20 61 63 74 69 76 65 20 6F 66 66 0D 0A`
975	Limiter: Line out 8: Limiter on on	`set output 8 lim active on`	`73 65 74 20 6F 75 74 70 75 74 20 38 20 6C 69 6D 20 61 63 74 69 76 65 20 6F 6E 0D 0A`
976	Limiter: Line out 8: Limiter on off	`set output 8 lim active off`	`73 65 74 20 6F 75 74 70 75 74 20 38 20 6C 69 6D 20 61 63 74 69 76 65 20 6F 66 66 0D 0A`
977	Limiter: Line out 1: Clear the limiter	`set output 1 lim clear`	`73 65 74 20 6F 75 74 70 75 74 20 31 20 6C 69 6D 20 63 6C 65 61 72 0D 0A`
978	Limiter: Line out 2: Clear the limiter	`set output 2 lim clear`	`73 65 74 20 6F 75 74 70 75 74 20 32 20 6C 69 6D 20 63 6C 65 61 72 0D 0A`
979	Limiter: Line out 3: Clear the limiter	`set output 3 lim clear`	`73 65 74 20 6F 75 74 70 75 74 20 33 20 6C 69 6D 20 63 6C 65 61 72 0D 0A`
980	Limiter: Line out 4: Clear the limiter	`set output 4 lim clear`	`73 65 74 20 6F 75 74 70 75 74 20 34 20 6C 69 6D 20 63 6C 65 61 72 0D 0A`
981	Limiter: Line out 5: Clear the limiter	`set output 5 lim clear`	`73 65 74 20 6F 75 74 70 75 74 20 35 20 6C 69 6D 20 63 6C 65 61 72 0D 0A`
982	Limiter: Line out 6: Clear the limiter	`set output 6 lim clear`	`73 65 74 20 6F 75 74 70 75 74 20 36 20 6C 69 6D 20 63 6C 65 61 72 0D 0A`
983	Limiter: Line out 7: Clear the limiter	`set output 7 lim clear`	`73 65 74 20 6F 75 74 70 75 74 20 37 20 6C 69 6D 20 63 6C 65 61 72 0D 0A`
984	Limiter: Line out 8: Clear the limiter	`set output 8 lim clear`	`73 65 74 20 6F 75 74 70 75 74 20 38 20 6C 69 6D 20 63 6C 65 61 72 0D 0A`
985	Presets: Presets 1	`set preset recall 1`	`73 65 74 20 70 72 65 73 65 74 20 72 65 63 61 6C 6C 20 31 0D 0A`
986	Presets: Presets 2	`set preset recall 2`	`73 65 74 20 70 72 65 73 65 74 20 72 65 63 61 6C 6C 20 32 0D 0A`
987	Presets: Presets 3	`set preset recall 3`	`73 65 74 20 70 72 65 73 65 74 20 72 65 63 61 6C 6C 20 33 0D 0A`
988	Presets: Presets 4	`set preset recall 4`	`73 65 74 20 70 72 65 73 65 74 20 72 65 63 61 6C 6C 20 34 0D 0A`
989	Presets: Presets 5	`set preset recall 5`	`73 65 74 20 70 72 65 73 65 74 20 72 65 63 61 6C 6C 20 35 0D 0A`
990	Presets: Presets 6	`set preset recall 6`	`73 65 74 20 70 72 65 73 65 74 20 72 65 63 61 6C 6C 20 36 0D 0A`

991	Presets: Presets 7	`set preset recall 7`	`73 65 74 20 70 72 65 73 65 74 20 72 65 63 61 6C 6C 20 37 0D 0A`
992	Presets: Presets 8	`set preset recall 8`	`73 65 74 20 70 72 65 73 65 74 20 72 65 63 61 6C 6C 20 38 0D 0A`
993	Presets: Save 1	`set preset save 1`	`73 65 74 20 70 72 65 73 65 74 20 73 61 76 65 20 31 0D 0A`
994	Presets: Save 2	`set preset save 2`	`73 65 74 20 70 72 65 73 65 74 20 73 61 76 65 20 32 0D 0A`
995	Presets: Save 3	`set preset save 3`	`73 65 74 20 70 72 65 73 65 74 20 73 61 76 65 20 33 0D 0A`
996	Presets: Save 4	`set preset save 4`	`73 65 74 20 70 72 65 73 65 74 20 73 61 76 65 20 34 0D 0A`
997	Presets: Save 5	`set preset save 5`	`73 65 74 20 70 72 65 73 65 74 20 73 61 76 65 20 35 0D 0A`
998	Presets: Save 6	`set preset save 6`	`73 65 74 20 70 72 65 73 65 74 20 73 61 76 65 20 36 0D 0A`
999	Presets: Save 7	`set preset save 7`	`73 65 74 20 70 72 65 73 65 74 20 73 61 76 65 20 37 0D 0A`
1000	Presets: Save 8	`set preset save 8`	`73 65 74 20 70 72 65 73 65 74 20 73 61 76 65 20 38 0D 0A`
1001	Presets: Clear a preset 1	`set preset clear 1`	`73 65 74 20 70 72 65 73 65 74 20 63 6C 65 61 72 20 31 0D 0A`
1002	Presets: Clear a preset 2	`set preset clear 2`	`73 65 74 20 70 72 65 73 65 74 20 63 6C 65 61 72 20 32 0D 0A`
1003	Presets: Clear a preset 3	`set preset clear 3`	`73 65 74 20 70 72 65 73 65 74 20 63 6C 65 61 72 20 33 0D 0A`
1004	Presets: Clear a preset 4	`set preset clear 4`	`73 65 74 20 70 72 65 73 65 74 20 63 6C 65 61 72 20 34 0D 0A`
1005	Presets: Clear a preset 5	`set preset clear 5`	`73 65 74 20 70 72 65 73 65 74 20 63 6C 65 61 72 20 35 0D 0A`
1006	Presets: Clear a preset 6	`set preset clear 6`	`73 65 74 20 70 72 65 73 65 74 20 63 6C 65 61 72 20 36 0D 0A`
1007	Presets: Clear a preset 7	`set preset clear 7`	`73 65 74 20 70 72 65 73 65 74 20 63 6C 65 61 72 20 37 0D 0A`
1008	Presets: Clear a preset 8	`set preset clear 8`	`73 65 74 20 70 72 65 73 65 74 20 63 6C 65 61 72 20 38 0D 0A`
1009	System: Standby after no sound (min, 0 = never) = {level} (0 to 100)	`set auto stb {level}`	`the level in place of {level}`
1010	System: Standby after no sound (min, 0 = never) = 0	`set auto stb 0`	`73 65 74 20 61 75 74 6F 20 73 74 62 20 30 0D 0A`
1011	System: Standby after no sound (min, 0 = never) = 50	`set auto stb 50`	`73 65 74 20 61 75 74 6F 20 73 74 62 20 35 30 0D 0A`
1012	System: Standby after no sound (min, 0 = never) = 100	`set auto stb 100`	`73 65 74 20 61 75 74 6F 20 73 74 62 20 31 30 30 0D 0A`
1013	System: Standby kind = Standby	`set standby 1`	`73 65 74 20 73 74 61 6E 64 62 79 20 31 0D 0A`
1014	System: Standby kind = Sleep	`set standby 2`	`73 65 74 20 73 74 61 6E 64 62 79 20 32 0D 0A`

1015	**Power: Power On**	`power on`	`70 6F 77 65 72 20 6F 6E 0D 0A`
1016	**Power: Power Standby**	`power off`	`70 6F 77 65 72 20 6F 66 66 0D 0A`

4. READING THE UNIT BACK

Send these to read the unit back (on a timer, or after a change).

#	String	Bytes (hex)	The reply gives
1	`get input dca 1 vol`	`67 65 74 20 69 6E 70 75 74 20 64 63 61 20 31 20 76 6F 6C 0D 0A`	Volume
2	`get input dca 2 vol`	`67 65 74 20 69 6E 70 75 74 20 64 63 61 20 32 20 76 6F 6C 0D 0A`	Volume
3	`get input dca 3 vol`	`67 65 74 20 69 6E 70 75 74 20 64 63 61 20 33 20 76 6F 6C 0D 0A`	Volume
4	`get input dca 4 vol`	`67 65 74 20 69 6E 70 75 74 20 64 63 61 20 34 20 76 6F 6C 0D 0A`	Volume
5	`get input dca 1 mute`	`67 65 74 20 69 6E 70 75 74 20 64 63 61 20 31 20 6D 75 74 65 0D 0A`	Mute
6	`get input dca 2 mute`	`67 65 74 20 69 6E 70 75 74 20 64 63 61 20 32 20 6D 75 74 65 0D 0A`	Mute
7	`get input dca 3 mute`	`67 65 74 20 69 6E 70 75 74 20 64 63 61 20 33 20 6D 75 74 65 0D 0A`	Mute
8	`get input dca 4 mute`	`67 65 74 20 69 6E 70 75 74 20 64 63 61 20 34 20 6D 75 74 65 0D 0A`	Mute
9	`get output dca 1 vol`	`67 65 74 20 6F 75 74 70 75 74 20 64 63 61 20 31 20 76 6F 6C 0D 0A`	Volume
10	`get output dca 2 vol`	`67 65 74 20 6F 75 74 70 75 74 20 64 63 61 20 32 20 76 6F 6C 0D 0A`	Volume
11	`get output dca 3 vol`	`67 65 74 20 6F 75 74 70 75 74 20 64 63 61 20 33 20 76 6F 6C 0D 0A`	Volume
12	`get output dca 4 vol`	`67 65 74 20 6F 75 74 70 75 74 20 64 63 61 20 34 20 76 6F 6C 0D 0A`	Volume

13	`get output dca 1 mute`	`67 65 74 20 6F 75 74 70 75 74 20 64 63 61 20 31 20 6D 75 74 65 0D 0A`	Mute
14	`get output dca 2 mute`	`67 65 74 20 6F 75 74 70 75 74 20 64 63 61 20 32 20 6D 75 74 65 0D 0A`	Mute
15	`get output dca 3 mute`	`67 65 74 20 6F 75 74 70 75 74 20 64 63 61 20 33 20 6D 75 74 65 0D 0A`	Mute
16	`get output dca 4 mute`	`67 65 74 20 6F 75 74 70 75 74 20 64 63 61 20 34 20 6D 75 74 65 0D 0A`	Mute
17	`get output 1 eq active`	`67 65 74 20 6F 75 74 70 75 74 20 31 20 65 71 20 61 63 74 69 76 65 0D 0A`	EQ on
18	`get output 2 eq active`	`67 65 74 20 6F 75 74 70 75 74 20 32 20 65 71 20 61 63 74 69 76 65 0D 0A`	EQ on
19	`get output 3 eq active`	`67 65 74 20 6F 75 74 70 75 74 20 33 20 65 71 20 61 63 74 69 76 65 0D 0A`	EQ on
20	`get output 4 eq active`	`67 65 74 20 6F 75 74 70 75 74 20 34 20 65 71 20 61 63 74 69 76 65 0D 0A`	EQ on
21	`get output 5 eq active`	`67 65 74 20 6F 75 74 70 75 74 20 35 20 65 71 20 61 63 74 69 76 65 0D 0A`	EQ on
22	`get output 6 eq active`	`67 65 74 20 6F 75 74 70 75 74 20 36 20 65 71 20 61 63 74 69 76 65 0D 0A`	EQ on
23	`get output 7 eq active`	`67 65 74 20 6F 75 74 70 75 74 20 37 20 65 71 20 61 63 74 69 76 65 0D 0A`	EQ on
24	`get output 8 eq active`	`67 65 74 20 6F 75 74 70 75 74 20 38 20 65 71 20 61 63 74 69 76 65 0D 0A`	EQ on
25	`get input 1 eq active`	`67 65 74 20 69 6E 70 75 74 20 31 20 65 71 20 61 63 74 69 76 65 0D 0A`	EQ on

26	get input 2 eq active	67 65 74 20 69 6E 70 75 74 20 32 20 65 71 20 61 63 74 69 76 65 0D 0A	EQ on
27	get input 3 eq active	67 65 74 20 69 6E 70 75 74 20 33 20 65 71 20 61 63 74 69 76 65 0D 0A	EQ on
28	get input 4 eq active	67 65 74 20 69 6E 70 75 74 20 34 20 65 71 20 61 63 74 69 76 65 0D 0A	EQ on
29	get input 5 eq active	67 65 74 20 69 6E 70 75 74 20 35 20 65 71 20 61 63 74 69 76 65 0D 0A	EQ on
30	get input 6 eq active	67 65 74 20 69 6E 70 75 74 20 36 20 65 71 20 61 63 74 69 76 65 0D 0A	EQ on
31	get input 7 eq active	67 65 74 20 69 6E 70 75 74 20 37 20 65 71 20 61 63 74 69 76 65 0D 0A	EQ on
32	get input 8 eq active	67 65 74 20 69 6E 70 75 74 20 38 20 65 71 20 61 63 74 69 76 65 0D 0A	EQ on
33	get input 1 exp active	67 65 74 20 69 6E 70 75 74 20 31 20 65 78 70 20 61 63 74 69 76 65 0D 0A	Expander on
34	get input 2 exp active	67 65 74 20 69 6E 70 75 74 20 32 20 65 78 70 20 61 63 74 69 76 65 0D 0A	Expander on
35	get input 3 exp active	67 65 74 20 69 6E 70 75 74 20 33 20 65 78 70 20 61 63 74 69 76 65 0D 0A	Expander on
36	get input 4 exp active	67 65 74 20 69 6E 70 75 74 20 34 20 65 78 70 20 61 63 74 69 76 65 0D 0A	Expander on
37	get input 5 exp active	67 65 74 20 69 6E 70 75 74 20 35 20 65 78 70 20 61 63 74 69 76 65 0D 0A	Expander on
38	get input 6 exp active	67 65 74 20 69 6E 70 75 74 20 36 20 65 78 70 20 61 63 74 69 76 65 0D 0A	Expander on

39	`get input 7 exp active`	`67 65 74 20 69 6E 70 75 74 20 37 20 65 78 70 20 61 63 74 69 76 65 0D 0A`	Expander on
40	`get input 8 exp active`	`67 65 74 20 69 6E 70 75 74 20 38 20 65 78 70 20 61 63 74 69 76 65 0D 0A`	Expander on
41	`get input 1 exp setting`	`67 65 74 20 69 6E 70 75 74 20 31 20 65 78 70 20 73 65 74 74 69 6E 67 0D 0A`	Expander setting
42	`get input 2 exp setting`	`67 65 74 20 69 6E 70 75 74 20 32 20 65 78 70 20 73 65 74 74 69 6E 67 0D 0A`	Expander setting
43	`get input 3 exp setting`	`67 65 74 20 69 6E 70 75 74 20 33 20 65 78 70 20 73 65 74 74 69 6E 67 0D 0A`	Expander setting
44	`get input 4 exp setting`	`67 65 74 20 69 6E 70 75 74 20 34 20 65 78 70 20 73 65 74 74 69 6E 67 0D 0A`	Expander setting
45	`get input 5 exp setting`	`67 65 74 20 69 6E 70 75 74 20 35 20 65 78 70 20 73 65 74 74 69 6E 67 0D 0A`	Expander setting
46	`get input 6 exp setting`	`67 65 74 20 69 6E 70 75 74 20 36 20 65 78 70 20 73 65 74 74 69 6E 67 0D 0A`	Expander setting
47	`get input 7 exp setting`	`67 65 74 20 69 6E 70 75 74 20 37 20 65 78 70 20 73 65 74 74 69 6E 67 0D 0A`	Expander setting
48	`get input 8 exp setting`	`67 65 74 20 69 6E 70 75 74 20 38 20 65 78 70 20 73 65 74 74 69 6E 67 0D 0A`	Expander setting
49	`get output 1 lim active`	`67 65 74 20 6F 75 74 70 75 74 20 31 20 6C 69 6D 20 61 63 74 69 76 65 0D 0A`	Limiter on
50	`get output 2 lim active`	`67 65 74 20 6F 75 74 70 75 74 20 32 20 6C 69 6D 20 61 63 74 69 76 65 0D 0A`	Limiter on
51	`get output 3 lim active`	`67 65 74 20 6F 75 74 70 75 74 20 33 20 6C 69 6D 20 61 63 74 69 76 65 0D 0A`	Limiter on

52	get output 4 lim active	67 65 74 20 6F 75 74 70 75 74 20 34 20 6C 69 6D 20 61 63 74 69 76 65 0D 0A	Limiter on
53	get output 5 lim active	67 65 74 20 6F 75 74 70 75 74 20 35 20 6C 69 6D 20 61 63 74 69 76 65 0D 0A	Limiter on
54	get output 6 lim active	67 65 74 20 6F 75 74 70 75 74 20 36 20 6C 69 6D 20 61 63 74 69 76 65 0D 0A	Limiter on
55	get output 7 lim active	67 65 74 20 6F 75 74 70 75 74 20 37 20 6C 69 6D 20 61 63 74 69 76 65 0D 0A	Limiter on
56	get output 8 lim active	67 65 74 20 6F 75 74 70 75 74 20 38 20 6C 69 6D 20 61 63 74 69 76 65 0D 0A	Limiter on
57	get output 1 lim setting	67 65 74 20 6F 75 74 70 75 74 20 31 20 6C 69 6D 20 73 65 74 74 69 6E 67 0D 0A	Limiter setting
58	get output 2 lim setting	67 65 74 20 6F 75 74 70 75 74 20 32 20 6C 69 6D 20 73 65 74 74 69 6E 67 0D 0A	Limiter setting
59	get output 3 lim setting	67 65 74 20 6F 75 74 70 75 74 20 33 20 6C 69 6D 20 73 65 74 74 69 6E 67 0D 0A	Limiter setting
60	get output 4 lim setting	67 65 74 20 6F 75 74 70 75 74 20 34 20 6C 69 6D 20 73 65 74 74 69 6E 67 0D 0A	Limiter setting
61	get output 5 lim setting	67 65 74 20 6F 75 74 70 75 74 20 35 20 6C 69 6D 20 73 65 74 74 69 6E 67 0D 0A	Limiter setting
62	get output 6 lim setting	67 65 74 20 6F 75 74 70 75 74 20 36 20 6C 69 6D 20 73 65 74 74 69 6E 67 0D 0A	Limiter setting
63	get output 7 lim setting	67 65 74 20 6F 75 74 70 75 74 20 37 20 6C 69 6D 20 73 65 74 74 69 6E 67 0D 0A	Limiter setting
64	get output 8 lim setting	67 65 74 20 6F 75 74 70 75 74 20 38 20 6C 69 6D 20 73 65 74 74 69 6E 67 0D 0A	Limiter setting

5. TROUBLESHOOTING

Nothing happens.

Check the unit's IP address and that TCP 8000 is open between the Tesira server and the unit (same network or VLAN, or routed; no firewall in between). Check the line ending is sent after each string.

The unit answers with an error.
The string or its value is not one it takes, or the unit is in standby: turn it on first.